


High power and Programmable Switching Power supply

IT6500C Series User Manual



Model: IT6512C/IT6513C/IT6514C/IT6515C/IT6516C/IT6517C/
IT6522C/IT6523C/IT6524C/IT6525C/IT6526C/IT6527C/
IT6532C/IT6533C/IT6534C/IT6535C/IT6536C/IT6537C/
IT6542C/IT6543C/IT6544C/IT6545C/IT6546C/IT6547C/
IT6552C/IT6553C/IT6554C/IT6555C/IT6556C/IT6557C/
IT6562C/IT6563C/IT6564C/IT6565C/IT6566C/IT6567C/
IT6572C/IT6573C/IT6574C/IT6575C/IT6576C/IT6577C/
IT6582C/IT6583C/IT6584C/IT6585C/IT6586C/IT6587C/
IT6592C/IT6593C/IT6594C/IT6595C/IT6596C/IT6597C

Version: 4.5

Notices

© Itech Electronic, Co., Ltd. 2018

No part of this manual may be reproduced in any form or by any means (including electronic storage and retrieval or translation into a foreign language) without prior permission and written consent from Itech Electronic, Co., Ltd. as governed by international copyright laws.

Manual Part Number

IT6500C-402248

Revision

4th Edition: July, 24, 2018

Itech Electronic, Co., Ltd.

Trademarks

Pentium is U.S. registered trademarks of Intel Corporation.

Microsoft, Visual Studio, Windows and MS Windows are registered trademarks of Microsoft Corporation in the United States and/or other countries and regions.

Warranty

The materials contained in this document are provided “as is”, and is subject to change, without prior notice, in future editions. Further, to the maximum extent permitted by applicable laws, ITECH disclaims all warrants, either express or implied, with regard to this manual and any information contained herein, including but not limited to the implied warranties of merchantability and fitness for a particular purpose. ITECH shall not be held liable for errors or for incidental or indirect damages in connection with the furnishing, use or application of this document or of any information contained herein. Should ITECH and the user enter into a separate written agreement with warranty terms covering the materials in this document that conflict with these terms, the warranty terms in the separate agreement shall prevail.

Technology Licenses

The hardware and/or software described herein are furnished under a license and may be used or copied only in accordance with the terms of such license.

Restricted Rights Legend

Restricted permissions of the U.S. government. Permissions for software and technical data which are authorized to the U.S. Government only include those for custom provision to end users. ITECH provides this customary commercial license in software and technical data pursuant to FAR 12.211 (Technical Data) and 12.212 (Computer Software) and, for the Department of Defense, DFARS 252.227-7015 (Technical Data – Commercial Items) and DFARS 227.7202-3 (Rights in Commercial Computer Software or Computer Software Documentation).

Safety Notices

CAUTION

A CAUTION sign denotes a hazard. It calls attention to an operating procedure or practice that, if not correctly performed or adhered to, could result in damage to the product or loss of important data. Do not proceed beyond a CAUTION sign until the indicated conditions are fully understood and met.

WARNING

A WARNING sign denotes a hazard. It calls attention to an operating procedure or practice that, if not correctly performed or adhered to, could result in personal injury or death. Do not proceed beyond a WARNING sign until the indicated conditions are fully understood and met.



NOTE

A NOTE sign denotes important hint. It calls attention to tips or supplementary information that is essential for users to refer to.

Quality Certification and Assurance

We certify that IT6500C series power supply meets all the published specifications at time of shipment from the factory.

Warranty

ITECH warrants that the product will be free from defects in material and workmanship under normal use for a period of one (1) year from the date of delivery (except those described in the Limitation of Warranty below).

For warranty service or repair, the product must be returned to a service center designated by ITECH.

- The product returned to ITECH for warranty service must be shipped PREPAID. And ITECH will pay for return of the product to customer.
- If the product is returned to ITECH for warranty service from overseas, all the freights, duties and other taxes shall be on the account of customer.

Limitation of Warranty

This Warranty will be rendered invalid if the product is:

- Damaged resulting from customer-wired circuits or customer-supplied parts or accessories;
- Modified or repaired by customer without authorization;
- Damaged resulting from customer-wired circuits or use in an environment not designated by us;
- The product model or serial number is altered, deleted, removed or made illegible by customer;
- Damaged as a result of accidents, including but not limited to lightning, moisture, fire, improper use or negligence.

Safety Symbols

	Direct current		ON (power)
	Alternating current		OFF (power)
	Both direct and alternating current		Power-on state
	Chassis (earth ground) symbol.		Power-off state
	Earth (ground) terminal		Reference terminal
	Caution		Positive terminal
	Warning (refer to this manual for specific Warning or Caution information)		Negative terminal
	A chassis terminal	-	-

Safety Precautions

The following safety precautions must be observed during all phases of operation of this instrument. Failure to comply with these precautions or specific warnings elsewhere in this manual will constitute a default under safety standards of design, manufacture and intended use of the instrument. ITECH assumes no liability for the customer's failure to comply with these precautions.

WARNING

- Do not use the instrument if it is damaged. Before operation, check the casing to see whether it cracks. Do not operate the instrument in the presence of inflammable gasses, vapors or dusts.
- The power supply is provided with a power line during delivery and should be connected to junction box. Before operation, be sure that the power supply is well grounded. Make sure to use the power cord supplied by ITECH.
- Check all marks on the instrument before connecting the instrument to power supply.
- Use electric wires of appropriate load. All loading wires should be capable of bearing maximum short-circuit of electronic load without overheating. If there are multiple loads, each pair of the load power cord must be carry out the full rated short-circuit output current of the power securely.
- Make sure to follow the manual description for wiring.
- Ensure the voltage fluctuation of mains supply is less than 10% of the working voltage range in order to reduce risks of fire and electric shock.
- Do not install alternative parts on the instrument or perform any unauthorized modification.
- Do not use the instrument if the detachable cover is removed or loosen.
- To prevent the possibility of accidental injuries, be sure to use the power adapter supplied by the manufacturer only.
- We do not accept responsibility for any direct or indirect financial damage or loss of profit that might occur when using the instrument.
- This instrument is used for industrial purposes. Do not apply this product to IT power supply system.
- Never use the instrument with a life-support system or any other equipment subject to safety requirements.

CAUTION

- Failure to use the instrument as directed by the manufacturer may render its protective features void.
- Always clean the casing with a dry cloth. Do not clean the internals.
- Make sure the vent hole is always unblocked.

Environmental Conditions

The instrument is designed for indoor use and an area with low condensation. The table below shows the general environmental requirements for the instrument.

Environmental Conditions	Requirements
--------------------------	--------------

Operating temperature	0°C to 40°C
Operating humidity	20%-80% (non-condensation)
Storage temperature	-10°C to 70 °C
Altitude	Operating up to 2,000 meters
Installation category	II
Pollution degree	Pollution degree 2


Note

To make accurate measurements, allow the instrument to warm up for 30 min.

Regulatory Markings

	The CE mark indicates that the product complies with all the relevant European legal directives. The specific year (if any) affixed refers to the year when the design was approved.
	The instrument complies with the WEEE Directive (2002/96/EC) marking requirement. This affix product label indicates that you must not discard the electrical/electronic product in domestic household waste.
	This symbol indicates the time period during which no hazardous or toxic substances are expected to leak or deteriorate during normal use. The expected useful life of the product is 10 years. The product can be used safely during the 10-year Environment Friendly Use Period (EFUP). Upon expiration of the EFUP, the product must be immediately recycled.

Waste Electrical and Electronic Equipment (WEEE) Directive



2002/96/EC Waste Electrical and Electronic Equipment (WEEE) Directive

This product complies with the WEEE Directive (2002/96/EC) marking requirement. This affix product label indicates that you must not discard the electrical/electronic product in domestic household waste.

Product Category

With reference to the equipment classifications described in the Annex 1 of the WEEE Directive, this instrument is classified as a "Monitoring and Control Instrument".

To return this unwanted instrument, contact your nearest ITECH office.

Compliance Information

Complies with the essential requirements of the following applicable European Directives, and carries the CE marking accordingly:

- Electromagnetic Compatibility (EMC) Directive 2014/30/EU
- Low-Voltage Directive (Safety) 2014/35/EU

Conforms with the following product standards:

EMC Standard

IEC 61326-1:2012/ EN 61326-1:2013 ¹²³

Reference Standards

CISPR 11:2009+A1:2010/ EN 55011:2009+A1:2010 (Group 1, Class A)
IEC 61000-4-2:2008/ EN 61000-4-2:2009
IEC 61000-4-3:2006+A1:2007+A2:2010/ EN 61000-4-3:2006+A1:2008+A2:2010
IEC 61000-4-4:2004+A1:2010/ EN 61000-4-4:2004+A1:2010
IEC 61000-4-5:2005/ EN 61000-4-5:2006
IEC 61000-4-6:2008/ EN 61000-4-6:2009
IEC 61000-4-11:2004/ EN 61000-4-11:2004

1. The product is intended for use in non-residential/non-domestic environments. Use of the product in residential/domestic environments may cause electromagnetic interference.
2. Connection of the instrument to a test object may produce radiations beyond the specified limit.
3. Use high-performance shielded interface cable to ensure conformity with the EMC standards listed above.

Safety Standard

IEC 61010-1:2010/ EN 61010-1:2010

Content

Quality Certification and Assurance	1
Warranty.....	1
Limitation of Warranty	1
Safety Symbols	1
Safety Precautions	2
Environmental Conditions	2
Regulatory Markings	3
Waste Electrical and Electronic Equipment (WEEE) Directive	3
Compliance Information.....	4
Chapter1 Inspection and Installation	1
1.1 Verifying the Shipment.....	1
1.2 Instrument Size Introduction.....	1
1.3 Connecting the Power Cord.....	9
1.4 Connecting Test Lines (Optional).....	12
Chapter2 Quick Start.....	13
2.1 Brief Introduction	13
2.2 Front Panel Introduction	15
2.3 Keyboard Introduction	15
2.4 Rotary Knob and Coarse/Fine Button Introduction.....	16
2.5 VFD Indicator Lamps Description	17
2.6 Rear Panel Introduction.....	17
2.7 Power-on Selftest	17
Chapter3 Function and Features	20
3.1 Setting Voltage	20
3.2 Setting Current	20
3.3 Setting Power	20
3.4 Output On/Off Button	21
3.5 Switching Setting Value and Actual Value	21
3.6 Switching Local/Remote Mode.....	21
3.7 Key Lock Function.....	21
3.8 Save/Recall Operation	21
3.9 System Menu.....	22
3.10 Setup Menu	26
3.11 Setting Output Rise Time/Fall Time.....	28
3.12 Protection Function.....	28
3.13 Setting Maximum and Minimum Values	30
3.14 Load Function.....	31
3.15 Charge Protection.....	34
3.16 Static Protection Function of Battery	34
3.17 Internal Resistance Setting	35
3.18 CC/CV Priority.....	35
3.19 LIST Operation	37
3.20 PV Simulation	40
3.21 Built-in Waveform	42
3.21.1 Automotive Starting Waveform.....	45
3.21.2 simulate the waveform to verify the anti-interference performance of the automotive electronics' products	46
3.21.3 42V Road vehicles — Electrical and electronic equipment for a supply voltage of 42 V — Electrical loads.....	52
3.21.4 SAEJ1113-11 Waveform protocol	54
3.21.5 LV124	55
3.22 DC Internal Resistance Measure.....	59
3.23 Parallel Operation.....	60
3.24 Rear Panel Terminal Functions	61

3.25 Analogue Interface (Enhanced Isolation)	63
Chapter4 Remote Control	69
4.1 RS232 Interface	69
4.2 USB Interface	70
4.3 GPIB Interface.....	70
4.4 LAN Interface	71
4.5 CAN Communication Port.....	71
Chapter5 Specification	73
5.1 Main technical parameters.....	73
5.2 Supplemental characteristics	153
Appendix	154
Specifications of Red and Black Test Lines.....	154
How to avoid it couldn't start when test battery	154

Chapter1 Inspection and Installation

1.1 Verifying the Shipment

Unpack the box and check the contents before operating the instrument. If wrong items have been delivered, if items are missing, or if there is a defect with the appearance of the items, contact the dealer from which you purchased the instrument immediately. The package contents include:

Checklist of Package Contents

Item	Qty.	Model	Remarks
IT6500C power supply	x1	IT6500C series	IT6500C series include IT6512C/IT6513C/IT6514C/IT6515C/ IT6516C/IT6517C/ IT6522C/IT6523C/IT6524C/IT6525C/ IT6526C/IT6527C/ IT6532C/IT6533C/IT6534C/IT6535C/ IT6536C/IT6537C /IT6542C/IT6543C/IT6544C/IT6545C /IT6546C/IT6547C /IT6552C/IT6553C/IT6554C/IT6555C /IT6556C/IT6557C /IT6562C/IT6563C/IT6564C/IT6565C /IT6566C/IT6567C /6572C/IT6573C/IT6574C/IT6575C/I T6576C/IT6577C /IT6582C/IT6583C/IT6584C/IT6585C /IT6586C/IT6587C/ IT6592C/IT6593C/IT6594C/IT6595C/ IT6596C/IT6597C
Power cord	xN	-	Number of the power cords vary depending on the model, See the Section Connecting the Power Cord for power cord connection.
USB cable	x1	-	This accessory is selected when the USB interface is used for starting up remote operation.
CD	x1	-	It contains power supply User's Manual, Programming Guide and other user documentations.
Ex-factory Test Report	x1	-	It is the test report of the instrument before delivery.



NOTE


Upon verification of the shipment, keep the package and relevant contents thereof in a safe place. When returning the instrument for warranty service or repair, the specified packing requirements shall be met.

1.2 Instrument Size Introduction


The instrument should be installed at well-ventilated and rational-sized space. Please select appropriate space for installation based on the power supply size.


IT6500C series power supply different models are not the same size, the detail size of the power supply are shown as below.

2U Model




Detailed Dimension Drawing







4U Model




Detailed Dimension Drawing







6U Model





Detailed Dimension Drawing






15U Model





24U Model



1.3 Connecting the Power Cord

Before Connecting the Power Cord

IT6500C Series power supply can also work in 110V voltage circumstances. However, the output power is limited. For full-power output, please use 220V $\pm$ 10% voltage or 380V $\pm$ 10% voltage.

CAUTION

- The power cords supplied with this product is certified for safety. In case the supplied lines assembly needs to be replaced, or an extension lines must be added, be sure that it can meet the required power ratings of this product. Any misuse voids the warranty of this product.
- Before connecting power cord, be sure to switch off the instrument. Power switch is in Off position.
- To avoid fire or electric shock, Make sure to use the power cord supplied by ITECH.
- Be sure to connect the main power socket to the power outlet with

protective grounding. Do not use terminal board without protective grounding.

- Do not use an extended power cord without protective grounding, otherwise the protection function will fail.

Power Cord Type and Connecting Method

IT6500C series contains many models. Different model is supplied with different power cord. The power cord and connection of different models are introduced as follow.


- IT6512C to IT6537C series power supply provides the standard power cords as below.

The IT6532C to IT6537C Series power supply consist of two power supply units, and ITECH provides two power lines during delivery. The user needs to connect each power supply unit to the AC 220V power source.




Connecting Method:

1. See the below illustration, one end of the AC power cord is connected to the AC input terminal in the rear board of the power supply. Connect the fire wire, zero line and ground to the corresponding terminal of the device.
2. Connect the plug on the other end of the power cord to your AC 220V power source. Connect the three terminals brown to line (L), blue to neutral (N), and yellow-green to ground (PE) on the other end of the power cord to your AC distribution panel.




- IT6542C to IT6547C Series power supply provides the standard power cords as below.

This series power supplies consist of three power supply units. ITECH provides a tailor-made power lines, making it convenient to connect the power supply to the three-phase distribution box(380V).



Connecting method:


1. See the below illustration, one end of the AC power cord is connected to the AC input terminal in the rear board of the power supply. And directly insert the green terminals to AC input terminals, respectively.
2. The other end of the power cord is converted to cables of three-phase five-wire. Connect the five terminals to your AC 380V power source. And gray to line (L1), brown to line (L2), black to line (L3), blue to neutral (N), and yellow to protective ground (PE).



- IT6552C to IT6597C series power supply connects the end of power cords with cabinet.

User connects the other end of power cord to AC distribution panel. The power supply AC input connecting as follows:

Connect the five terminals brown to line (L1), black to line (L2), gray to line (L3), blue to neutral (N), and yellow to ground (G) on the other end of the power cord to your AC distribution panel.



1.4 Connecting Test Lines (Optional)

Test lines are not standard accessories of the instrument. Please select optional red and black test lines for individual sales based on the maximum current value. For specifications of test lines and maximum current values, refer to “**Specifications of Red and Black Test Lines**” in “**Appendix**”.

WARNING

- Before connecting test lines, be sure to switch off the instrument. Power switch is in Off position. Otherwise, contact with output terminals in rear panel may cause electrical shock.
- To avoid electrical shock, before testing, please make sure the rating values of the testing lines, and do not measure the current that higher than the rating value. All test lines shall be capable of withstanding the maximum short circuit output current of the power supply without causing overheating.
- If several loads are provided, each pair of load wires shall safely withstand the rated short circuit output current of the power supply under full load.
- To avoid battery short circuit, be sure to check that the test line end is not connected when connecting or disassembling the test line. When the test line end is connected with battery, short circuit may cause severe accident.
- Always use test lines provided by ITECH to connect the equipment. If test lines from other factories are used, please check that the test line can withstand maximum current.
- During wiring, check that the anode and cathode of the test lines are properly and tightly connected; anode ON and cathode OFF are prohibited.

Test line connection is given below taking local measurement as example. For details of local and remote measurements, refer to “**Functions of Rear Panel Terminal**”.

1. Before connecting the test lines, be sure that the instrument Power is in Off position.
2. Check whether the shorting clip of Sense terminal is correctly mounted.
3. Unscrew the screws of the output terminals and connect the red and black test lines to the output terminals. Re-tighten the screws.

When maximum current that one test line can withstand fails to meet the current rated current, use several pieces of red and black test lines. For example, the maximum current is 1,200A, then 4 pieces of 360A red and black lines are required.

4. Directly connect the other end of the red and black lines to the DUT terminal.

Chapter2 Quick Start

This chapter introduces power-on check steps of IT6500C series to ensure normal start-up and usage under initialization status. This part also introduces the front panel, the rear panel, key functions and VFD display function of the power supply, make sure that you can quickly know the appearance, instruction and the key function before you operate the power supply. Help you make better use of this series of power supply.

2.1 Brief Introduction

With ITECH latest technology, the IT6500C series offers a full-featured high-performance power test solution. With fast response these DC power supplies provide users with a new level of power supply performance. The whole series include more than 100 models. The maximum output voltage and current is up to 1000V and 1200A respectively. With its auto ranging capability, it also has a super wide range of voltage and current applications. Users can choose the power supply that fits their testing requirements perfectly.

IT6500C Series power supply is featured with:

- Low ripple and low noise
- High Resolution Display
- Built-in internal electronic load and also used as external load
- Working with power dissipater unit, expanding load ability up to 300%
- The 2-quadrant current output ability provides seamless switching across two quadrants
- Two-quadrant current output, fast switching between quadrants, and seamless switching¹, suitable for battery rapid charging/discharging test
- CC & CV Priority Function, Fast curves changing without overshoot
- Flexible and simple programming the parameters of source and load
- Supporting with power supply CV/CC/CP modes and electronic load CC/CP modes
- Programming the resistance value
- parallel function, active current averaging and expandable power output capacity
- Sequence programming (List mode)
- Built-in DIN40839 & ISO-16750-2 test sequences
- Solar panel I-V curve simulation function
- Adjustable rising time and falling time speed and independent time setting in various mode
- Fully protections as OVP, OCP, OTP and OPP for source, OCP, OPP and OTP for load, ORVS, UVP and so on.
- Analog Control Interface and remote sense
- Intelligent fans control
- High visibility vacuum fluorescent display (VFD)
- RS232/USB/GPIB /LAN/CAN standard interfaces



Note

1: Seamless switching function can be achieved on the condition that when testing with high-powered battery (12V/120AH). When testing with low-powered battery, the instrument only can achieve fast switching and is unable to realize Seamless switching.


Model	Rated value	Rated value of internal load	Height
IT6512C	80V/120A/1800W	50A/150W	2U
IT6513C	200V/60A/1800W	25A/150W	
IT6514C	360V/30A/1800W	12.5A/150W	
IT6515C	500V/20A/1800W	8A/150W	
IT6516C	750V/15A/1800W	5A/150W	
IT6517C	1000V/10A/1800W	4.2A/150W	
IT6522C	80V/120A/3KW	50A/150W	
IT6523C	200V/60A/3KW	25A/150W	
IT6524C	360V/30A/3KW	12.5A/150W	
IT6525C	500V/20A/3KW	8A/150W	
IT6526C	750V/15A/3KW	5A/150W	
IT6527C	1000V/10A/3KW	4.2A/150W	
IT6532C	80V/240A/6KW	100A/300W	4U
IT6533C	200V/120A/6KW	50A/300W	
IT6534C	360V/60A/6KW	25A/300W	
IT6535C	500V/40A/6KW	16A/300W	
IT6536C	750V/30A/6KW	10A/300W	
IT6537C	1000V/20A/6KW	8.4A/300W	
IT6542C	80V/360A/9KW	150A/450W	6U
IT6543C	200V/180A/9KW	75A/450W	
IT6544C	360V/90A/9KW	37.5A/450W	
IT6545C	500V/60A/9KW	24A/450W	
IT6546C	750V/45A/9KW	15A/450W	
IT6547C	1000V/30A/9KW	12.6A/450W	15U
IT6552C	80V/480A/12KW	200A/600W	
IT6553C	200V/240A/12KW	100A/600W	
IT6554C	360V/120A/12KW	50A/600W	
IT6555C	500V/80A/12KW	32A/600W	
IT6556C	750V/60A/12KW	20A/600W	
IT6557C	1000V/40A/12KW	16.8A/600W	
IT6562C	80V/600A/15KW	250A/750W	
IT6563C	200V/300A/15KW	125A/750W	
IT6564C	360V/150A/15KW	62.5A/750W	
IT6565C	500V/100A/15KW	40A/750W	
IT6566C	750V/75A/15KW	25A/750W	
IT6567C	1000V/50A/15KW	21A/750W	24U
IT6572C	80V/840A/21KW	350A/1050W	
IT6573C	200V/420A/21KW	175A/1050W	
IT6574C	360V/210A/21KW	87.5A/1050W	
IT6575C	500V/140A/21KW	56A/1050W	
IT6576C	750V/105A/21KW	35A/1050W	
IT6577C	1000V/70A/21KW	29.4A/1050W	
IT6582C	80V/960A/24KW	400A/1200W	
IT6583C	200V/480A/24KW	200A/1200W	
IT6584C	360V/240A/24KW	100A/1200W	
IT6585C	500V/160A/24KW	64A/1200W	
IT6586C	750V/120A/24KW	40A/1200W	
IT6587C	1000V/80A/24KW	33.6A/1200W	
IT6592C	80V/1200A/30KW	500A/1500W	
IT6593C	200V/600A/30KW	250A/1500W	
IT6594C	360V/300A/30KW	125A/1500W	
IT6595C	500V/200A/30KW	80A/1500W	
IT6596C	750V/150A/30KW	50A/1500W	

Model	Rated value	Rated value of internal load	Height
IT6597C	1000V/100A/30KW	42A/1500W	

2.2 Front Panel Introduction

The 2U models of IT6500C Series power supply have the same front panels. Other models have the same panels as 2U Model. The front panel diagram and function key diagram of 2U Model are as follows.


IT6512C/IT6513C/IT6514C/IT6515C/IT6516C/IT6517C/IT6522C/IT6523C/IT6524C/IT6525C/IT6526C/IT6527C



- 1 Power Switch
- 2 VFD Screen
- 3 pulsating knob to control voltage, coarse button, fine button
- 4 pulsating knob to control current, coarse button, fine button
- 5 direction key and OK key
- 6 function keys and composite key
- 7 numeric key and Esc key
- 8 Vent hole

2.3 Keyboard Introduction

IT6500C series power supply different models are same the key function in front board, schematic graph as follow.




Detailed description of keys

Key Name	Description
0-9	Numeric button
Shift	Composite key
P-set(Menu)	Power setting button, used to set the output power value/menu function button which used to set the related parameters of power supply.

Key Name	Description
V-set(Setup)	Voltage setting button, used to set the output voltage of power supply (set power supply slope/protection function/upper and lower limits and load power/current set value/slope/protection function/upper and lower limits)
I-set(Function)	Current setting button, used to set the output current value of power supply (set power supply List function/built-in waveform and PV curve function)
Recall(Save)	Callback button, used to recall a saved setting parameter/save button, used to save a setting parameter.
Meter/(Local)	Meter button, used to switch the display between actual value and setting value/switch to the local mode.
Enter/(Trigger)	Confirm button, used to confirm the setting numbers or functions/trigger button
On/Off(Lock)	Output on/off button, used to control the output status of power supply/lock function button, used to lock the front panel buttons
	Left and right direction button, used to adjust the location of the cursor
	Up and down direction button, used to select the items of the menu or increase(decrease) the output voltage and current value
	Confirm button
	Return key
	Dot

2.4 Rotary Knob and Coarse/Fine Button Introduction

IT6500C series power supply is supplied with the voltage adjustment knob and the current adjustment knob, as shown below.



Adjust the voltage or current set value

The voltage knob or the current knob is used to adjust the voltage set value or current set value. Rotate the knob clockwise to increase the set value and anticlockwise to decrease the set value.

- The user can press the **[Coarse]** button and then rotate the knob to adjust the set value in integer bit. The step size of Coarse adjustment is 10. You can press left and right navigation key to move the cursor position.

- The user can press the **[Fine]** button and then rotate the knob to adjust the set value in decimal bit. The step size of Fine adjustment is 0.1. You can press left and right navigation key to move the cursor position.

Select the menu item

The voltage adjustment knob can be used to select the menu item. Press **[Shift]+ [P-set](Menu)** to enter the menu interface and then rotate the voltage adjustment knob to select the menu item from left to right.

2.5 VFD Indicator Lamps Description


IT6500C series power supply VFD indicator lamps description as follows:

Flag	Function Description	Flag	Function Description
OFF	Power supply in off mode	Timer	none
CV	Power supply in CV mode	Sense	none
CC	Power supply in CC mode	Ext	none
*	Open the keylock function	Addr	When received command successfully, the flag will display 3 seconds.
Meter	"Meter" button in on mode	Rmt	Remote control mode
Shift	using composite function	Error	Error occur
Rear	Analog function begin to work	Prot	Protections for OV or OT
SRQ	Serial request query	Trig	waiting for triggering signal
OFF	Power supply in off mode	Timer	none
CW	Power supply in CP mode	-	-

2.6 Rear Panel Introduction

Different models of IT6500C Series power supply have different rear panels. The 2U rear panel is as shown below. Other models have same rear panels as 2U Model except system bus and AC input terminal.

IT6512C/IT6513C/IT6514C/IT6515C/IT6516C/IT6517C/IT6522C/IT6523C/IT6524C/
IT6525C/IT6526C/IT6527C



- | | | |
|-------------------|---|---------------------------------------|
| 1 GPIB interface | 6 Not for user | 11 The positive terminal of output |
| 2 RS232 interface | 7 Earth (ground) terminal | 12 Sense terminals |
| 3 LAN interface | 8 AC power input terminals | 13 The negative terminal of output |
| 4 USB interface | 9 AC power input terminals for Power Dissipater | 14 System bus |
| 5 Fan | 10 Control interface of load | 15 Analog interface and CAN interface |

2.7 Power-on Selftest

A successful selftest indicates that the purchased power product meets delivery

standards and is available for normal usage.

Before operation, please confirm that you have fully understood the safety instructions.


WARNING

- To avoid burning out, be sure to confirm that power voltage matches with supply voltage.
- Be sure to connect the main power socket to the power outlet of protective grounding. Do not use terminal board without protective grounding. Before operation, be sure that the power supply is well grounded.
- The system bus interface is not isolated from the output electrode. After power on, it is not allowed to insert or pull out the bus and terminal matching resistance.
- To avoid burning out, pay attention to marks of positive and negative polarities before wiring.

Power Switch Introduction

User can press the power switch of IT6500C series power supply directly to turn on or turn off the instrument.


The status of Power switch is as follows.



Selftest steps

Normal selftest procedures:

1. Correctly connect the power cord. Press **Power** key to start up.
2. After selftest, VFD displays the output voltage and current status as below. The precision of different models are different, and the interface displays are not exactly the same. Please refer to the actual display.



Error Information References

The following error information may occur when an error occurs during Power On self-test:

- If the EEPROM was damaged, the VFD will display "Eeprom Failure".
- If the system setting data in EEPROM is lost, the VFD will display "Main frame Initialize Lost".
- If the calibration data in EEPROM is lost, then VFD will display "Calibration Data Lost".
- If the latest operation data in EEPROM is lost, then VFD will display "Config Data Lost".
- In case of parallel networking fault, networking will be failed and "NETWORKING..." will be prompted.

Exception handling

If the power supply cannot start normally, please check as below steps.

1. Check whether the power cord is correctly connected and confirm whether the power supply is powered.
Correct wiring of power cord = > 2
Incorrect wiring of power cord = > Re-connect the power cord and check whether the exception is removed.
2. Check whether the power turn On. Power key is under "I" "ON" status.
Yes = > 3
No = > Please check the Power key to start power and check whether the exception is removed.
3. Check whether the terminal resistance (plug) of the system bus is correctly installed, before checking, confirm the alarm information have read.
Yes => 4
No => Please re-install the terminal resistance. For 2U model, insert the terminal resistance at any end of the system bus interface. For other models, insert the terminal resistance to the bus Input of the first power supply system and the bus Output of the last power supply system. Restart the power supply to see whether the fault is removed.
4. When error information prompts at startup, Press [Esc] key to see whether present fault state can be cleared. Or, the user can attempt to clear the fault state by restarting the instrument. Do not restart the instrument until it is completely powered down. If not, contact ITECH engineer.

Chapter3 Function and Features

This chapter describes in detail the use of the front-panel keys and shows how they are used to accomplish power supply operation.

3.1 Setting Voltage

The constant voltage range is from 0V to the maximum voltage value. It is very easy for you to set the constant voltage output. You have 3 solutions to set the constant voltage value. And when you press [**V-set**], this button will be lit.

- directly input through number keys
Input the value you want to set and then please press [**Enter**] or [**OK**] button to confirm.
- using knob to set value
Press [**V-set**] button, press [**Coarse**] button (coarse adjustment, change the value in integer bit) or [**Fine**] button (fine adjustment, change the value in decimal bit), and then rotate the knob to set the value
- using left and right direction key to set value
Press [**V-set**] button
Press [**Coarse**] button(coarse adjustment, change the value in integer bit) or [**Fine**] button(fine adjustment, change the value in decimal bit), move the cursor by left and right keys, then to adjust values through ▲and▼.

3.2 Setting Current

The constant current range is from 0A to the maximum current value. It is very easy for you to set the constant current output. You have 3 solutions to set the constant current value. And when you press [**I-Set**], this button will be lit.

- directly input through number keys.
Input the value you want to set and then please press [**Enter**] or [**OK**] button to confirm.
- using knob to set value
Press [**I-Set**] button
Press [**Coarse**] button (coarse adjustment, change the value in integer bit) or [**Fine**] button(fine adjustment, change the value in decimal bit), and then rotate the knob to set the value
- using left and right direction key to set value
Press [**I-Set**] button
- Press [**Coarse**] button (coarse adjustment, change the value in integer bit) or [**Fine**] button(fine adjustment, change the value in decimal bit), move the cursor by left and right keys, then to adjust values through ▲and▼.

3.3 Setting Power

The constant current range is from 0W to the maximum power value. It is very easy for you to set the constant power output. When you press [**P-set**], this button will be lit. Then you can input the power value by numeric and press [**Enter**] or [**OK**] button to confirm.

3.4 Output On/Off Button

[On/Off] button is used to control the output state of power supply. If [On/Off] button is lit, this represents output is open. And in on mode, the indicator lamp (CC/CV/CW) will be lit.



NOTE

Please ensure that the DC source and product under test have been connected well before you press [On/Off] button.

3.5 Switching Setting Value and Actual Value

[Meter] button is used to switch the display between actual value and setting value. When [Meter] button is lit, this represents that VFD board display is actual value. Reversely, if [Meter] button is dark, VFD board display is corresponding to setting value.

This option allows users to enable an internal fixed timer delay (5 seconds) for the power supply to automatically switch from setting display to measured display. When enabled, if the power supply output state is ON (enabled) and if the display shows setting voltage and current, it will automatically switch to measured voltage and current display after 5 seconds. **Factory default is Off status.**

3.6 Switching Local/Remote Mode

Power supply provides local and remote modes. The two modes can be switched through communication commands. The default setting is local mode.

- Local mode: use press keys on the power supply front panel to operate.
- Remote mode: connect the power supply with PC, and operate power supply through PC. When it's remote mode, only [On/Off], [Meter], [Shift]+[Meter] (Local) work, with all the other panel keys not working. It can be switched to local mode by [Shift]+[Meter] (Local). The power supply's output parameters won't be influenced when mode is switched.

3.7 Key Lock Function

[Shift]+[On/Off] (Lock) button can enable you to lock the front panel buttons, then VFD will display “*”. In keylock mode, all buttons will not work except for [On/Off], [Meter] and [Shift] buttons. Re-press [Shift]+[On/Off] (Lock) button will release the keylock function.

3.8 Save/Recall Operation

IT6500C can enable you to save some frequently-used parameters in nonvolatile memory up to 100 sets, so that you can recall the parameters quickly. The following ways can help you achieve the save and recall operations: by pressing composite button [Shift] +[Recall] (Save) button or through command *SAV,*RCL. Save operation should work in with GROUP. Each GROUP can save 10sets, IT6500C includes 10 GROUP from 0-9.

Saved contents include voltage set value, current set value and power set value of the power supply, and the current set value and power set value of the load. You can also save the maximum and minimum values of the power supply and load, and select the load type and number of external loads.

Save method:

Using composite button [Shift]+[Recall] (Save) + number keys 1...9, and then pressing [Enter] button to save the preset value into specified memory region.

Using **[Recall]** (Save) button +number keys 1-9, and then pressing **[Enter]** button to recall the saved parameters from specified memory region.

3.9 System Menu

Press the composite key **[Shift] + [P-set]** (Menu) to enter the menu function. At this time, VFD displays optional menus. Scroll the VFD screen with Left/Right key or knob, and the following functions will appear in sequence. Press **[Enter]** to enter function options where the screen display locates. Press **[Esc]** to return to previous menu.

Menu	Menu setting	
SYSTEM	System menu	
	Reset	Restore to factory defaults
	Power-On	Set power on parameters
		Rst(Def) Initialize the system
		Sav0 Remain last shutdown parameters
	Trigger	Set the trigger mode
		Manual(Def) Manual trigger
		Bus Bus trigger
		Ext External trigger
	Memory	Work with Recall(Save) button to recall 100 sets saved parameters
		Group = 0 0: represents 0-9sets; 1: represents 10-19sets, by parity of reasoning
	Buzzer	Set the buzzer function
		On(Def) enable the buzzer function
		Off disable the buzzer function
	Communication	Select the communication interface
		RS232(Def) Select RS232 communication interface
		Baud rate : 4800/9600/19200/38400/57600/115200
		Data bit: 8 O Odd parity 2
		Parity bit: None/ E (Even parity)/O (Odd parity)
		Stop bit: 1/2
		Addr: Address=1
	USB	Select USB communication interface
	GPIB	Select GPIB communication interface
		Address= 15 Set the communication address (1 -30)
	LAN	Select LAN communication interface

CONFIG			Info: The information of LAN. LAN Status: Down IP Mode: Disconnect IP Addr: 0.0.0.0 SubNet: 0.0.0.0 Gateway: 0.0.0.0 DNS1: 0.0.0.0 DNS2: 0.0.0.0 MAC: 8C:C8:F4:40:01:E1 MDNS Status: HostName: HostDesc: Domain: TCPIP::INSTR: Socket Port: 30000	
			Config: IP-Mode: Auto/Manual Server-Config: MDNS: On/Off PING: On/Off telnet-scp: On/Off Web: On/Off VX-11: On/Off Raw-socket: On/Off	
			Restore: Restore to factory defaults, and the settings take effect after restart.	
			Reset: Save all of setting, and the settings take effect after restart.	
			CAN	Select CAN communication interface
				250K: Baud rate
		Addr: address of power supply		
		Prescaler: Prescaler		
		BS1 Value: Not settable		
		BS2 Value: Not settable		
		ReturnMeter	Enables automatic delay to switch display from setting to measured value (meter).	
			Off(Def)	Auto return Meter function disabled.
	On		Auto return Meter function enabled	
	P-Out	Power whether power supply was on		
		Off(Def)	After power on, the instrument will be in the off state.	
		Last	If output was on prior to turning the power off, the ON state will be resumed after power on.	
	CONFIG	Config menu		
		Load-Status	Setting the load status.	
		Load		
			Off(Def)	Load function is switched off.
On			Internal(Def): internal load function	
			External: external load function Ext Load Num: number of external loads.	
Static-Curr	Setting the static current when output is Off			

		Off	Turn off static current function (avoid current flow-backward)	
		On(Def)	Turn on static current function (clear voltage mantissa)	
	Monitor	10V(Def)	10V monitoring mode options	
		5V	5V monitoring mode options	
	Ext- Ctrl	External control mode and related parameter setting		
		Voltage(Def)	Voltage setting mode selection	
		10V(Def)/5V	10V or 5V setting mode selection. select by left/right key.	
		Resistance	Resistance setting mode selection.	
		10k/5k	10K or 5K setting mode selection, select by left/right key.	
		Off	Disable or enable this function. Select by up/down key.	
		On		
	Parallel	Parallel mode set up		
		Single	Single mode	
		Master	Act as a master mode	
			Master Mount: total number of instruments in parallel.	
		Slave	Act as a slave mode	
	Loop-Mode	Control loop setting		
		CV-Loop	CV loop control	
				High(Def): High speed
			Low: Low speed	
		CC-Loop	CC loop control	
				High(Def): High speed
			Low: Low speed	
		Priority	Priority setting	
				CV(Def): CV priority
			CC: CC priority	
		Filter	Set the display filter frequency of the power supply	
		Low	Low speed frequency	
		Mid(Def)	Middle speed frequency	
		Fast	High speed frequency	
	Info	Product information		
		Model	Model of power supply	
Ver		Software version		
SN		Serial number		
Last Cal		calibration information for last time		


Note

Press **[Shift]+[P-set]**(Menu) to view the menu items, press **[Esc]** to quit menu operation. Besides, press **[Esc]** button can enable you quit the function operation state.

Restored to Factory Setting (Reset)

This option is used to restore all settings in the system menu to factory setting values. Press **[Enter]** to restore to factory setting values. In this case, all set values in the system will be restored to factory setting values, i.e., the (Def) mark values.

Power On Parameter (Power-on)

When the power-on parameter is set as Rst, at each time of power on, the set parameters of the power supply will be 0V, 0.5A (The current set value of different models are different.) and the power rated value. The setting parameter of load will be internal load rated value. The parameter setting values under Setup and Function menus will also be restored to initial values.

Rst will not initialize the system setting and configuration setting. If Sav0 is selected, the parameters will be all setting values at the time of last power-off, including output and input setting values of the power supply/load.

Trigger Mode (Trigger)

Trigger is used for trigger the output of voltage, current and power, and there're three kinds of trigger options: Manual, Bus, and Ext. The default settings is Manual

- Manual: the trigger signal will be given by composite keys **[Shift]+[Enter]**(Trigger)
- Bus: bus trigger mode.
- Ext: external signal trigger.

Save Group Operation (Memory)

Power source can save 100sets parameters in nonvolatile memory by the save group setting. This operation provides the customer with a convenient and quick save/recall using condition.

GRP0: save (recall) power source parameters in 0-9 sets. Press **[Shift]+[Recall]**(Save)+0-9 numeric keys(**[Recall]** +0-9 numeric keys to recall the parameters)

GRP1: save (recall) parameters in 10th -19th sets. Press **[Shift]+[Recall]**(Save)+numbers1-9 to save the parameters(**[Recall]** +numbers1-9 to recall parameters).Under this condition,number "1" represents to save or recall the 10th parameters.Number "2" represents to save or recall the eleventh parameter.GRP2-GRP9 can be understood in the same manner.

Key Sound Set (Buzzer)

This item can set the buzzer state. **On** option indicates that when you push buttons, the buzzer will sound. **Off** option indicates that the buzzer function is disabled. Factory default is **On** option.

Communication Set (Communication)

Under this item, you can set the concrete communication mode. This unit has provided multiple communication interfaces: RS232/USB/GPIB/LAN/CAN.Of which, the GPIB are addressable from 1-30. The baudrate options of RS232 are 4800, 9600, 19200, 38400, 57600, 115.2K. Data bit is 8bits. Parity bit has three options: NONE, ODD, EVEN. Please ensure the configuration consistency between our instrument and PC, so that you could have a successful communication.

Return to Meter state (Return Meter)

This option allows users to enable an internal fixed timer delay (5 seconds) for the power supply to automatically switch from setting display to measured display. When enabled, if the power supply output state is ON (enabled) and if the display shows setting voltage and current, it will automatically switch to measured voltage and current display after 5 seconds.

Power On Output State (P-OUT)

This item can set the power on output state. If you select **Last** item, that indicates the power on output state is the same with output state before this item is set. If you select **Off** item, unit will automatically in off mode when you power on. Factory default is **Off** option. And this setting is effected by Power-on, and take effect when the Power-on set to Save0.

Setting Filter

This option sets the display filter frequency of the power supply. The filter function of this series of power supply is averaging calculation. The average values of different frequencies are different, as shown below: Low: 2^{16} ; Mid: 2^{14} ; High: 2^8 .

3.10 Setup Menu

In the configuration menu, the user can configure all parameters related to the power supply and the load as well as resistance setting.

Configuration parameters of the power supply are as follows:

- Voltage/current/power slope
- OVP/OCP/OPP
- Maximum and minimum limits of voltage/current/power

Configuration parameters of the load are as follows:

- Current and power
- Current and power slope
- OCP/OPP
- Maximum and minimum limits of current/power

The user can directly enter into the Configuration Menu by pressing the **[Setup]** key on the front panel.

Setup	Source	Configure menu		
		Slope	Set the source slope	
			V-Rise: voltage rise slope	
			V-Fall: voltage fall slope	
			I-Rise: current rise slope	
			I-Fall: current fall slope	
			P-Rise: power rise slope	
			P-Fall: power fall slope	
		OVP	Over voltage protection of source	
			On(Def)	Enable over voltage protection function
				V: OVP value
				Delay: delay time of protection
			Off	Disable over voltage protection

				function
		OCP	Over current protection of source	
			On(Def)	Enable over current protection function
				I: OCP value
				Delay: delay time of protection
			Off	Disable over current protection function
		OPP	Over power protection of source	
			On(Def)	Enable over power protection function
				P: OPP value
				Delay: delay time of protection
			Off	Disable over power protection function
		Limit	V-Max	Maximum voltage setting
			V-Min	Minimum voltage setting
			I-Max	Maximum current setting
			I-Min	Minimum current setting
			P-Max	Maximum power setting
			P-Min	Minimum power setting
	Load	P-set	Setting the load power	
		I-set	Setting the load current	
		Slope	Setting the load slope	
			I-Fall: current fall slope	
			I-Rise: current rise slope	
			P-Fall: power fall slope	
			P-Rise: power rise slope	
		OCP	Over current protection of load	
			On(Def)	Enable over current protection function
				I: OCP value
				Delay: delay time of protection
			Off	Disable over current protection function
		OPP	Over power protection of load	
			On(Def)	Enable over power protection function
				P: OPP value
				Delay: delay time of protection
			Off	Disable over power protection function
		Limit	Set the maximum and minimum value of load	
			I-Max: Maximum load current setting	
			I-Min: Minimum load current setting	
			P-Max: Maximum load power setting	
			P-Min: Minimum load power setting	
	Resistance	Resistance	Output resistance setting	

3.11 Setting Output Rise Time/Fall Time

Rise/fall time is the time taken for one voltage point to rise/fall to the other under the output status is ON. When view the fall time that voltage falls to 0V, set 0V through [V-set]. After press [Enter] to confirm, voltage will fall based on the set fall time.

This series of power supply is supported the rise and fall times in all modes (Source: CV, CC, CP, Load: CC, CP), the range of time is 0.001S~24H.

1. Press [Shift] + [V-set](Setup) to enter power supply setting screen.
2. Select "Source", press [Enter].
Or, the user can select "Load" to set the load slope.
3. Select "Slope".

You can set the rise/fall times for voltage, current and power. The unit is second (S). Each setting can be selected through the Up/Down key. Adjust the rise time through the numeric key, Up/Down key or knob. After input, then press [Enter] or [OK] for confirmation.

- V-Rise/ V-Fall: Voltage rise/fall slope.
- I-Rise/ I-Fall: Current rise/fall slope.
- P-Rise/P-Fall: Power rise/fall slope.



Note

The drop rate of the voltage is affected by the internal load input current. Setting the load input current to the maximum will get the drop rate of the voltage up. Please refer to the Set load input in 3.14 Load Function for more detailed setting.

When CC mode is selected from CC/CV Priority, the two-quadrant current slope is only affected by the hardware and cannot be changed by the setting parameter, but the one-quadrant current slope can be controlled by the setting parameter.

3.12 Protection Function

IT6500C Series provides OVP, OCP, OPP for power supply as well as OCP and OPP for the load. In addition, this power supply also provides OTP, Sense reverse protection, power-down protection and input under-voltage protection. In case of protection, please check fault reason and remove fault. Press the [Esc] key to disarm protection status.

OVP

User can enable the over voltage protection function and set the protection value in setup menu, Over Voltage Protection will be triggered when the voltage exceeds the protection value. Many reasons could cause over voltage protection. For example, caused by internal defect, misoperation or too high external voltage.

Once the power supply is over voltage protected, will the output be shut down at once, and "Prot" indicator lamp will be lit, and prompt "Over Voltage" will be displayed on VFD screen. Please avoid inputting a external voltage higher than 120% rated value, or the instrument will be damaged.

When the power source is in OVP state, you should check the external cause firstly. When the external factors are excluded, please press [On/Off] button. Then the unit could have a output voltage again. If in remote control mode, you should clear the OVP state, then could you open the output by OUTP ON command.

Set the OVP voltage value as follows:

1. Press the composite key **[Shift] + [V-set]** (Setup) to enter the setup Menu.
2. Select "Source" in the menu and press **[Enter]** for confirmation.
The power supply can set its OVP.
3. Select OVP with Left/Right key and press **[Enter]** for confirmation.
4. Select On to enable OVP function and press **[Enter]**.
5. Set OVP voltage value with numeric key and press **[Enter]** for confirmation.
6. Set OVP delay time with numeric key and press **[Enter]** for confirmation.
The range of delay time is 0.001S~10.00S. Press **[Esc]** to exit menu setting.

OCP

User can enable the over current protection function and set the protection value in setup menu, Over Current Protection will be triggered when the current in circuit exceeds the protection value.

Once the power supply is over voltage protected, will the output be shut down at once, and "Prot" indicator lamp will be lit, and prompt "Over Current" will be displayed on VFD screen. At same time, the beeper will be on.

Set the OCP current value as follows:

1. Press the composite key **[Shift] + [V-set]** (Setup) to enter the setup Menu.
2. Select "Source" in the menu and press **[Enter]** for confirmation.
Or, the user can select "Load" to set the load OCP.
3. Select OCP with Left/Right key and press **[Enter]** for confirmation.
4. Select On to enable OCP function and press **[Enter]**.
5. Set OCP current value with numeric key and press **[Enter]** for confirmation.
6. Set OCP delay time with numeric key and press **[Enter]** for confirmation.
The range of delay time is 0.001S~10.00S. Press **[Esc]** to exit menu setting.

OPP

OPP is a protection measure taken when the actual power exceeds the rated power of the power supply. Under OPP, the power supply output will be switched off and VFD indicator "Prot" will be lighted on. In addition, the VFD display screen will display "Over Power" or "Load Over Power".

This series of power supply can set OPP.

Set the OPP current value as follows:

1. Press the composite key **[Shift] + [V-set]** (Setup) to enter the setup Menu.
2. Select "Source" in the menu and press **[Enter]** for confirmation.
Or, the user can select "Load" to set the load OPP.
3. Select OPP with Left/Right key and press **[Enter]** for confirmation.
4. Select On to enable OPP function and press **[Enter]**.
5. Set OPP power value with numeric key and press **[Enter]** for confirmation.
6. Set OPP delay time with numeric key and press **[Enter]** for confirmation.
The range of delay time is 0.001S~10.00S. Press **[Esc]** to exit menu setting.

Over-temperature protection

When internal power device of instrument is higher than about 90 °C, the instrument is under temperature protection. At this time, the instrument will automatically be OFF and VFD will display “Over Temperature”.

Power down protection

With power-down protection, when the instrument power supply is switched off and the instrument detects power-down status, the instrument will immediately execute output switch-off and the instrument interface will display “power-down”.

Under Voltage Protection

When internal voltage is low due to internal fault or when AC input voltage is low, the instrument will initiate the under-voltage protection. Or when 110V AC power supply is connected, the instrument output function is limited. When the set output power exceeds limit value, the instrument will also initiate under-voltage protection status. In the case of under-voltage protection, the instrument interface will prompt “Under Voltage Prot”.

Sense Reverse Protection

The instrument defaults to provide sense reverse protection. When the output state is ON and the difference between output terminal voltage and sense remote voltage exceeds the specified voltage, sense reverse protection will be enabled after 500ms. The power supply output will be immediately switched to Off and the buzzer will sound if the sense terminals are reversed. The display screen will display “Sense Reverse Prot”. Press **[Esc]** to clean the protection.

When the power source is in Sense Reverse Protection state, you should check the whether the polarities are connected reversely or not firstly. When the polarities connect correctly, please press **[On/Off]** button. Then the unit could have a output voltage again.

The voltage difference between output terminal and remote sense terminal of each model is not the same. The detailed value is shown in the next table. When the remote sense terminal is connected reversely, the maximum voltage will not exceed the sum of set voltage and the difference voltage.

IT6512C~IT6592C	5V
IT6513C~IT6593C	5V
IT6514C~IT6594C	7V
IT6515C~IT6595C	10V
IT6516C~IT6596C	15V
IT6517C~IT6597C	20V

3.13 Setting Maximum and Minimum Values

The maximum voltage of the power supply ranges from V-min to full-rated output voltage. Press the composite key **[Shift] + [V-set] (Setup)** to enter the Configuring Menu for setting maximum and minimum values of power supply voltage, current and power. When limit setting is finished, the voltage, current and power setting values can only be set within the maximum and minimum limits.



Note

Function and external analog programming are not limited by Limit.

Set the maximum and minimum voltages as follows:

1. Press the composite key [Shift] + [V-set] (Setup) to enter the Configuring Menu.
2. Select "Source" in the menu and press **[Enter]** for confirmation.
Or, the user can select "Load" to set the load Limit. For load, you can only set the maximum and minimum limits of the current and power.
3. Select Limit with Left/Right key and press **[Enter]** for confirmation.
4. Set the V-Max with numeric key and press **[Enter]**.
5. Set the V-Min with numeric key and press **[Enter]** for confirmation.
Or, select the maximum/minimum current or power with Arrow key.
6. Set maximum/minimum current or power with numeric key or press **[Esc]** to exit menu setting.

After the maximum/minimum voltage is set, the output voltage can only be set within this range. Vmax factory setting is the rated output voltage of corresponding model of the power supply. V-Min is 0V.

3.14 Load Function

The load function in this series of power supply extends the working range of the power supply to make it absorb certain current and power. This is a two-quadrant power supply, which can be switched quickly under current mode of the power supply and the load, so as to enable speedy, continuous and seamless switching between output and absorption current. It can be applied in charge/discharge tests of the battery. The load is divided into internal load and external load based on discharging capacity. For detailed specifications, refer to Technical Specification Parameters.

Internal load

When the load function is initiated, the system is defaulted to be in internal load mode. By default, the default value of power is power rated values. The default value of current is small and different for each model. Please refer to the actual value.

The user can turn on load function in the Configuration Menu. Detailed operations are as follows.

1. Press **[Shift]+[P-set]** (Menu) to enter the Menu operation. The interface displays information as follows:

DEVICE MENU

SYSTEM CONFIG INFO

2. Press the Right key to select "**CONFIG**" in the Menu to enter the Menu operation and select Load-Status. Press **[OK]/[Enter]** for confirmation and select the **[Load]** to set the load status.
3. The user can select On through Arrow key to turn on the load function.

On: the current load function is on. The user can select On or Off to turn on or off the load function through Up/Down key. When the load is on, you need to select internal load or external load. The instrument defaults to internal load.

Internal: the current load is internal load. The user can select Internal (internal load) or External (external load) through Up/Down key.


External load

In using external load function, the user needs to parallel the IT-E500 Series power dissipater. When using external load function, you need to set the number of power dissipaters so that the user interface can automatically zoom the range. The power dissipater can be paralleled to extend or discharge power but not current. Maximum average discharge power $\leq$ maximum output voltage $\times$ maximum discharge current.

1. Press **[Shift]+[P-set] (Menu)** to enter the Menu operation. The interface displays information as follows:
2. Press the Right key to select "**CONFIG**" in the Menu to enter the Menu operation and select Load-Status. Press **[OK]/[Enter]** for confirmation and select the **[Load]** to set the load status.
3. The user can select On through Arrow key to turn on the load function.
On: the current load function is on. The user can select On or Off to turn on or off the load function through Up/Down key.
4. Select current load as External and press **[Enter]** for confirmation.
5. Press the number key to set the number of power dissipaters in parallel, for example Num = 1. When external load function is selected, you need to set the number of external power dissipaters in parallel. This number is multiple extended of power instead of total number of power dissipaters. Setting range is 1-3. The load power of each instrument can be extended by 300%.

Parallel connection of power dissipaters

IT-E500 Series power dissipater is an accessory provided by ITECH for this power supply. Each IT-E500 power dissipater can provide discharge capacity up to 3KW and supports parallel connection of several power dissipaters. Each 2U power supply can be paralleled to 3 power dissipaters at most. You can select the power dissipater based on power supply model. For detailed description of the power dissipater, refer to IT-E500 Series User Manual. The wiring method for three parallel power dissipaters is as shown below.



Wiring instruction:

1. Connect the external load's connection terminal of IT6500C Series power supply to the load input interface of IT-E500 Series power dissipater. Connections of other power dissipaters are as shown in blue lines in the figure.
2. Connect the external load AC input interface OUTPUT (LOAD) of IT6500C Series power supply to the AC input interface of the power dissipater. AC input connections of other power dissipaters are as shown in red lines in the figure. Please pay attention to corresponding L/N/G terminals.

Set load input

When using load function, the user can set load current, power and slope as well as OCP, OPP, etc.

Set the load input current and input power in **Setup** menu. Details about load

input current/power are as shown below.

In internal load mode, the value of load power is defaulted to rated value, and the value of current is defaulted to a small value. In external load mode, the values of load power and current are defaulted to zero.

1. Press **[Shift]+ [V-set]**(Setup) to enter the Menu operation. The interface displays information as follows:

SETUP		
Source	Load	Resistance

2. Select **"Load"** to set parameters related to the load.

LOAD			
P-set	I-set	Slope	OCP

Select "P-set" to set the input power value.

Select "I-set" to set input current value.

Press the Number key or use Knob to directly set the power or current value.

3.15 Charge Protection

This power supply is applicable to battery charge test and provides charge protection during battery charge test. Even when the internal load is activated, the UUT will not be discharged. During charge protection, the power supply switches off output as follows.

1. Power output is switched off (On/Off key is lighted off) and power supply will stop output.
2. The internal load discharges the capacity energy at power output through a small current.
 - When abnormal capacity energy discharge is detected, the UUT connected at the output terminal is a battery or other energy storage devices. To step3.
 - When capacity energy discharge of the power supply is normal, it means that no energy storage device is found. Continue to discharge the current to 0V. To end.
3. The power supply will automatically adjust the internal load discharge current to 0 and stop discharge.

This protection function forbids UUT discharge to guarantee device safety. It also avoids insufficient charge during battery charge test.

3.16 Static Protection Function of Battery

The power supply is designed with the battery protection function in static state (when the output is off). If the DUT is the energy storage device like battery, the power supply will prevent battery from consumption.

1. Press **[Shift]+[P-set]**(Menu) to enter the system menu.
2. Select "Static-Curr" and turn off static current function when output is Off.

If the DUT is the energy storage device like battery, you need to turn off the static current function. Otherwise, the current of the battery will be consumed and flow backwards to the power supply. The value of the current flowing backwards of different models is not the same. It ranges from 0.1A to 0.5A approximately.

3.17 Internal Resistance Setting

During the simulation of the battery charging/discharging, it's necessary to consider about the internal resistance changes of the battery. For accurate battery simulation test, IT6500C Series power supply provides internal resistance setting to simulate various kinds of actual working statuses of the battery.

To set internal resistance, follow the methods below.

1. Press the composite key **[Shift]+[V-set]** (Setup) to enter the Configuring Menu.
2. Select "Resistance" in the menu and press **[Enter]** for confirmation.
3. Set internal resistance value with number key and press **[Enter]** for confirmation.

3.18 CC/CV Priority


IT6500C Series is innovatively designed with CV/CC priority concept in the industry to solve various strict problems in long-term test applications and to make applications (e.g., speedy or no-overshoot operation of power supply) more flexible. As everyone knows, power supply has two working modes including constant voltage and constant current, which correspond to two inside loops (CV control loop and CC control loop). Traditional power supplies always take CV loop as priority, which are not suitable for circumstances having high requirements on current overshoot. With new CC/CV priority concept in IT6500C, the user can realize CC control loop, response speed of CV control loop and any combination setting of control loops under CC and CV mode through the power supply menu interface to meet diversified field applications. With this function, the user can save a lot of costs as no purchased parts are required.

Example of application circumstance in typical configuration application:

- Strict requirements on current overshoot

Set Priority as CC, CC-Loop as High and CV-Loop as Low. This priority is applicable for circumstances having high current overshoot requirements, like LED lamp, laser test, etc.


Traditional power supply has low priority due to slow CC loop speed and cannot quickly detect and inhibit current overshoot when the current reaches the set current. Through IT6500C menu, you can set the CC control loop to High priority to quickly make the power supply in constant current status so as to inhibit current overshoot at the starting moment. Waveform characteristics are as shown below. Yellow means output voltage and green means output current.



- Start up the over-current range of surge current to quickly set up voltage.

As the input end of power supply module has large capacity, large surge current will generate at starting moment, which will lower the power supply voltage at the input side of DC module. In addition, this will result in CC current limit mode, where low supply voltage will cause under-voltage protection of DC module, making startup fails.


Set Priority as CV, CC-Loop as Low and CV-Loop as High. The voltage is not sensitive to current at phase step and voltage edge can be realized quickly. In addition, this avoids surge current at startup, which may cause CC mode and startup failure. Waveform characteristics are as shown below. Yellow means output voltage and green means output current.



- Battery charge-discharge, high speed, seamless, and no overshoot

Set Priority as CC, CC-Loop as High and CV-Loop as High to represent CC characteristics entirely. In this way, you can quickly create current and inhibit current overshoot so as to realize seamless and no-overshoot current switch. Waveform characteristics are as shown below. Yellow means output voltage

and green means output current.



WARNING


When CV mode is selected from CC/CV Priority, the load current value set in List wave file fails and discharge current is the I-set value set in the power supply **Setup** menu. Pay attention to current value to avoid over-current. For detailed checking and setting methods, refer to 3.14 Load Function.

To set loop and CC/CV mode, follow the method below.

1. Press the composite key **[Shift]+[P-set] (Menu)** to enter the Configuring Menu.
2. Select "CONFIG" in the menu and press **[Enter]** for confirmation.
3. Select "Loop-Mode" with Right key and press **[Enter]** for confirmation.
4. Select CV-Loop or CC-Loop to set the loop response speed.
5. Select Priority and set the current priority work mode, which defaults to CV mode.

3.19 LIST Operation

IT6500C LIST mode comprises 10 files (File1-File10) in total, and each has 10 waves. Each wave has 10 steps. You need to edit the voltage, current, load current, pulse width and rise/fall slope of each step. Each wave can set repetition, so does each list file. Ten wave files can be linked in sequence under one list. Relationship between List file and wave file is shown below.



List file can select any one from 100 waves. Each List file can select 10 wave files at most and combine them into a List file based on sequence.

Each wave file has ten steps. The List file can select the wave file and set the count of repetitions to be executed.

List function menu is as follows.

List	List function menu	
	On/Off	List function switch
	Recall	List file recall
		Recall List File: Need to recall list file number.
	EditFile	List file edit
		Repeat: count of List file repetitions (0-65535)
		Wave Count: total count of waves contained in this List file. (1-10)
		1 st Wave Select: number of the first wave selected
		1 st Wave Repeat: count of repetitions of the first wave selected (0-65535)
		Yes/No: save to the file or not
	EditWave	Wave file edit
		Recall Wave: Need to recall Wave file number.
		Step Count: total count of steps contained in the Wave file (1-10)
		Step1 Voltage: Voltage setting of step 1 (0-Vmax)
		Step1 Current: Current setting of step 1 (0-I _{max})
		Step1 LoadCurr: Load current setting of step 1 (0-I _{max} (load))
		Step1 Width: Width setting of step 1 (0s-24h)
		Step1 Slope: Slope setting of step 1 (0s-24h)
		Save to Wave: save to the Wave file

Wave edit and List edit have no order of priority.

Editing Wave

List file can arrange and link several Wave files. The user can pre-edit several Wave files and select edited wave file that meets requirements during usage. In this series of power supply, at most 100 wave files can be edited.

Take an example for 3 steps, the steps of editing Wave file are as follows:

1. Press [**Shift**]+[**I-set**] (Function) to enter List operation.

2. Press  to select **EditWave** from the menu, and press **[Enter]** for confirmation.
3. Press numeric key to input the number of Wave file under edit, where Recall Wave= 01, and press **[Enter]** for confirmation.
4. Press numeric key to input total count of steps for the current Wave file, where Step Count=03, and press **[Enter]** for confirmation.
5. Press the numeric key to set the voltage, current, load current, slope and width of the Wave step 1 in sequence.

Step1 Voltage = 1V

Step1 Current = 1A

Step1 LoadCurr = 1A

Step1 Width = 1s

Step1 Slope = 0.1s



NOTE

When CV mode is selected from CC/CV Priority, the load current value set in List wave file fails and discharge current is the I-set value set in the power supply Setup menu. Pay attention to current value to avoid over-current. For detailed checking and setting methods, refer to 3.14 Load Function.

When CC mode is selected from CC/CV Priority, the two-quadrant current slope is only affected by the hardware and cannot be changed by the setting parameter, but the one-quadrant current slope can be controlled by the setting parameter.

6. After editing the above parameters in step 1, continue to edit the same parameters for step 2 and step 3. Count of steps is up to customer requirements. At most 10 steps can be edited. The edited Step Count shall be consistent with the one defined by the customer.
7. Select Save to Wave to save, and press **[Enter]** for confirmation.
Select Yes. After editing, select Yes or No. Select Yes to save to the Wave file. Select No not to save and return back to the List Setting screen.

Editing List File

List file editing means to arrange and link several Waves in certain sequence.

Take an example for 3 wave files, the steps of editing list file are as follows:

1. Press **[Shift]+ [I-set]**(Function) to enter List operation.
2. Press  to select **EditFile** from the menu.
3. Press the numeric key to set the count of repetitions in executing this List file. For example, if there are 2 repetitions, Repeat = 2.
4. Press the numeric key to set the count of Waves contained in this List. For example, Wave Cont = 3.
5. Press the numeric key to input the number and count of repetitions of the first Wave selected.
1st Wave Select = 02
1st Wave Repeat = 1
6. Press the numeric key to input the number and count of repetitions of the second Wave selected.
2nd Wave Select = 02

2nd Wave Repeat = 1

7. Select the Wave arranged and count of repetitions in sequence. The Wave count and arrangement sequence of each List file can be defined by the customer based on requirements. A List file can link 10 Waves at most. The edited Wave count shall be consistent with the one defined by the customer.
8. Select Yes. After editing, select Yes or No. Select Yes to save to the List file. Select No not to save and return back to the List Setting screen.
9. Select Save to File = 01 to save, and press **[Enter]** for confirmation.

Run List File

After editing List file, the user needs to set the trigger mode and run List function. Return to the main screen for triggering. Detailed steps are as follows:

- Before starting up List function, please set trigger mode first. See Section 3.9 for trigger source.
1. Press the composite key **[Shift]+[P-set]** (Menu) to enter the System Menu.
 2. Select SYSTEM and press left and right key to select Trigger.
Set the required trigger mode. Default trigger mode is Manual.
 - Trigger the List file as follows
 1. Press **[Shift]+[I-set]**(Function) to enter List operation.
 2. Press  to select Recall from the menu, and press **[Enter]** for confirmation.

Recall File Name = 01

3. Press Arrow key to select Off. Press **[Enter]** for confirmation. Then, Off is changed to On. List function is switched on.

On Recall EditFile EditWave

4. Press **[Esc]** back to the main screen. Press **[On/Off]** to switch on power output. The screen is displayed as follows.

0.00V 0.00A
0.0W List

5. Press **[Shift]+[I-set]**(Trigger) for triggering. The VFD Trig is lighted up.




NOTE

If On Recall EditFile EditWave is displayed under LIST MENU or the external analog control function is switched on, neither List nor Wave file editing is accessible. In this case, change On Recall EditFile EditWave to Off Recall EditFile EditWave before operation.

3.20 PV Simulation

The PV array/module/cell is a device that converts from light energy to electric energy. It is made by a simple semiconductor PN junction that the major output characteristic is that there's only one maximum power point (MPP) at certain sunlight intensity. The PV inverter is designed to track this point to harvest maximum energy that is generated by the PV array. Therefore, all the PV inverters have the maximum power point tracking (MPPT) mechanism built-in, and it is very important to test the efficiency of this MPPT.

PV array VI curve here:



Editing Array VI Curve

A PV (photovoltaic) array simulator is built-in the PVS series power supply to output the PV's V/I (voltage/current) curve for PV inverter testing. User can set up to 100 curves by 2 major parameters of the PV array (Pmp and Vmp) and one 4096-point V/I table.

The menu as below:

PV-SIM	PV Simulation		
	On/Off	Enable/Disable the PV simulation function	
	Static		
		Recall	Recall Curve=1: Recall the exist curve
		EditCurve	Edit the PV curve
			Curve: curve number
			Pmp: maximum power setting
			Vmp: maximum power voltage setting
			SANDIA:
			TF: Thin-Film SCMC: Standard Crystalline or Multi-crystalline HEC: High-efficiency Crystalline
			EN50530:
	Table	User defined the I-V curve table	

- To edit internal curve, follow the operation steps below:

1. Press **[Shift]+ [I-set]** (Function) to enter the Menu operation.
2. Select PV-SIM with Left/Right key and press **[Enter]** for confirmation.
3. Select Static with Left/Right key and press **[Enter]** for confirmation.

You can enter Static to edit the curve only when the photovoltaic curve is Off. Otherwise, you cannot edit the photovoltaic curve.

4. Select the instrument as simulation of one photovoltaic curve based on 2 parameters. Select "EditCurve" to enter editing mode.

Under this mode, the user needs to define the curve number, maximum power and maximum power voltage. For detailed parameter description, refer to internal waveform menu description.

Run the photovoltaic curve.

After set of desired curve, run the photovoltaic analog. The power supply will change the output voltage and current at 1ms interval to keep the voltage and current above V/I curve. This speed is enough to meet most trace mechanisms at maximum power point.

You can set and run local edit curves locally or remotely.

The user-defined 4096-point V/I datasheet can only be set via remote PC, but can be run locally or remotely.

1. Press **[Shift]+ [I-set]** (Function) to enter the Menu operation.
2. Select PV-SIM with Left/Right key and press **[Enter]** for confirmation.
3. Select On or Off. Press **[Enter]** to switch the current curve status as On.
4. Press **[Esc]** to exit the main interface, as shown below.

0.00 V 0.00A
0.0W PV-SIM

5. Press **[On/Off]** to turn on the power supply output. The power supply will output corresponding voltage based on the current value.

3.21 Built-in Waveform

IT6500C models have built in DIN40839 waveform, ISO-16750-2 waveform and ISO21848 Provide for user to execute the test directly.

Menu as below:

Road-Vehicles	Vehicle waveform				
	DIN40839	Evaluation of automotive starting waveform			
		12V	Select the 12V waveform		
		24V	Select the 24V waveform		
		User-defined	User defined waveform		
		Off	Disable/Enable the automotive starting waveform function.		
		On			
	ISO16750-2	simulate the waveform to verify the anti-interference performance of the automotive electronics' products.			
		Short-Drop	This test simulates the effect when a conventional fuse element melts in another circuit		
				12V	Select 12V or 24V waveform
		24V			
		Off		Enable or Disable the Short voltage drop function.	
		On			
		Reset-Test	This test verifies the reset behavior of the DUT at different voltage drops. This test is applicable to equipment with reset function		
				Usmin...	The minimum supply voltage Usmin
		Off		Enable/Disable this function	
		On			
		Starting-Pro file		This test verifies the behavior of a DUT during and after cranking.	
			12V	Select 12V or 24V test system	
			24V		

				Set the levels/voltages/duration of starting profile The levels of 12V: 1-4 The levels of 24V: 1-3
				1
				Off
				On
				Enable/Disable this function
			Load-Dump	Load dump curve
				Test A
				select centralized load dump Unsuppression
				Test B
				select centralized load dump suppression
				Off
				Turn on/off load dump waveform
				On
				12V
				Select 12V or 24V voltage system
				24V
				Td
				Pulse width
				Un
				Peak voltage
				Us
				clamping voltage
		ISO21848	Simulate the curve of "Electrical and electronic equipment for a supply voltage of 42 V — Electrical loads"	
			Umax,dyn	Umax,dyn Test pulse
				Off
				Turn on / off Umax,dyn test pulse
				On
			Momentary-Drop	Transit Voltage drop
				Off
				Turn on / off transit Voltage drop wave
				On
			Reset	Reset test supply Voltage
				Ulow
				Set supply Voltage
				Off
				Turn on /off rest test function
				On
			Start	Startup pulse
				Off
				Turn on /off startup pulse
				On
		SAEJ1113-1	SAEJ1113-11 waveform protocol	
			Test 2B	Transient from DC motors acting as generators after ignition switch OFF
				Off
				Turn on/off this function
				On
				12V
				Select 12V or 24V voltage system
				24V
				Td
				Test pulse width
			Test 4	Starter motor engagement disturbance pulse
				Off
				Turn on/off this function
				On
				12V
				Select 12V or 24V voltage system
				24V
				Vs
				Refer to the figure
				Va
				-
				T7
				-
				T9
				-
				T11
				-

		Test 5	Load dump waveform	
			Test A	select centralized load dump Unsuppression
			Test B	select centralized load dump suppression
			Off	Turn on/off load dump waveform
			On	
			12V	Select 12V or 24V voltage system
			24V	
			Td	Pulse width
			Un	Peak voltage
		Us	clamping voltage	
	LV124	LV124 waveform protocol		
		E-02	Transient overvoltage test waveform	
			Off	Turn on / off this funciton
			On	
		E-04	LV124 E-04	Jump start test waveform
			Off	Turn on/off this funciton
			On	
		E-05	LV124 E-05	Load dump test waveform
			Off	Turn on/off this function
			On	
		E-07	LV124 E-07	Slow decrease and increase of the supply voltage test waveform
			Ubmax	Start voltage
			Ubmin	Holding voltage
			Ubmin Holding Time	Holding time at Ubmin
			Off	Turn on/off this function
On				
E-08		LV124 E-08	Slow decrease, quick increase of the supply voltage test waveform	
		Ubmax	Start voltage	
		Ubmin	Holding voltage	
		Ubmin Holding Time	Holding time at Ubmin	
		Off	Turn on/off this function	
		On		
E-09		LV124 E-09	Reset behavior test waveform	
		Ubmin	Holding voltage	
	Off	Turn on/off this function		
	On			
E-11	LV124 E-11	Start pulses		
	Cold-Start	Cold start		
		Normal: normal pulse		
		Severe: severe pulse		
	Warm-Start	Warm start		
	Off	Turn on/off this function		
	On			
E-12	LV124 E-12	Voltage curve with intelligent generator control		

			ΔU	Voltage drop between DUT and battery terminals
			Off	Turn on/off this function
			On	

3.21.1 Automotive Starting Waveform

IT6500C models have built in DIN40839 waveform. This test verifies the behavior of a DUT during and after cranking. This waveform can reproduce the voltage curve for automotive power network confirms to DIN 40839 standard, thus facilitating quick call by customers.

For automotive startup voltage waveform, the startup voltage can also be set based on customers' requirements. In this way, the user can create waveform between 8V to 32V.




Note

When recalling the DIN40839 waveform, to ensure the validity of the DIN40839 waveform, the user needs to enable the internal load function at first and then set the current of internal load to the maximum value. Please refer to 3.14 Load Function for the detailed operation.

● DIN40839 for 12V system:

Steps	Voltage (V)	Current(A)	Width(mS)	Slope(mS)
1	4.5	60	15	5
2	6	60	2000	5
3	12	60		10



● DIN40839 for 24V system:


Steps	Voltage (V)	Current(A)	Width(mS)	Slope(mS)
1	8V	60	50	10
2	12	60	2000	5
3	24V	60		10

How to recall "DIN40839 waveform" from menu (take 12V system as an example):

1. Press **[Shift]+ [I-set]** (Function) to enter the Menu operation.
2. Select Road-Vehicle with Left/Right key and press **[Enter]** for confirmation.
3. Select DIN40839 with Left/Right key and press **[Enter]** for confirmation.
4. Select On with Left/Right key and press **[Enter]** for confirmation.
5. Select 12V with Left/Right key and press **[Enter]** for confirmation.

6. DIN40839 appears at the right bottom of the panel.
7. Press **[On/Off]** to turn on power supply output.
8. Press **[Shift]+[Enter]** (Trigger) for trigger. The power supply will output based on set sequence. Trig mark is lit.
- Start up voltage waveform program through user-defined function.

The user can define the startup voltage, ranging from 8V to 32V. When the waveform program is divided into 8V-16V, the waveform is consistent with standard 12V; when the waveform program is divided into 16V-32V, the waveform is consistent with the standard 24V waveform. The waveform diagram is shown below.



Call the self-defined DIN waveform operation (taking 12.5V voltage waveform as an example):

1. Press **[Shift]+ [I-set]** (Function) to enter the Menu operation.
2. Select Road-Vehicle with Left/Right key and press **[Enter]** for confirmation.
3. Select On with Left/Right key and press **[Enter]** for confirmation
4. Select DIN40839 with Left/Right key and press **[Enter]** for confirmation.
5. Press Left/Right key to select **"User-defined"**. Press **[Enter]** for confirmation.
6. Set the startup voltage value, V=12.6V. Press **[Enter]** for confirmation.
7. DIN40839 appears at the right bottom of the panel.
8. Press **[On/Off]** to turn on power supply output.
9. Press **[Shift]+[Enter]** (Trigger) for trigger. The power supply will output based on set sequence. Trig mark is lit.

3.21.2 simulate the waveform to verify the anti-interference performance of the automotive electronics' products

IT6500C models have built-in ISO16750-2 waveforms. To verify the

anti-interference performance of the automotive electronics' products. Output pulse waveform completely meets the International Standard ISO-16750-2, convenient for quick recall by the user.




Note

When recalling the ISO16750-2 waveform, to ensure the validity of the waveform, the user needs to enable the internal load function at first and then set the current of internal load to the maximum value. Please refer to 3.14 Load Function for the detailed operation.


Short voltage drop

This test simulates the effect when a conventional fuse element melts in another circuit.

■ 12V system



■ 24V system



How to recall "Short voltage drop" waveform from menu (take 12V system as an example):

1. Press **[Shift]+[I-set]** (Function) to enter the menu operation.
2. Press right direction key to select ISO16750-2, press **[Enter]**.
3. Press Left/Right direction keys to select "Short", press **[Enter]**.
4. Press right direction key to select "On", press **[Enter]**.
5. Press Up/Down direction key to select "12V", press **[Enter]**.
6. VFD will display ISO-Short in the lower right corner.
7. Press **[On/Off]**, turn on the output.
8. Press **[Shift]+[Enter]** (Trigger) to generate a trigger signal. The DC source will output Short voltage drop waveform. The Trig indicating lamp will be lit and display on the VFD.




Note

Please make sure the trigger source is selected in MANUAL item in above operations (refer to step 8th). And user need to turn on the internal load to speed up the falling time during ISO16750-2 waveform operations.

Reset Test

This test verifies the reset behavior of the DUT at different voltage drops. This test is applicable to equipment with reset function, e.g. equipment containing microcontroller.

Apply the test pulse simultaneously in figure below to all relevant inputs (connections) and check the reset behavior of the DUT. Decrease the supply voltage by 5 % from the minimum supply voltage, U_{Smin} , to $0,95U_{Smin}$. Hold this voltage for 5 s. Raise the voltage to U_{Smin} . Hold U_{Smin} for at least 10 s and perform a functional test. Then decrease the voltage to $0,9U_{Smin}$. Continue with steps of 5 % of U_{Smin} , as shown in Figure 6, until the lower value has reached 0 V. Then raise the voltage to U_{Smin} again.



How to recall "Profile for the reset test" waveform from menu (take 12V system as an example):

1. Press **[Shift]+ [I-set]** (Function) to enter the menu operation.
2. Press Right direction key to select ISO16750-2, press **[Enter]**
3. Press Up/Down direction keys to select "Reset", press **[Enter]**.
4. VFD display **Usmin...**, press **[Enter]** to confirm. VFD will display $U_{Smin}=12.000V$, user can select the U_{Smin} level.
5. Press Right direction key to "On", press **[Enter]**.
6. VFD will display ISO-Reset in the lower right corner.
7. Press **[On/Off]**, turn on the output.
8. Press **[Shift]+[Enter]** (Trigger) to generate a trigger signal. The DC source will output Short voltage drop waveform. The Trig indicating lamp will be lit and display on the VFD.




Note

Please make sure the trigger source is selected in MANUAL item in above operations(refer to step 8th). And user need to turn on the internal load to speed up the falling time during ISO16750-2 waveform operations.

Starting Waveform

This test verifies the behavior of a DUT during and after cranking.

Apply the starting profile ten times, as specified in Figure and Table below simultaneously to all relevant inputs (connections) of the DUT. A break of 1 s to 2 s between the starting cycles is recommended. One or more profiles as described in Tables 3 and 4 shall be chosen in accordance with the application.



- Standards for 12V system:
Curve should be selected based on actual test requirements. To create waveform within 12V, follow the set standards as below:

Levels/voltages/duration of starting profile				
I	II	III	IV	Tolerances
$U_S = 8 \text{ V}$	$U_S = 4,5 \text{ V}$	$U_S = 3 \text{ V}$	$U_S = 6 \text{ V}$	$+ 0,2 \text{ V}$
$U_A = 9,5 \text{ V}$	$U_A = 6,5 \text{ V}$	$U_A = 5 \text{ V}$	$U_A = 6,5 \text{ V}$	
$t_r = 5 \text{ ms}$				$\pm 10 \%$
$t_6 = 15 \text{ ms}$				
$t_7 = 50 \text{ ms}$				
$t_8 = 1 \text{ s}$	$t_8 = 10 \text{ s}$	$t_8 = 1 \text{ s}$	$t_8 = 10 \text{ s}$	
$t_f = 40 \text{ ms}$	$t_f = 100 \text{ ms}$	$t_f = 100 \text{ ms}$	$t_f = 100 \text{ ms}$	

- Standards for 24V system:

Levels/voltages/duration of starting profile			
I	II	III	Tolerances
$U_S = 10 \text{ V}$	$U_S = 8 \text{ V}$	$U_S = 6 \text{ V}$	+ 0,2 V
$U_A = 20 \text{ V}$	$U_A = 15 \text{ V}$	$U_A = 10 \text{ V}$	
$t_r = 10 \text{ ms}$			$\pm 10 \%$
$t_6 = 50 \text{ ms}$			
$t_7 = 50 \text{ ms}$			
$t_8 = 1 \text{ s}$	$t_8 = 10 \text{ s}$	$t_8 = 1 \text{ s}$	
$t_f = 40 \text{ ms}$	$t_f = 100 \text{ ms}$	$t_f = 40 \text{ ms}$	

How to recall "Starting Profile" waveform from menu (take 12V system as an example):

- Press **[Shift]+[I-set]** (Function) to enter the menu operations.
- Press Right direction key to select ISO16750-2, press **[Enter]**.
- Press Left/Right direction keys to select "Start", press **[Enter]**.
- Press Right direction key to "On", press **[Enter]**.
- Press Left/Right direction keys to select 12V/24V, and set the levels, press **[Enter]**.
- VFD will display ISO-Start in the lower right corner.
- Press **[On/Off]**, turn on the output.
- Press **[Shift]+[Enter]** (Trigger) to generate a trigger signal. The DC source will output Short voltage drop waveform. The Trig indicating lamp will be lit and display on the VFD.



Note

Please make sure the trigger source is selected in MANUAL item in above operations(refer to step 8th). And user need to turn on the internal load to speed up the falling time during ISO16750-2 waveform operations.


Load dump dynamic behavior

This test is a simulation of load dump transient occurring in the event of a discharged battery being disconnected while the alternator is generating charging current with other loads remaining on the alternator circuit at this moment.

- The amplitude of load dump is determined by the rotational speed of alternator and the strength of magnetic field in the case of disconnection of the battery.
- The pulse duration of load dump is mainly determined by the time constant and pulse amplitude of the excitation circuit.

Inside most novel alternator, the amplitude of load dump is decreased by increasing the limiter diode (clamping diode). The load dump may be caused by cable corrosion, poor cable contact or disconnecting the battery intentionally when the engine is running.

The pulse shape and parameters for an alternator without centralized load dump suppression are given in follow.



TEST PULSE 5A & 5C

Description:

t : time

U : test voltage

t_d : Duration of pulse

t_r : Rising Slope


U_A : Supply Voltage for generator in operation(see ISO 16750-1)

U_S : supply Voltage

Parameter	Type of system		Minimum test requirements
	$U_N=12V$	$U_N=24V$	
$U_S^a(V)$	$79 \leq U_S \leq 101$	$151 \leq U_S \leq 202$	10 pulses at 1 min intervals
$R_i^a(\Omega)$	$0.5 \leq R_i \leq 4$	$1 \leq R_i \leq 8$	
$t_d(ms)$	$40 \leq t_d \leq 400$	$100 \leq t_d \leq 350$	

$t_r(\text{ms})$	10^0_{-5}	10^0_{-5}	
^a If not otherwise agreed, use the upper voltage level with the upper value for internal resistance or use the lower voltage level with the lower value for internal resistance.			

LOAD DUMP, SINGLE PULSE - WITH CENTRALIZED LOAD DUMP SUPPRESSION



TEST PULSE 5B

t: time

U: test voltage

t_d : Duration of pulse

t_r : Rising Slope

U_A : Supply Voltage for generator in operation(see ISO 16750-1)

U_S : supply Voltage

U_S^* : supply voltage with load dump suppression

Parameter	Type of system		Minimum test requirements
	$U_N=12V$	$U_N=24V$	
$U_S^a(V)$	$79 \leq U_S \leq 101$	$151 \leq U_S \leq 202$	5 pulses at 1 min intervals
$U_S^*(V)$	35	As specified by customer (typical value 58)	
$R_i^a(\Omega)$	$0.5 \leq R_i \leq 4$	$1 \leq R_i \leq 8$	
$t_d(ms)$	$40 \leq t_d \leq 400$	$100 \leq t_d \leq 350$	
$t_r(ms)$	10^0_{-5}	10^0_{-5}	
^a If not otherwise agreed, use the upper voltage level with the upper value for internal resistance or use the lower voltage level with the lower value for internal resistance.			

The following general considerations of the dynamic behavior of alternators during load dump apply:

- The internal resistance of an alternator, in the case of load dump, is mainly a function of alternator rotational speed and excitation current.
- The internal resistance, R_i , of the load dump test pulse generator shall be obtained from the following relationship

$$R_i = \frac{10 \times U_{nom} \times N_{act}}{0.8 \times I_{rated} \times 12000 \text{min}^{-1}}$$

where:

- U_{nom} : is the specified voltage of the alternator
- I_{rated} : is the specified current at an alternator speed of 6000 min⁻¹ (as given in ISO 8854)
- N_{act} : is the actual alternator speed, in reciprocal minutes

The pulse is determined by the peak voltage V_s , the internal resistance R_i , and the pulse duration t_d ; in all cases small values of V_s are correlated with small values of R_i and t_d , and high values of V_s with high values of R_i and t_d . For the test voltage U_A please refer to ISO16750-1.

3.21.3 42V Road vehicles — Electrical and electronic equipment for a supply voltage of 42 V — Electrical loads

A test wave completely conforming to International Standard ISO21848 is built inside the device, which can be used for the test of Electrical and electronic equipment for a supply voltage of 42V - Electrical loads. The user can directly and quickly recall this function during test.




Note

When recalling the ISO21848 waveform, to ensure the validity of the waveform, the user needs to enable the internal load function at first and then set the current of internal load to the maximum value. Please refer to 3.14 Load Function for the detailed operation.

$U_{max,dyn}$ test pulse

Detect the function when the DUT is under maximum dynamic Voltage $U_{max,dyn}$, and simulate the maximum dynamic Voltage of high-energy pulse raised from throw load in 42V electrical system, where the upper limit is the protection voltage of throw load.

Apply 1 test pulse to the DUT, as shown below:



t: time (in ms)


U: Voltage (in V)

Supply Voltage Transient Drop

Simulate the affect from short circuit when fuse element of another circuit is melt. Detect the function status of the DUT at transient drop of Voltage.

When the given test pulse is applied at all input terminals of the DUT, the

rise and fall time between U_{low} and 16V level shall not be longer than 10ms.




Reset Performance at Transient Drop of Voltage

Detect the reset performance of the DUT at different Voltage drops. Applicable for devices with reset function (for example, device installed with one or several micro controllers)

As shown in the figure, apply test pulse and detect the reset performance of the DUT.


The supply voltage drops from U_{low} to $0.95U_{low}$ by 5% and keeps for 5s, and then rise to U_{low} and keep for at least 10s for function test. Then, drop Voltage to $0.9U_{low}$, and so on. As shown in the figure, drop the voltage from U_{low} to 0V by 5% and raise the voltage to U_{low} . The Rise and Fall time shall be between 10ms and 1s.



Start-up Characteristics

Detect DUT characteristics before and after vehicle startup.

Apply the startup characteristic parameters as shown in the figure and table to related input terminals of the DUT simultaneously.



t: time (in s)
U: voltage (in V)
 U_S : 18V
 U_A : 21V
 U_T : 42V
t1: 5ms
t2: 15ms
t3: 50ms
t4: 10000ms
t5: 100ms

3.21.4 SAEJ1113-11 Waveform protocol




Note

When recalling this waveform, to ensure the validity of the waveform, the user needs to enable the internal load function at first and then set the current of internal load to the maximum value. Please refer to 3.14 Load Function for the detailed operation.

Test 2b


Transient from DC motors acting as generators after ignition switch OFF



Parameters	12V System	24V System
V_S	10V	20V
R_i	$\leq 0.05\Omega$	$\leq 0.05\Omega$
t_d	0.2 to 2s	0.2 to 2s
t_1	1ms $\pm$ 50%	1ms $\pm$ 50%
t_r	1ms $\pm$ 50%	1ms $\pm$ 50%
t_6	1ms $\pm$ 50%	1ms $\pm$ 50%

Test 4

Starter motor engagement disturbance pulse.



Parameters	12V System	24V System
V_S (From V_B)	-4V to -7V	-5V to -16V
V_a (From V_B)	-2.5 to -6V with $ V_a \leq V_S $	-5 to -12V with $ V_a \leq V_S $
R_i	0Ω to 0.02Ω	0Ω to 0.02Ω
t_7	15 to 40ms ⁽¹⁾	50 to 100ms ⁽¹⁾
t_8	≤50ms	≤50ms
t_9	0.5 to 20s ⁽¹⁾	0.5 to 20s ⁽¹⁾
t_{10}	5ms	10ms
t_{11}	5 to 100ms ⁽²⁾	10 to 100 ms ⁽³⁾

1. The value used should be agreed between the vehicle manufacturer and the equipment supplier to suit the proposed application.

2. t_{11} =5 ms is typical of the case when engine starts at the end of the cranking period, while t_{11} =100 ms is typical of the case when the engine does not start.

3. t_{11} =10 ms is typical of the case when engine starts at the end of the cranking period, while t_{11} =100 ms is typical of the case when the engine does not start.

Test 5

For the details, please refer to the 3.20.2 simulate the waveform to verify the anti-interference performance of the automotive electronics' products.

3.21.5 LV124

IT6500C series all come with built-in curves which meet general requirements, test conditions and tests of electrical and electronic components in motor vehicles up to 3.5 t.




Note

When recalling this waveform, to ensure the validity of the waveform, the user needs to enable the internal load function at first and then set the current of internal load to the maximum value. Please refer to 3.14 Load Function for the detailed operation. And the CC/CV priority of power need to be CV option.

E-02 Transient Overvoltage Pulse


Transient overvoltages may occur in the electric system due to the switching off

of loads and due to short accelerator tip-ins. These overvoltages are simulated by means of this test. This test may be used for the electrical life test. The test pulse of E-02 Transient overvoltage is shown in the next figure.




E-04 Jump Start

External starting of the vehicle is simulated. The maximum test voltage results from commercial vehicle systems and their increased power supply voltage. The test pulse of E-04 Jump start is shown in the next figure.




E-05 Load Dump

Dumping of an electric load, in combination with a battery with reduced buffering ability, results in an energy-rich overvoltage pulse due to the generator characteristics. This pulse is simulated by means of this test.




E-07 Slow Decrease and Increase of the Supply Voltage

The slow decrease and increase of the supply voltage is simulated as it occurs during the slow discharging and charging procedure of the vehicle battery.




E-08 Slow Decrease, Quick Increase of the Supply Voltage

This test simulates the slow decrease of the battery voltage to 0 V and the sudden reconnection of the battery voltage e.g. by means of applying a jump start source.



E-09 Reset Behavior


The reset behavior of a component in its environment is simulated and tested. Test boundary conditions (e.g. assembly, terminal, system) must be described in detail. During operation, an arbitrary sequence of repeated switching-on/off procedures occurs; this must not lead to an undefined behavior of the component. The reset behavior is represented by a voltage variance and a time variance. Two different test sequences are required to simulate different switch-off times. A component must always undergo both sequences.




E-11 Start Pulses

When starting the engine, the battery voltage drops to a low value for a short period and then slightly rises again. Most components are activated directly before starting for a short period, then deactivated during starting and activated again after starting when the engine is running. This test serves to verify normal operation under these conditions. The starting process may be performed under different vehicle starting conditions, cold start and warm start. In order to cover both cases, two different test sequences are required. A component must always undergo both sequences.

● Cold Start Test Pulse




- Warm Start Test Pulse



E-12 Voltage Curve with Intelligent Generator Control

The behavior of the electric system when intelligent generator controls are used is simulated. The behavior goes from DC to voltage changes within max. 300 ms.



3.22 DC Internal Resistance Measure


In addition to various test functions of original power supply, this Series of power supply provides measure function for internal resistance at charging and discharging the battery, which needs no various detection devices.

To measure the DUT internal resistance, turn on the DC internal resistance measure function in the menu and set the DUT capacity. During measure, the Meter interface will display the real-time DC internal resistance of the DUT.

DCR	DC internal resistance measure	
	Battery Capacity = 0AH	Input battery capacity
	Off/On	Turn off/on DC internal resistance measure function

To turn on the DC internal resistance measure, follow the steps below:

1. Press [**Shift**]+[**I-set**](Function) to enter the menu for operation.
2. Press  to select **DCR** in the menu and press [**Enter**] for confirmation.
3. Set battery capacity, where Battery Capacity =1AH.
4. Select On to turn on DC internal resistance measure function.
5. The Meter interface displays as follows. The precision of different models are different, and the interface displays are not exactly the same. Please refer to the actual display.



3.23 Parallel Operation


CAUTION

- When connecting the system bus, please note the built-in terminal matching resistance at the rear panel. If the resistance is removed, the instrument may not work properly. The user can install the terminal matching resistance on the Input end of the first system bus and the Output end of the last system bus.
- The system bus interface is not isolated from the output electrode. After power on, it is not allowed to insert or pull out the bus and terminal matching resistance.

This series of power supply supports mutual parallel operation of same models and to increase output power and output current. In addition, active current sharing is provided for parallel instruments.

The figure below shows 3 pcs power supplies in parallel, in which, the system bus is used for master-slave connection.

Fig.1 Schematic Diagram of 3 Pcs Power Supplies in Parallel



The master-slave connection for configuring 3 pcs power supplies is as follows:

1. Configure one power supply as the Master and the other power supplies as Slave. Press the composite key **[Shift]+[P-set]**(Menu) to enter the System Menu.
2. Press the Right key to select **"CONFIG"** and press **[Enter]** to enter the Configuring Menu.
3. Press the Right key to select **"Parallel"** and press **[Enter]** for parallel setting.

- Single: Single mode.
- Slave: Slave mode.
- Master: Master mode. If Master mode is selected, you need to set the number of Slaves for the Master.


Mount: total number of instruments in parallel. For example, Mount=3.

4. After setting of host and slave, switch off the power supply. Connect the networking.
5. Connect the networking as shown above. Please connect the network after parallel setup. Otherwise, at start up, the power supply will detect parallel setup fault and fail to start up.

3.24 Rear Panel Terminal Functions

If the tested instrument consumes large current, a large voltage drop will be detected in connection line between tested instrument and power supply terminal. To ensure measurement accuracy, a remote sense measurement terminal is provided at power supply rear panel to compensate voltage drop lost in wire.

When the power supply is used for measuring battery charge in actual applications, the voltage drop of the wire will lead to voltage inconsistency of both ends and inconsistency of the cutoff voltage of power supply and the actual voltage of battery, resulting in inaccurate measurement.




- **V0+, V0-**: output terminals
- **Vs+, Vs-**: remote sense terminal

When using the remote sense function, please cut off the connection wire between **V0+** and **Vs+**, so will the line between **V0-** and **Vs-** terminals. Then extending lines from Vs+ to the positive terminal of undertested product and line from Vs- to the negative terminal of undertested product.

Use local sense:

Local sense doesn't compensate the voltage drop on the connection wire, the operation is:

1. Connect the V0+ and Vs+, V0- and Vs- for short circuit using the short clips on the back panel of the instrument or electric wire. When using local sense, the remote sense terminal cannot be disconnected. illustrated below.



2. Connect the positive and negative terminals of the rear panel to the DUT.




Note

DO not disconnect the wires if remote sense is not used. Doing so will cause erratic behavior and may damage the power supply under certain conditions

Use remote sense:

Disconnect the wires between **V0+** and **Vs+**, and **V0-** and **Vs-** pins if you want to use remote sense function. Then lead a wire from Vs+, Vs- pins and connect to the DUT.

1. Disconnect the wires/short clips between V0+ and Vs+, V0- and Vs-.
2. Connect the **Vs+** to the DUT's positive (+) terminal, and connect the **Vs-** to the DUT's negative (-) terminal.
3. Connect wires from **V0+**, **V0-** to the device under test.



NOTE

In order to ensure the stability of the system, using armored twisted pair cable between the remote sense terminal of IT6500C and DUT.

Please note that the positive and negative polarity when wiring, otherwise it will damage the instrument!

Remote Sense Protection(>Sense-Protect)

The power supply output will be immediately switched to Off and the buzzer will sound if the sense terminals are reversed. The VFD display screen will display "Sense Reverse Prot". And please press [On/Off] to clean the protection.

When power supply in sense reverse protection state, please check the anode and cathode of the sense terminal must be connected properly.

3.25 Analogue Interface (Enhanced Isolation)

A DB25 analog interface is set at the rear panel of the power supply, through which, you can connect the external voltage (0V-5V/0V-10V) or external resistance (0K Ω -5K Ω /0K Ω -10K Ω) to program output voltage or current on 0-full range. At the same time, with analog monitoring function (0V-5V/0V-10V), you can monitor the output voltage or current on 0-full range.

Analog signal bandwidth is less than 100Hz,. support any waveform within signal bandwidth. When the program signal frequency or amplitude exceeds output capacity, the output amplitude will be automatically limited.

In parallel operation, you can program or monitor output through the host analog interface. The 0V-5V/0V-10V program and monitoring range is changed to 0-full range of parallel machine. Safe electrical isolation is set between this analog interface and output electrode.

To run this function, you need to set the parameters below:


Monitor	10V(Def)	10V monitoring mode options
	5V	5V monitoring mode options
Ext- Ctrl	External control mode and related parameter setting	
	Voltage (Def)	Voltage setting mode selection
	10V(Def)/5V	10V or 5V setting mode selection, select by Left/Right key.

Resistance	Resistance setting mode selection
10k(Def)/5k	10K or 5K setting mode selection, select by Left/Right key.
Off	Disable or enable this function. Select by up/down key.
On	

The above parameters can be selected through the configuration menu.

1. Press the **[Shift]+[P-set]** (Menu) to enter the menu.
2. Press the Right Key to select **CONFIG** and press **[Enter]** to enter the configuration menu;
3. Press the Right Key to select the Ext-Ctrl and press **[Enter]** to enter the configuration of external analog parameters. When setting every item, please use the Up/Down Key for selection.

After selecting the **Ext-Ctrl** as “On”, exit the Menu. At this time, the Rear indicator on the VFD status bar will be lighted on and the right corner will display “Analog”.



Pin	Name	Instruction
Pin 1 and Pin 14	CANH CANL	Pin 1 used for CAN H interface, and Pin 14 used for CAN L interface.
Pin 2	+12V	Power supply output 12V, driving capacity 0.1A
Pin 3	Shut Off	Used for switching off the function under emergency status (In general circumstances, the pin is suspended, and defaulted to low level); when external high level is connected, output is off.
Pin 15	EXT ON	Used for controlling output On/Off of the power supply; default setting is high level. Output is controlled by On/Off; when external low level is connected, or when it is short circuited to DGND, output is switched off. At this time, setting of output On/Off fails.
Pin 16	Power OK	Used for indicating whether the power output is normal; if so, output 5V; in case of power supply failure, output 0V.
Pin 17	TrigIN	Input signal of reverse protection mode. When input is low level, alarm "OutPut Reverse Protect" fault. At the mean while, in external trigger mode, when input is low level, then actualize trigger function

Pin	Name	Instruction
Pin 6	TrigOUT	Output signal of reverse protection mode. When power supply output is On, this pin outputs high level; when this power supply output is Off, this pin outputs low level; it can be used for synchronous control of On/Off for other devices with driving capacity of 5V/5mA
Pin 18	+5V	The power supply outputs 5V voltage, which is used for digital power supply with driving capacity of 0.1A.
Pin 19 and Pin 20	CV_CC+ CV_CC-	The output between these two pins is used for indicating the working status of power supply; under CV mode, the output between these two pins is 5V; and under CC mode, - 5V.
Pin 21	Voltage Program (Voltage setting)	Output voltage of analog control: In setting the Voltage and 10v, the input analog range should be 0-10V voltage, and the regulated output voltage should be from 0 to full range; In setting the Voltage and 5v, the input analog range should be 0-5V voltage, and the regulated output voltage should be from 0 to full range; In setting the Resistance and 10K, the input analog range should be 0-10K resistance, and the regulated output voltage should be from 0 to full range; In setting the Resistance and 5K, the input analog range should be 0-5K resistance, and the regulated output voltage should be from 0 to full range;
Pin 22	REF_10V	The 10V reference voltage output by the power supply can be connected to a resistance subdivision for analog control.
Pin 23	Current Program (Current Setting)	Output current of analog control: In setting the Voltage and 10v, the input analog range should be 0-10V voltage, and the regulated output current should be from 0 to full range; In setting the Voltage and 5v, the input analog range should be 0-5V voltage, and the regulated output current should be from 0 to full range; In setting the Resistance and 10K, the input analog range should be 0-10K resistance, and the regulated output current should be from 0 to full range; In setting the Resistance and 5K, the input analog range should be 0-5K resistance, and the regulated output current should be from 0 to full range;
Pin 24	Voltage Monitor (Voltage monitoring)	The actual value from monitoring is the corresponding monitor voltage value. For example, when the analog voltage is 10V, power supply control voltage 0~80V and the power supply output voltage 20V, this pin will output 2.5V voltage. Similarly, when the analog voltage is 5V, control voltage 0~80V and the power supply output voltage 20V, this pin will output 1.25V voltage.
Pin 25	Current Monitor (Current monitoring)	The actual value from monitoring is the corresponding monitor voltage value. For example, when the analog voltage is 10V, power supply control current 0~120A and the power supply output current 12A, this pin will output 1V voltage. Similarly, when the analog voltage is 5V, control current 0~120A and the power supply output voltage 12A, this pin will output 0.5V voltage.
Pins 9, 10, 11, 12 and 13	Connection to AGND	Ground wires for analog interfaces (including Pin 21 VPRG, Pin 22 REF_10V, Pin 23 IPRG, Pin 24 VMON, Pin 25 IMON).
Pins 4, 5, 7,8	Internal connection to DGND	Ground wires for Pin 15 EXT ON, Pin 3 SHUT OFF, Pin 16 POWER OK, Pin 17 TrigIN, Pin 6 TrigOUT, pin 19 CV_CC+ and Pin 20 CV_CC-.



NOTE


- The value of the output current must be under the definition value of the current which is driving capacity in the DB25 pins of the power supply. Otherwise, the power supply will be damaged.
- The maximum digital signal input voltage $\leq 5V$
- The maximum analog signal input voltage $\leq 12V$

Voltage Setting (Voltage Program)

This function enables change of voltage output through external analog signal by connecting external DC voltage (under voltage mode) or an external resistor (under resistor mode) to Pin 21. To enable this function, the output control should be under the external analog control mode. Used for controlling the external voltage range of full-scale output voltage or the resistor can be selected from 0~5V/0~10V or 0~5K Ω /0~10K Ω . To switch on the voltage setting, open the MENU (Menu) → CONFIG (Configure) → Ext-Ctrl (External Analog Control). Press the Right Key to select Voltage (or Resistance). Press the Up/Down Key to select the voltage mode or resistor mode.


- Voltage Mode

Under voltage mode, the user can set the voltage output value of power supply through Pin 21.



- Resistor Mode

Pin 21 and Pin 13 (GND wire) can be connected to a resistor for setting the output voltage value of the power supply.



To set the 0~5V/0~10V or 0~5K Ω /0~10K Ω external analog setting range, open the MENU (Menu) → CONFIG (Configure) → Ext-Ctrl (External Analog Control). Press the Right Key to select Voltage (or Resistance). Press the Right Key to select 5V/10V or 5K Ω /10K Ω within the full scale scope.


Current Setting (Current Program)

This function enables change of current output through external analog signal by connecting external DC voltage (under voltage mode) or an external resistor (under resistor mode) to Pin 23. To enable this function, the output control should be under the external analog control mode. Used for controlling the external voltage range of full-scale output voltage or the resistor can be selected from 0~5V/0~10V or 0~5K Ω /0~10K Ω . To switch on the current setting, open the MENU (Menu) → CONFIG (Configure) → Ext-Ctrl (External Analog

Control). Press the Right Key to select Voltage (or Resistance). Press the Up/Down Key to select the voltage mode or resistor mode.


- Voltage Mode

Under the voltage mode, the user can set the voltage output value of the power supply through Pin 23.



- Resistor Mode

Pin 23 and Pin 13 (GND wire) can be connected to a resistor for setting the output voltage value of the power supply.



To set the 0~5V/0~10V or 0~5KΩ/0~10KΩ external analog setting range, open the MENU (Menu) → CONFIG (Configure) → Ext-Ctrl (External Analog Control). Press the Right Key to select Voltage (or Resistance).


Press the Right Key to select 5V/10V or 5KΩ/10KΩ within the full scale scope.

Voltage monitoring

This function enables monitoring of voltage output via Pin 24 or the GND pin (i.e., Pin 13), which can be connected to a digital voltmeter (DVM). To use this function, the output control should be under the external analog control mode. The output voltage monitoring range (which reflects the power supply output voltage from zero to full scale) can be selected from 0-10V or 0-5V. To switch on the monitoring range setting, open the MENU (Menu) → CONFIG (Configure) → Monitor (External monitor mode). Press the Right Key to select Voltage (or Resistance).

Press the Right Key to select the output voltage monitoring range (0-10V or 0-5V).

The connection setting of digital voltmeter is shown below.




Current Monitoring

This function enables monitoring of current output via Pin 25 or the GND pin (i.e., Pin 13), which can be connected to a digital voltmeter (DVM). To use this function, the output control should be under the external analog control mode. The output current monitoring range (which reflects the power supply output current from zero to full scale) can be selected from 0-10V or 0-5V. To switch on the monitoring range setting, open the MENU (Menu) → CONFIG (Configure) → Monitor (External monitor mode).

Press the Right Key to select the output current monitoring range (0~10V or 0~5V).

The connection setting of digital voltmeter is shown below.



Chapter4 Remote Control

IT6500C have five standard communication interfaces: RS232, USB, GPIB, LAN and CAN. The customer can choose any one according to his demands.

4.1 RS232 Interface

Using a cable with two COM ports to connect power supply and PC. Then please press **[Shift] + [P-set]** (Menu) button to enter the menu to configure the communication parameters. You could do the secondary development with all SCPI commands.



Note

The setup about RS232 in the program should agree with the configuration in the system set. If you want to change the communication parameters, please press **[Shift] + [P-set]** (Menu) button to enter the system set.

RS-232 Data style

RS232 with start bit and stop bit. The start bit and stop bit cannot be edited. While you could select the odd parity or even parity under the system set.

Odd or EVEN options have been saved in the nonvolatile memory.

Baudrate

Edit baudrate: press **[Shift] + [P-set]** (Menu) to enter the menu setup, you could select the baudrate among the following options:


4800/ 9600/ 19200/ 38400/ 57600/ 115200

RS-232 connection

Please use a straight-through RS232 cable with DB9 interface and connect the RS232 serial port with the controller's serial port(for example. PC). Form 2-2 gives a detailed description for each pin.

RS-232 pins description

Pin	description
1	connectionless
2	TXD, transmit data
3	RXD, receive data
4	connectionless
5	GND
6	connectionless
7	connectionless
8	connectionless
9	connectionless



RS-232 Troubleshooting:

If you meet some problems when communicating with PC by RS232 interface, please check the following items:

- Please check the parameters setting
PC and power supply must have the same configuration in the following items: baudrate, parity bit, data bit and flow control. Please note that power supply has been configured with a start bit and stop bit(the two values are fixed).
- Check the cable
Ensure you have used the correct communication cable. Please pay attention that some cable may not have a correct internal wiring even it is with a appropriate DB9 interface.
The RS232 communication cable should have been connected to a correct serial port of the PC.

Communication Setup

Please ensure the PC and power supply have the same configuration in the following items.

Baud rate: 9600(4800, 9600, 19200, 38400, 57600, 115200).You could enter the system menu to set the baudrate.

Data bit: 8

Stop bit: 1

Parity bit: (none, even, odd)

EVEN **8 data bits have even parity**

ODD **8 data bits have odd parity**

NONE **8 data bits have no parity**

Native machine address: (0 ~31, factory default is 0)

Parity= None	Start Bit	8 Data Bits	Stop Bit
-----------------	-----------	-------------	----------

4.2 USB Interface

Use a cable with two USB ports to connect power supply and PC. You can program through USB interface to achieve all functions of power supply.

The functions of USB488 interface are as follows:

- Interface is 488.2 USB488 interface
- Receive the following request: REN_CONTROL, GO_TO_LOCAL, and LOCAL_LOCKOUT
- When the interface receives MsgID = TRIGGER USBTMC command, it will transmit the TRIGGER command to the function layer

The functions of power supply's USB488 are as follows:

- receive all SCPI commands
- device is SR1 enabled
- device is RL1 enabled
- device is DT1 enabled

4.3 GPIB Interface

Use a IEEE488 bus to connect GPIB interfaces of power supply and PC. Please ensure that the screws have been screwed down in order to have a full connection. Then press **[Shift] + [P-set]** (Menu) to enter the system menu to set the address. The address range of power supply is 1-30. After you set the

address, please press **[Enter]** button to confirm. GPIB address is saved in nonvolatile memory.

4.4 LAN Interface

Press **[Shift]** + **[P-set]** (Menu) button to enter the system set. Please select "LAN" in the Communication from System and then configure Gateway, IP, Mask and SocketPort in the LAN option.

Connect the LAN interface of power supply to the computer with a reticle (crossed). The gateway address should be consistent with that of the PC, and the IP address should be at the same network segment with the PC's IP address.

4.5 CAN Communication Port

There is one DB25 interface at the rear panel, and the pin definition is shown below. The user can use this terminal for PC connection; to activate connection, be sure that the values set in the System menu are same as the corresponding values set in PC.



Note

CAN setting in the program shall be consistent with the one set in the System menu of front panel. To query and change, press the composite key **[Shift]** + **[P-set](Menu)** to enter the setting screen in System menu for query and change. For details, refer to 3.9 System Menu.

Baud Rate

In the front panel **[Shift]** + **[P-set](Menu)**, under the System menu, the user can select one Baud rate stored in NVM:

20K|40K|50K|80K|100K|125K|150K|200K|250K|400K|500K|1000K

CAN Pin Definition

Use DB25 interface for connection. CAN interface pin is as follows.

CAN interface pin

Pin No.	Description
1	CANH
14	CANL

CAN Troubleshooting:

If CAN connection fails, check that:

1. The PC and power supply have same Baud rate.
2. Appropriate interface pin or adapter is used, as described in CAN connector.
3. The interface cable is correctly connected (CAN_H to CAN_H, CAN_L to CAN_L).

Check whether 120 Ω terminal resistance is connected.

Setting Communication

Before running communication, please match the power supply parameters with the PC parameters as shown below.

Baud rate: 20K(20K, 40K, 50K, 80K, 100K, 125K, 150K, 200K, 250K, 400K, 500K, 500K). You can enter the System menu through panel and set the communication Baud rate.

Addr.: 1-127

Prescale (Pres): Not settable. Change with Baud rate setting.

PTS (BS1): Not settable. Change with Baud rate setting.

PBS (BS2): Not settable. Change with Baud rate setting.

Baud rate	(Prescale)	PTS	PBS
20k	150	1	6
40K	75	1	6
50K	60	1	6
80K	75	1	1
100K	30	1	6
125K	30	0	5
150K	20	6	1
200K	15	1	6
250K	15	1	5
400K	15	1	1
500K	6	1	6
1000K	3	1	6

Chapter5 Specification

This chapter will introduce the rated voltage, current, power and many other main parameters of IT6500C series.

5.1 Main technical parameters

Parameter		IT6512C	Version: V1.4
Output Rating (0 °C-40 °C)	Output Voltage	0-80V	
	Output Current	0-120A	
	Internal Sink Current ¹	0-50A	
	External Sink Current ¹	0-120A	
	Output Power	0-1800W	
	Internal Sink Power ¹	0-150W	
	External Sink Power ¹	0-5400W	
Output Resistance	Range	0-3.556Ω	
	Accuracy ²	0.25%+30mΩ*A	
	Resolution	0.1mΩ	
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+10mV	
	Current	≤0.01%+60mA	
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+30mV	
	Current	≤0.05%+120mA	
Setup Resolution	Voltage	10mV	
	Current	10mA	
	Power	0.1W	
Read Back Resolution	Voltage	10mV	
	Current	10mA	
	Power	0.1W	
Setup Accuracy ³ (within 12 months, 25°C±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+30mV	
	Current	≤0.2%+120mA	
	Power	1%+30W	
Read Back Accuracy ⁴ (within 12 months, 25°C±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+30mV	
	Current	≤0.2%+120mA	
	Power	1%+30W	
Ripple (20Hz -20MHz)	Voltage	≤80mVp-p	
	Current	≤0.05%+60mA _{rms}	
Setup Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+30mV	
	Current	≤0.02%+120mA	
Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+30mV	
	Current	≤0.02%+120mA	
Rise time(no load) ⁵	Voltage	≤10ms	
Rise time(full load) ⁵	Voltage	≤20ms	
Fall time(no load) ⁵	Voltage	≤30ms	
Fall time(full load) ⁵	Voltage	≤20ms	
Current seamless switching ⁶	-90%-90%	≤10ms	
	90%--90%	≤10ms	

Transient Response Time	Voltage	≤3ms
AC Input ⁷	Voltage	220V±10%
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+120mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+120mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+120mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+120mA
efficiency		80%
Remote Sense Compensation Voltage		3V
Command Response Time		20mS
Power Factor		0.99
Maximum input current ⁸		12A
Maximum input apparent power		2300VA
Storage temperature		-10℃-70℃
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)		500V
Series Number		≤2
Parallel Number		≤8
Parallel Number of Power Dissipater		1/2/3
Working temperature		0-40℃
Dimension (mm)	483mmW×105.4mmH×640.8mmD	
Weight(net)	17Kg	

Parameter		IT6522C	Version: V1.4
Output Rating (0℃-40℃)	Output Voltage	0-80V	
	Output Current	0-120A	
	Internal Sink Current ¹	0-50A	
	External Sink Current ¹	0-120A	
	Output Power	0-3000W	
	Internal Sink Power ¹	0-150W	
	External Sink Power ¹	0-9000W	
Output Resistance	Range	0-2.133Ω	
	Accuracy ²	0.25% + 30mΩ*A	
	Resolution	0.1mΩ	
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+10mV	
	Current	≤0.01%+60mA	
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+30mV	
	Current	≤0.05%+120mA	
Setup Resolution	Voltage	10mV	
	Current	10mA	
	Power	0.1W	
Read Back Resolution	Voltage	10mV	

	Current	10mA
	Power	0.1W
Setup Accuracy ³ (within 12 months, 25°C±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+30mV
	Current	≤0.2%+120mA
	Power	1%+30W
Read Back Accuracy ⁴ (within 12 months, 25°C±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+30mV
	Current	≤0.2%+120mA
	Power	1%+30W
Ripple (20Hz -20MHz)	Voltage	≤80mVp-p
	Current	≤0.05%+60mArms
Setup Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+30mV
	Current	≤0.02%+120mA
Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+30mV
	Current	≤0.02%+120mA
Rise time(no load) ⁵	Voltage	≤10ms
Rise time(full load) ⁵	Voltage	≤20ms
Fall time(no load) ⁵	Voltage	≤30ms
Fall time(full load) ⁵	Voltage	≤10ms
Current seamless switching ⁶	-90%-90%	≤10ms
	90%--90%	≤10ms
Transient Response Time	Voltage	≤3ms
AC Input ⁷	Voltage	220V±10%
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+120mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+120mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+120mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+120mA
efficiency		80%
Remote Sense Compensation Voltage		3V
Command Response Time		20mS
Power Factor		0.99
Maximum input current ⁸		19A
Maximum input apparent power		3800VA
Storage temperature		-10°C-70°C
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)		500V
Series Number		≤2
Parallel Number		≤8
Parallel Number of Power Dissipater		1/2/3
Working temperature		0-40°C
Dimension (mm)	483mmW×105.4mmH×640.8mmD	

Weight(net)	17Kg
--------------	------

Parameter		IT6532C	Version: V1.4
Output Rating (0 °C-40 °C)	Output Voltage	0-80V	
	Output Current	0-240A	
	Internal Sink Current ¹	0-100A	
	External Sink Current ¹	0-240A	
	Output Power	0-6KW	
	Internal Sink Power ¹	0-300W	
	External Sink Power ¹	0-18KW	
Output Resistance	Range	0-1.067Ω	
	Accuracy ²	0.25%+30mΩ*A	
	Resolution	0.1mΩ	
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+10mV	
	Current	≤0.01%+120mA	
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+30mV	
	Current	≤0.05%+240mA	
Setup Resolution	Voltage	10mV	
	Current	100mA	
	Power	0.1W	
Read Back Resolution	Voltage	10mV	
	Current	100mA	
	Power	0.1W	
Setup Accuracy ³ (within 12 months, 25°C±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+30mV	
	Current	≤0.2%+240mA	
	Power	1%+60W	
Read Back Accuracy ⁴ (within 12 months, 25°C±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+30mV	
	Current	≤0.2%+240mA	
	Power	1%+60W	
Ripple (20Hz -20MHz)	Voltage	≤80mVp-p	
	Current	≤0.05%+120mArms	
Setup Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+30mV	
	Current	≤0.02%+240mA	
Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+30mV	
	Current	≤0.02%+240mA	
Rise time(no load) ⁵	Voltage	≤10ms	
Rise time(full load) ⁵	Voltage	≤20ms	
Fall time(no load) ⁵	Voltage	≤30ms	
Fall time(full load) ⁵	Voltage	≤10ms	
Current seamless switching ⁶	-90%-90%	≤20ms	
	90%--90%	≤20ms	
Transient Response Time	Voltage	≤3ms	
AC Input ⁷	Voltage	220V±10%	
	Frequency	47Hz-63Hz	
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+30mV	
	Current	≤0.1%+240mA	
Setup stability-8h	Voltage	≤0.05%+30mV	

(%of Output +Offset)	Current	$\leq 0.1\%+240\text{mA}$
Readback stability-30min (%of Output +Offset)	Voltage	$\leq 0.05\%+30\text{mV}$
	Current	$\leq 0.1\%+240\text{mA}$
Readback stability-8h (%of Output +Offset)	Voltage	$\leq 0.05\%+30\text{mV}$
	Current	$\leq 0.1\%+240\text{mA}$
efficiency		80%
Remote Sense Compensation Voltage		3V
Command Response Time		20mS
Power Factor		0.99
Maximum input current ⁸		38A
Maximum input apparent power		7600VA
Storage temperature		-10℃-70℃
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)		500V
Series Number		≤ 2
Parallel Number		≤ 8
Parallel Number of Power Dissipater		2/4/6
Working temperature		0-40℃
Dimension (mm)	483mmW×194mmH×640.8mmD	
Weight(net)	35Kg	

Parameter		IT6542C	Version: V1.4
Output Rating (0℃-40℃)	Output Voltage	0-80V	
	Output Current	0-360A	
	Internal Sink Current ¹	0-150A	
	External Sink Current ¹	0-360A	
	Output Power	0-9KW	
	Internal Sink Power ¹	0-450W	
	External Sink Power ¹	0-27KW	
Output Resistance	Range	0-0.711Ω	
	Accuracy ²	0.25%+30mΩ*A	
	Resolution	0.1mΩ	
Line regulation ±(%of Output+Offset)	Voltage	$\leq 0.01\%+10\text{mV}$	
	Current	$\leq 0.01\%+180\text{mA}$	
Load regulation ±(%of Output+Offset)	Voltage	$\leq 0.01\%+30\text{mV}$	
	Current	$\leq 0.05\%+360\text{mA}$	
Setup Resolution	Voltage	10mV	
	Current	100mA	
	Power	0.1W	
Read Back Resolution	Voltage	10mV	
	Current	100mA	
	Power	0.1W	
Setup Accuracy ³ (within 12 months, 25℃±5℃) ±(%of Output+Offset)	Voltage	$\leq 0.05\%+30\text{mV}$	
	Current	$\leq 0.2\%+360\text{mA}$	
	Power	1%+90W	

Read Back Accuracy ⁴ (within 12 months, 25°C±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+30mV
	Current	≤0.2%+360mA
	Power	1%+90W
Ripple (20Hz -20MHz)	Voltage	≤80mVp-p
	Current	≤0.05%+180mA _{rms}
Setup Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+30mV
	Current	≤0.02%+360mA
Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+30mV
	Current	≤0.02%+360mA
Rise time(no load) ⁵	Voltage	≤10ms
Rise time(full load) ⁵	Voltage	≤20ms
Fall time(no load) ⁵	Voltage	≤30ms
Fall time(full load) ⁵	Voltage	≤10ms
Current seamless switching ⁶	-90%-90%	≤30ms
	90%--90%	≤30ms
Transient Response Time	Voltage	≤3ms
AC Input ⁷	Voltage	220V±10%
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+360mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+360mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+360mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+360mA
efficiency	80%	
Remote Sense Compensation Voltage	3V	
Command Response Time	20mS	
Power Factor	0.99	
Maximum input current ⁸	19A	
Maximum input apparent power	11400VA	
Storage temperature	-10℃-70℃	
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)	500V	
Series Number	≤2	
Parallel Number	≤8	
Parallel Number of Power Dissipater	3/6/9	
Working temperature	0-40℃	
Dimension (mm)	483mmW×283.2mmH×640.8mmD	
Weight(net)	53Kg	

Parameter		IT6552C	Version: V1.4
Output Rating	Output Voltage	0-80V	
	Output Current	0-480A	

(0 ℃-40 ℃)	Internal Sink Current ¹	0-200A
	External Sink Current ¹	0-480A
	Output Power	0-12KW
	Internal Sink Power ¹	0-600W
	External Sink Power ¹	0-36KW
Output Resistance	Range	0-0.133Ω
	Accuracy ²	0.25%+30mΩ*A
	Resolution	0.1mΩ
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+10mV
	Current	≤0.01%+240mA
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+30mV
	Current	≤0.05%+480mA
Setup Resolution	Voltage	10mV
	Current	100mA
	Power	0.1W
Read Back Resolution	Voltage	10mV
	Current	100mA
	Power	0.1W
Setup Accuracy ³ (within 12 months, 25℃±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+30mV
	Current	≤0.2%+480mA
	Power	1%+120W
Read Back Accuracy ⁴ (within 12 months, 25℃±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+30mV
	Current	≤0.2%+480mA
	Power	1%+120W
Ripple (20Hz -20MHz)	Voltage	≤80mVp-p
	Current	≤0.05%+240mA _{rms}
Setup Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.01%+30mV
	Current	≤0.02%+480mA
Read Back Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.01%+30mV
	Current	≤0.02%+480mA
Rise time(no load) ⁵	Voltage	≤10ms
Rise time(full load) ⁵	Voltage	≤20ms
Fall time(no load) ⁵	Voltage	≤30ms
Fall time(full load) ⁵	Voltage	≤10ms
Current seamless switching ⁶	-90%-90%	≤40ms
	90%--90%	≤40ms
Transient Response Time	Voltage	≤3ms
AC Input ⁷	Voltage	380Vac±10%(Three-phase five wire)
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+480mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+480mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+480mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+480mA

efficiency	80%
Remote Sense Compensation Voltage	3V
Command Response Time	20mS
Power Factor	0.99
Maximum input current ⁸	38A
Maximum input apparent power	15200VA
Storage temperature	-10℃-70℃
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect
standard Interface	USB/RS232/CAN/GPIB/LAN
Isolation (output to ground)	500V
Series Number	≤2
Parallel Number	≤8
Parallel Number of Power Dissipater	4/8/12
Working temperature	0-40℃
Dimension (mm)	554mmW×902mmH×807.5mmD(ITECH 15U Cabinet)
Weight(net)	119KG

Parameter		IT6562C	Version: V1.4
Output Rating (0℃-40℃)	Output Voltage	0-80V	
	Output Current	0-600A	
	Internal Sink Current ¹	0-250A	
	External Sink Current ¹	0-600A	
	Output Power	0-15KW	
	Internal Sink Power ¹	0-750W	
	External Sink Power ¹	0-45KW	
Output Resistance	Range	0-0.107Ω	
	Accuracy ²	0.25%+30mΩ*A	
	Resolution	0.1mΩ	
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+10mV	
	Current	≤0.01%+300mA	
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+30mV	
	Current	≤0.05%+600mA	
Setup Resolution	Voltage	10mV	
	Current	100mA	
	Power	0.1W	
Read Back Resolution	Voltage	10mV	
	Current	100mA	
	Power	0.1W	
Setup Accuracy ³ (within 12 months, 25℃±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+30mV	
	Current	≤0.2%+600mA	
	Power	1%+150W	
Read Back Accuracy ⁴ (within 12 months, 25℃±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+30mV	
	Current	≤0.2%+600mA	
	Power	1%+150W	
Ripple	Voltage	≤80mVp-p	

(20Hz -20MHz)	Current	≤0.05%+300mA
Setup Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+30mV
	Current	≤0.02%+600mA
Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+30mV
	Current	≤0.02%+600mA
Rise time(no load) ⁵	Voltage	≤10ms
Rise time(full load) ⁵	Voltage	≤20ms
Fall time(no load) ⁵	Voltage	≤30ms
Fall time(full load) ⁵	Voltage	≤10ms
Current seamless switching ⁶	-90%-90%	≤50ms
	90%--90%	≤50ms
Transient Response Time	Voltage	≤3ms
AC Input ⁷	Voltage	380Vac±10%(Three-phase five wire)
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+600mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+600mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+600mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+600mA
efficiency		80%
Remote Sense Compensation Voltage		3V
Command Response Time		20mS
Power Factor		0.99
Maximum input current ⁸		38A
Maximum input apparent power		19000VA
Storage temperature		-10℃-70℃
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)		500V
Series Number		≤2
Parallel Number		≤8
Parallel Number of Power Dissipater		5/10/15
Working temperature		0-40℃
Dimension (mm)	554mmW×902mmH×807.5mmD(ITECH 15U Cabinet)	
Weight(net)	137Kg	

Parameter		IT6572C	Version: V1.4
Output Rating (0 °C-40 °C)	Output Voltage	0-80V	
	Output Current	0-840A	
	Internal Sink Current ¹	0-350A	
	External Sink Current ¹	0-840A	
	Output Power	0-21KW	

	Internal Sink Power ¹	0-1050W
	External Sink Power ¹	0-63KW
Output Resistance	Range	0-0.076Ω
	Accuracy ²	0.25%+30mΩ*A
	Resolution	0.1mΩ
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+10mV
	Current	≤0.01%+420mA
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+30mV
	Current	≤0.05%+840mA
Setup Resolution	Voltage	10mV
	Current	100mA
	Power	0.1W
Read Back Resolution	Voltage	10mV
	Current	100mA
	Power	0.1W
Setup Accuracy ³ (within 12 months, 25°C±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+30mV
	Current	≤0.2%+840mA
	Power	1%+210W
Read Back Accuracy ⁴ (within 12 months, 25°C±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+30mV
	Current	≤0.2%+840mA
	Power	1%+210W
Ripple (20Hz -20MHz)	Voltage	≤80mVp-p
	Current	≤0.05%+420mA _{rms}
Setup Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+30mV
	Current	≤0.02%+840mA
Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+30mV
	Current	≤0.02%+840mA
Rise time(no load) ⁵	Voltage	≤10ms
Rise time(full load) ⁵	Voltage	≤20ms
Fall time(no load) ⁵	Voltage	≤30ms
Fall time(full load) ⁵	Voltage	≤10ms
Current seamless switching ⁶	-90%-90%	≤70ms
	90%--90%	≤70ms
Transient Response Time	Voltage	≤3ms
AC Input ⁷	Voltage	380Vac±10%(Three-phase five wire)
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+840mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+840mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+840mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+840mA
efficiency	80%	
Remote Sense Compensation Voltage	3V	
Command Response	20mS	

Time	
Power Factor	0.99
Maximum input current ⁸	57A
Maximum input apparent power	26600VA
Storage temperature	-10℃-70℃
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP, Vsense reversed protect
standard Interface	USB/RS232/CAN/GPIB/LAN
Isolation (output to ground)	500V
Series Number	≤2
Parallel Number	≤8
Parallel Number of Power Dissipater	7/14/21
Working temperature	0-40℃
Dimension (mm)	554mmW×902mmH×807.5mmD(ITECH 15U Cabinet)
Weight(net)	180Kg

Parameter		IT6582C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-80V	
	Output Current	0-960A	
	Internal Sink Current ¹	0-400A	
	External Sink Current ¹	0-960A	
	Output Power	0-24KW	
	Internal Sink Power ¹	0-1200W	
	External Sink Power ¹	0-72KW	
Output Resistance	Range	0-0.067Ω	
	Accuracy ²	0.25%+30mΩ*A	
	Resolution	0.1mΩ	
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+10mV	
	Current	≤0.01%+480mA	
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+30mV	
	Current	≤0.05%+960mA	
Setup Resolution	Voltage	10mV	
	Current	100mA	
	Power	0.1W	
Read Back Resolution	Voltage	10mV	
	Current	100mA	
	Power	0.1W	
Setup Accuracy ³ (within 12 months, 25℃±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+30mV	
	Current	≤0.2%+960mA	
	Power	1%+240W	
Read Back Accuracy ⁴ (within 12 months, 25℃±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+30mV	
	Current	≤0.2%+960mA	
	Power	1%+240W	
Ripple (20Hz -20MHz)	Voltage	≤80mVp-p	
	Current	≤0.05%+480mArms	
Setup Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.01%+30mV	
	Current	≤0.02%+960mA	

Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+30mV
	Current	≤0.02%+960mA
Rise time(no load) ⁵	Voltage	≤10ms
Rise time(full load) ⁵	Voltage	≤20ms
Fall time(no load) ⁵	Voltage	≤30ms
Fall time(full load) ⁵	Voltage	≤10ms
Current seamless switching ⁶	-90%-90%	≤80ms
	90%--90%	≤80ms
Transient Response Time	Voltage	≤3ms
AC Input ⁷	Voltage	380Vac±10%(Three-phase five wire)
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+960mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+960mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+960mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+960mA
efficiency	80%	
Remote Sense Compensation Voltage	3V	
Command Response Time	20mS	
Power Factor	0.99	
Maximum input current ⁸	57A	
Maximum input apparent power	30400VA	
Storage temperature	-10℃-70℃	
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)	500V	
Series Number	≤2	
Parallel Number	≤8	
Parallel Number of Power Dissipater	8/16/24	
Working temperature	0-40℃	
Dimension (mm)	550mmW×1289.3mmH×834.8mmD	
Weight(net)	248Kg	

Parameter		IT6592C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-80V	
	Output Current	0-1200A	
	Internal Sink Current ¹	0-500A	
	External Sink Current ¹	0-1200A	
	Output Power	0-30KW	
	Internal Sink Power ¹	0-1500W	
	External Sink Power ¹	0-90KW	

Output Resistance	Range	0-0.053Ω
	Accuracy ²	0.25%+30mΩ*A
	Resolution	0.1mΩ
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+10mV
	Current	≤0.01%+600mA
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+30mV
	Current	≤0.05%+1200mA
Setup Resolution	Voltage	10mV
	Current	100mA
	Power	0.1W
Read Back Resolution	Voltage	10mV
	Current	100mA
	Power	0.1W
Setup Accuracy ³ (within 12 months, 25°C±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+30mV
	Current	≤0.2%+1200mA
	Power	1%+300W
Read Back Accuracy ⁴ (within 12 months, 25°C±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+30mV
	Current	≤0.2%+1200mA
	Power	1%+300W
Ripple (20Hz -20MHz)	Voltage	≤80mVp-p
	Current	≤0.05%+600mArms
Setup Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+30mV
	Current	≤0.02%+1200mA
Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+30mV
	Current	≤0.02%+1200mA
Rise time(no load) ⁵	Voltage	≤10ms
Rise time(full load) ⁵	Voltage	≤20ms
Fall time(no load) ⁵	Voltage	≤30ms
Fall time(full load) ⁵	Voltage	≤10ms
Current seamless switching ⁶	-90%-90%	≤100ms
	90%--90%	≤100ms
Transient Response Time	Voltage	≤3ms
AC Input ⁷	Voltage	380Vac±10%(Three-phase five wire)
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+1200mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+1200mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+1200mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+30mV
	Current	≤0.1%+1200mA
efficiency		80%
Remote Sense Compensation Voltage		3V
Command Response Time		20mS
Power Factor		0.99
Maximum input current ⁸		76A
Maximum input apparent		38000VA

power	
Storage temperature	-10℃-70℃
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect
standard Interface	USB/RS232/CAN/GPIB/LAN
Isolation (output to ground)	500V
Series Number	≤2
Parallel Number	≤8
Parallel Number of Power Dissipater	10/20/30
Working temperature	0-40℃
Dimension (mm)	550mmW×1289.3mmH×834.8mmD
Weight(net)	284Kg

Parameter		IT6513C	Version: V1.4
Output Rating (0℃-40℃)	Output Voltage	0-200V	
	Output Current	0-60A	
	Internal Sink Current ¹	0-25A	
	External Sink Current ¹	0-60A	
	Output Power	0-1800W	
	Internal Sink Power ¹	0-150W	
	External Sink Power ¹	0-5400W	
Output Resistance	Range	0-22.222Ω	
	Accuracy ²	0.25%+100mΩ	
	Resolution	1mΩ	
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+20mV	
	Current	≤0.01%+30mA	
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+50mV	
	Current	≤0.05%+60mA	
Setup Resolution	Voltage	10mV	
	Current	10mA	
	Power	0.1W	
Read Back Resolution	Voltage	10mV	
	Current	10mA	
	Power	0.1W	
Setup Accuracy (within 12 months, 25℃±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+100mV	
	Current	≤0.2%+60mA	
	Power	≤1%+30W	
Read Back Accuracy (within 12 months, 25℃±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+100mV	
	Current	≤0.2%+60mA	
	Power	≤1%+30W	
Ripple (20Hz -20MHz)	Voltage	≤200mVp-p	
	Current	≤50mA _{rms}	
Setup Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.05 %+100mV	
	Current	≤0.2%+60mA	

Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+60mA
Rise time(no load) ⁵	Voltage	≤15ms
Rise time(full load) ⁵	Voltage	≤30ms
Fall time(no load) ⁵	Voltage	≤50ms
Fall time(full load) ⁵	Voltage	≤30ms
Current seamless switching ⁶	-90%-90%	≤10ms
	90%--90%	≤10ms
Transient Response Time	Voltage	≤2ms
AC Input ⁷	Voltage	220V±10%
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+60mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+60mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+60mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+60mA
efficiency	89%(30V/60A)-90.5%(200V/9A)	
Remote Sense Compensation Voltage	2V	
Command Response Time	20mS	
Power Factor	0.99	
Maximum input current ⁸	10A	
Maximum input apparent power	2100VA	
Storage temperature	-10℃-70℃	
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP, Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)	500V	
Series Number	≤2	
Parallel Number	≤8	
Parallel Number of Power Dissipater	1/2/3	
Working temperature	0-40℃	
Dimension (mm)	483mmW×105.4mmH×640.8mmD	
Weight(net)	17Kg	

Parameter		IT6523C	Version: V1.4
Output Rating (0 °C-40 °C)	Output Voltage	0-200V	
	Output Current	0-60A	
	Internal Sink Current ¹	0-25A	
	External Sink Current ¹	0-60A	
	Output Power	0-3000W	
	Internal Sink Power ¹	0-150W	
	External Sink	0-9KW	

	Power¹	
Output Resistance	Range	0-13Ω
	Accuracy²	0.25%+100mΩ
	Resolution	1mΩ
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+20mV
	Current	≤0.01%+30mA
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+50mV
	Current	≤0.05%+60mA
Setup Resolution	Voltage	10mV
	Current	10mA
	Power	0.1W
Read Back Resolution	Voltage	10mV
	Current	10mA
	Power	0.1W
Setup Accuracy (within 12 months, 25°C ±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+60mA
	Power	≤1%+30W
Read Back Accuracy (within 12 months, 25°C ±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+60mA
	Power	≤1%+30W
Ripple (20Hz -20MHz)	Voltage	≤200mVp-p
	Current	≤50mArms
Setup Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.05 %+100mV
	Current	≤0.2%+60mA
Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+60mA
Rise time(no load)⁵	Voltage	≤15ms
Rise time(full load)⁵	Voltage	≤30ms
Fall time(no load)⁵	Voltage	≤50ms
Fall time(full load)⁵	Voltage	≤15ms
Current seamless switching⁶	-90%-90%	≤10ms
	90%--90%	≤10ms
Transient Response Time	Voltage	≤2ms
AC Input⁷	Voltage	220V±10%
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+60mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+60mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+60mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+60mA
efficiency	89%(50V/60A)-90.5%(200V/15A)	
Remote Sense Compensation Voltage	2V	

Command Response Time	20mS
Power Factor	0.99
Maximum input current ⁸	19A
Maximum input apparent power	3800VA
Storage temperature	-10℃-70℃
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP, Vsense reversed protect
standard Interface	USB/RS232/CAN/GPIB/LAN
Isolation (output to ground)	500V
Series Number	≤2
Parallel Number	≤8
Parallel Number of Power Dissipater	1/2/3
Working temperature	0-40℃
Dimension (mm)	483mmW×105.4mmH×640.8mmD
Weight(net)	17Kg

Parameter		IT6533C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-200V	
	Output Current	0-120A	
	Internal Sink Current ¹	0-50A	
	External Sink Current ¹	0-120A	
	Output Power	0-6KW	
	Internal Sink Power ¹	0-300W	
	External Sink Power ¹	0-18KW	
Output Resistance	Range	0-6.666Ω	
	Accuracy ²	0.25%+100mΩ	
	Resolution	1mΩ	
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+20mV	
	Current	≤0.01%+60mA	
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+50mV	
	Current	≤0.05%+120mA	
Setup Resolution	Voltage	10mV	
	Current	10mA	
	Power	0.1W	
Read Back Resolution	Voltage	10mV	
	Current	10mA	
	Power	0.1W	
Setup Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+100mV	
	Current	≤0.2%+120mA	
	Power	≤1%+60W	
Read Back Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+100mV	
	Current	≤0.2%+120mA	
	Power	≤1%+60W	
Ripple	Voltage	≤200mVp-p	

(20Hz -20MHz)	Current	≤100mArms
Setup Temperature Coefficient (%of Output/°C +Offset)	Voltage	≤0.05 %+100mV
	Current	≤0.2%+120mA
Read Back Temperature Coefficient (%of Output/°C +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+120mA
Rise time(no load) ⁵	Voltage	≤15ms
Rise time(full load) ⁵	Voltage	≤30ms
Fall time(no load) ⁵	Voltage	≤50ms
Fall time(full load) ⁵	Voltage	≤15ms
Current seamless switching ⁶	-90%-90%	≤20ms
	90%--90%	≤20ms
Transient Response Time	Voltage	≤2ms
AC Input ⁷	Voltage	220V±10%
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+120mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+120mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+120mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+120mA
efficiency	89%(50V/120A)-90.5%(200V/30A)	
Remote Sense Compensation Voltage	2V	
Command Response Time	20mS	
Power Factor	0.99	
Maximum input current ⁸	38A	
Maximum input apparent power	7600VA	
Storage temperature	-10℃-70℃	
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)	500V	
Series Number	≤2	
Parallel Number	≤8	
Parallel Number of Power Dissipater	2/4/6	
Working temperature	0-40℃	
Dimension (mm)	483mmW×194mmH×640.8mmD	
Weight(net)	35Kg	

Parameter		IT6543C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-200V	
	Output Current	0-180A	
	Internal Sink Current ¹	0-75A	
	External Sink Current ¹	0-180A	

	Output Power	0-9KW
	Internal Sink Power ¹	0-450W
	External Sink Power ¹	0-27KW
Output Resistance	Range	0-4.444Ω
	Accuracy ²	0.25%+100mΩ
	Resolution	1mΩ
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+20mV
	Current	≤0.01%+90mA
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+50mV
	Current	≤0.05%+180mA
Setup Resolution	Voltage	10mV
	Current	10mA
	Power	0.1W
Read Back Resolution	Voltage	10mV
	Current	10mA
	Power	0.1W
Setup Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+180mA
	Power	≤1%+90W
Read Back Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+180mA
	Power	≤1%+90W
Ripple (20Hz -20MHz)	Voltage	≤200mVp-p
	Current	≤150mArms
Setup Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.05 %+100mV
	Current	≤0.2%+180mA
Read Back Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+180mA
Rise time(no load) ⁵	Voltage	≤15ms
Rise time(full load) ⁵	Voltage	≤30ms
Fall time(no load) ⁵	Voltage	≤50ms
Fall time(full load) ⁵	Voltage	≤15ms
Current seamless switching ⁶	-90%-90%	≤30ms
	90%--90%	≤30ms
Transient Response Time	Voltage	≤2ms
AC Input ⁷	Voltage	220V±10%
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+180mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+180mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+180mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+180mA

efficiency	89%(50V/180A)-90.5%(200V/45A)
Remote Sense Compensation Voltage	2V
Command Response Time	20mS
Power Factor	0.99
Maximum input current ⁸	19A
Maximum input apparent power	11400VA
Storage temperature	-10℃-70℃
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect
standard Interface	USB/RS232/CAN/GPIB/LAN
Isolation (output to ground)	500V
Series Number	≤2
Parallel Number	≤8
Parallel Number of Power Dissipater	3/6/9
Working temperature	0-40℃
Dimension (mm)	483mmW×283.2mmH×640.8mmD
Weight(net)	53Kg

Parameter		IT6553C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-200V	
	Output Current	0-240A	
	Internal Sink Current ¹	0-100A	
	External Sink Current ¹	0-240A	
	Output Power	0-12KW	
	Internal Sink Power ¹	0-600W	
	External Sink Power ¹	0-36KW	
Output Resistance	Range	0-3.333Ω	
	Accuracy ²	0.25%+100mΩ	
	Resolution	1mΩ	
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+20mV	
	Current	≤0.01%+120mA	
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+50mV	
	Current	≤0.05%+240mA	
Setup Resolution	Voltage	10mV	
	Current	100mA	
	Power	0.1W	
Read Back Resolution	Voltage	10mV	
	Current	100mA	
	Power	0.1W	
Setup Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+100mV	
	Current	≤0.2%+240mA	
	Power	≤1%+120W	
Read Back Accuracy (within 12 months, 25℃ ±5℃)	Voltage	≤0.05%+100mV	
	Current	≤0.2%+240mA	

±(%of Output+Offset)	Power	≤1%+120W
Ripple (20Hz -20MHz)	Voltage	≤200mVp-p
	Current	≤200mArms
Setup Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.05 %+100mV
	Current	≤0.2%+240mA
Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+240mA
Rise time(no load) ⁵	Voltage	≤15ms
Rise time(full load) ⁵	Voltage	≤30ms
Fall time(no load) ⁵	Voltage	≤50ms
Fall time(full load) ⁵	Voltage	≤15ms
Current seamless switching ⁶	-90%-90%	≤40ms
	90%--90%	≤40ms
Transient Response Time	Voltage	≤2ms
AC Input ⁷	Voltage	380Vac±10%(Three-phase five wire)
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+240mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+240mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+240mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+240mA
efficiency	89%(50V/240A)-90.5%(200V/60A)	
Remote Sense Compensation Voltage	2V	
Command Response Time	20mS	
Power Factor	0.99	
Maximum input current ⁸	38A	
Maximum input apparent power	15200VA	
Storage temperature	-10°C-70°C	
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)	500V	
Series Number	≤2	
Parallel Number	≤8	
Parallel Number of Power Dissipater	4/8/12	
Working temperature	0-40°C	
Dimension (mm)	554mmW×902mmH×807.5mmD(ITECH 15U Cabinet)	
Weight(net)	119Kg	

Parameter		IT6563C	Version: V1.4
Output Rating (0 °C-40 °C)	Output Voltage	0-200V	
	Output Current	0-300A	

	Internal Sink Current ¹	0-125A
	External Sink Current ¹	0-300A
	Output Power	0-15KW
	Internal Sink Power ¹	0-750W
	External Sink Power ¹	0-45KW
Output Resistance	Range	0-2.666Ω
	Accuracy ²	0.25%+100mΩ
	Resolution	1mΩ
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+20mV
	Current	≤0.01%+150mA
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+50mV
	Current	≤0.05%+300mA
Setup Resolution	Voltage	10mV
	Current	100mA
	Power	0.1W
Read Back Resolution	Voltage	10mV
	Current	100mA
	Power	0.1W
Setup Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+300mA
	Power	≤1%+150W
Read Back Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+300mA
	Power	≤1%+150W
Ripple (20Hz -20MHz)	Voltage	≤200mVp-p
	Current	≤250mArms
Setup Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.05 %+100mV
	Current	≤0.2%+300mA
Read Back Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+300mA
Rise time(no load) ⁵	Voltage	≤15ms
Rise time(full load) ⁵	Voltage	≤30ms
Fall time(no load) ⁵	Voltage	≤50ms
Fall time(full load) ⁵	Voltage	≤15ms
Current seamless switching ⁶	-90%-90%	≤50ms
	90%--90%	≤50ms
Transient Response Time	Voltage	≤2ms
AC Input ⁷	Voltage	380Vac±10%(Three-phase five wire)
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+300mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+300mA

Readback stability-30min (%of Output +Offset)	Voltage	$\leq 0.05\% + 100\text{mV}$
	Current	$\leq 0.2\% + 300\text{mA}$
Readback stability-8h (%of Output +Offset)	Voltage	$\leq 0.05\% + 100\text{mV}$
	Current	$\leq 0.2\% + 300\text{mA}$
efficiency	89%(50V/300A)-90.5%(200V/75A)	
Remote Sense Compensation Voltage	2V	
Command Response Time	20mS	
Power Factor	0.99	
Maximum input current ⁸	38A	
Maximum input apparent power	19000VA	
Storage temperature	$-10^{\circ}\text{C} - 70^{\circ}\text{C}$	
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP, Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)	500V	
Series Number	≤ 2	
Parallel Number	≤ 8	
Parallel Number of Power Dissipater	5/10/15	
Working temperature	$0 - 40^{\circ}\text{C}$	
Dimension (mm)	554mmW×902mmH×807.5mmD(ITECH 15U Cabinet)	
Weight(net)	137Kg	

Parameter		IT6573C	Version: V1.4
Output Rating (0 °C-40 °C)	Output Voltage	0-200V	
	Output Current	0-420A	
	Internal Sink Current ¹	0-175A	
	External Sink Current ¹	0-420A	
	Output Power	0-21KW	
	Internal Sink Power ¹	0-1050W	
	External Sink Power ¹	0-63KW	
Output Resistance	Range	0-1.904Ω	
	Accuracy ²	0.25%+100mΩ	
	Resolution	1mΩ	
Line regulation ±(%of Output+Offset)	Voltage	$\leq 0.01\% + 20\text{mV}$	
	Current	$\leq 0.01\% + 210\text{mA}$	
Load regulation ±(%of Output+Offset)	Voltage	$\leq 0.01\% + 50\text{mV}$	
	Current	$\leq 0.05\% + 420\text{mA}$	
Setup Resolution	Voltage	10mV	
	Current	100mA	
	Power	0.1W	
Read Back Resolution	Voltage	10mV	
	Current	100mA	
	Power	0.1W	
Setup Accuracy (within 12 months, 25°C ±5°C)	Voltage	$\leq 0.05\% + 100\text{mV}$	
	Current	$\leq 0.2\% + 420\text{mA}$	

±(%of Output+Offset)	Power	≤1%+210W
Read Back Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+420mA
	Power	≤1%+210W
Ripple (20Hz -20MHz)	Voltage	≤200mVp-p
	Current	≤350mArms
Setup Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.05 %+100mV
	Current	≤0.2%+420mA
Read Back Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+420mA
Rise time(no load) ⁵	Voltage	≤15ms
Rise time(full load) ⁵	Voltage	≤30ms
Fall time(no load) ⁵	Voltage	≤50ms
Fall time(full load) ⁵	Voltage	≤15ms
Current seamless switching ⁶	-90%-90%	≤70ms
	90%--90%	≤70ms
Transient Response Time	Voltage	≤2ms
AC Input ⁷	Voltage	380V±10%(Three-phase five wire)
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+420mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+420mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+420mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+420mA
efficiency	89%(50V/420A)-90.5%(200V/105A)	
Remote Sense Compensation Voltage	2V	
Command Response Time	20mS	
Power Factor	0.99	
Maximum input current ⁸	57A	
Maximum input apparent power	26600VA	
Storage temperature	-10℃-70℃	
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)	500V	
Series Number	≤2	
Parallel Number	≤8	
Parallel Number of Power Dissipater	7/14/21	
Working temperature	0-40℃	
Dimension (mm)	554mmW×902mmH×807.5mmD(ITECH 15U Cabinet)	
Weight(net)	180Kg	

Parameter		IT6583C	Version: V1.4
Output Rating (0 °C-40 °C)	Output Voltage	0-200V	
	Output Current	0-480A	
	Internal Sink Current ¹	0-200A	
	External Sink Current ¹	0-480A	
	Output Power	0-24KW	
	Internal Sink Power ¹	0-1200W	
	External Sink Power ¹	0-72KW	
Output Resistance	Range	0-1.666Ω	
	Accuracy ²	0.25%+100mΩ	
	Resolution	1mΩ	
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+20mV	
	Current	≤0.01%+240mA	
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+50mV	
	Current	≤0.05%+480mA	
Setup Resolution	Voltage	10mV	
	Current	100mA	
	Power	0.1W	
Read Back Resolution	Voltage	10mV	
	Current	100mA	
	Power	0.1W	
Setup Accuracy (within 12 months, 25°C ±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+100mV	
	Current	≤0.2%+480mA	
	Power	≤1%+240W	
Read Back Accuracy (within 12 months, 25°C ±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+100mV	
	Current	≤0.2%+480mA	
	Power	≤1%+240W	
Ripple (20Hz -20MHz)	Voltage	≤200mVp-p	
	Current	≤400mArms	
Setup Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.05 %+100mV	
	Current	≤0.2%+480mA	
Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.05%+100mV	
	Current	≤0.2%+480mA	
Rise time(no load) ⁵	Voltage	≤15ms	
Rise time(full load) ⁵	Voltage	≤30ms	
Fall time(no load) ⁵	Voltage	≤50ms	
Fall time(full load) ⁵	Voltage	≤15ms	
Current seamless switching ⁶	-90%-90%	≤80ms	
	90%--90%	≤80ms	
Transient Response Time	Voltage	≤2ms	
AC Input ⁷	Voltage	380V±10%(Three-phase	five
	Frequency	wire)	47Hz-63Hz

Setup stability-30min (%of Output +Offset)	Voltage	$\leq 0.05\% + 100\text{mV}$
	Current	$\leq 0.2\% + 480\text{mA}$
Setup stability-8h (%of Output +Offset)	Voltage	$\leq 0.05\% + 100\text{mV}$
	Current	$\leq 0.2\% + 480\text{mA}$
Readback stability-30min (%of Output +Offset)	Voltage	$\leq 0.05\% + 100\text{mV}$
	Current	$\leq 0.2\% + 480\text{mA}$
Readback stability-8h (%of Output +Offset)	Voltage	$\leq 0.05\% + 100\text{mV}$
	Current	$\leq 0.2\% + 480\text{mA}$
efficiency	89%(50V/480A)-90.5%(200V/120A)	
Remote Sense Compensation Voltage	2V	
Command Response Time	20mS	
Power Factor	0.99	
Maximum input current ⁸	57A	
Maximum input apparent power	30400VA	
Storage temperature	$-10^{\circ}\text{C} - 70^{\circ}\text{C}$	
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP, Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)	500V	
Series Number	≤ 2	
Parallel Number	≤ 8	
Parallel Number of Power Dissipater	8/16/24	
Working temperature	$0 - 40^{\circ}\text{C}$	
Dimension (mm)	550mmW×1289.3mmH×834.8mmD	
Weight(net)	248Kg	

Parameter		IT6593C	Version: V1.4
Output Rating (0 °C-40 °C)	Output Voltage	0-200V	
	Output Current	0-600A	
	Internal Sink Current ¹	0-250A	
	External Sink Current ¹	0-600A	
	Output Power	0-30KW	
	Internal Sink Power ¹	0-1500W	
	External Sink Power ¹	0-90KW	
Output Resistance	Range	0-1.333Ω	
	Accuracy ²	0.25%+100mΩ	
	Resolution	1mΩ	
Line regulation ±(%of Output+Offset)	Voltage	$\leq 0.01\% + 20\text{mV}$	
	Current	$\leq 0.01\% + 300\text{mA}$	
Load regulation ±(%of Output+Offset)	Voltage	$\leq 0.01\% + 50\text{mV}$	
	Current	$\leq 0.05\% + 600\text{mA}$	
Setup Resolution	Voltage	10mV	
	Current	100mA	
	Power	0.1W	
Read Back Resolution	Voltage	10mV	
	Current	100mA	

	Power	0.1W
Setup Accuracy (within 12 months, 25°C ±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+600mA
	Power	≤1%+300W
Read Back Accuracy (within 12 months, 25°C ±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+600mA
	Power	≤1%+300W
Ripple (20Hz -20MHz)	Voltage	≤200mVp-p
	Current	≤500mArms
Setup Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.05 %+100mV
	Current	≤0.2%+600mA
Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+600mA
Rise time(no load) ⁵	Voltage	≤15ms
Rise time(full load) ⁵	Voltage	≤30ms
Fall time(no load) ⁵	Voltage	≤50ms
Fall time(full load) ⁵	Voltage	≤15ms
Current seamless switching ⁶	-90%-90%	≤100ms
	90%--90%	≤100ms
Transient Response Time	Voltage	≤2ms
AC Input ⁷	Voltage	380V±10%(Three-phase five wire)
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+600mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+600mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+600mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+100mV
	Current	≤0.2%+600mA
efficiency	89%(50V/600A)-90.5%(200V/150A)	
Remote Sense Compensation Voltage	2V	
Command Response Time	20mS	
Power Factor	0.99	
Maximum input current ⁸	76A	
Maximum input apparent power	38000VA	
Storage temperature	-10°C-70°C	
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)	500V	
Series Number	≤2	
Parallel Number	≤8	
Parallel Number of	10/20/30	

Power Dissipater	
Working temperature	0-40℃
Dimension (mm)	550mmW×1289.3mmH×834.8mmD
Weight(net)	284Kg

Parameter		IT6514C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-360V	
	Output Current	0-30A	
	Internal Sink Current ¹	0-12.5A	
	External Sink Current ¹	0-30A	
	Output Power	0-1800W	
	Internal Sink Power ¹	0-150W	
	External Sink Power ¹	0-5.4KW	
Output Resistance	Range	0-72Ω	
	Accuracy ²	0.25%+135mΩ*A	
	Resolution	1mΩ	
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+40mV	
	Current	≤0.01%+15mA	
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+135mV	
	Current	≤0.05%+30mA	
Setup Resolution	Voltage	10mV	
	Current	10mA	
	Power	0.1W	
Read Back Resolution	Voltage	10mV	
	Current	10mA	
	Power	0.1W	
Setup Accuracy ³ (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+135mV	
	Current	≤0.2%+30mA	
	Power	1%+30W	
Read Back Accuracy ⁴ (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+135mV	
	Current	≤0.2%+30mA	
	Power	1%+30W	
Ripple (20Hz -20MHz)	Voltage	≤360mVp-p	
	Current	≤0.05%+30mArms	
Setup Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.01%+135mV	
	Current	≤0.02%+30mA	
Read Back Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.01%+135mV	
	Current	≤0.02%+30mA	
Rise time(no load) ⁵	Voltage	≤50ms	
Rise time(full load) ⁵	Voltage	≤80ms	
Fall time(no load) ⁵	Voltage	≤250ms	
Fall time(full load) ⁵	Voltage	≤110ms	
Current seamless switching ⁶	-90%-90%	≤50ms	
	90%--90%	≤50ms	
Transient Response Time	Voltage	≤3ms	

AC Input ⁷	Voltage	220V±10%
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+30mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+30mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+30mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+30mA
efficiency		80%
Remote Sense Compensation Voltage		3V
Command Response Time		20mS
Power Factor		0.99
Maximum input current ⁸		12A
Maximum input apparent power		2300VA
Storage temperature		-10℃-70℃
Protective function		Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect
standard Interface		USB/RS232/CAN/GPIB/LAN
Isolation (output to ground)		500V
Parallel Number		≤8
Parallel Number of Power Dissipater		1/2/3
Working temperature		0-40℃
Dimension (mm)		483mmW×105.4mmH×640.8mmD
Weight(net)		17Kg

Parameter		IT6524C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-360V	
	Output Current	0-30A	
	Internal Sink Current ¹	0-12.5A	
	External Sink Current ¹	0-30A	
	Output Power	0-3000W	
	Internal Sink Power ¹	0-150W	
	External Sink Power ¹	0-9KW	
Output Resistance	Range	0-43.2Ω	
	Accuracy ²	0.25%+135mΩ*A	
	Resolution	1mΩ	
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+40mV	
	Current	≤0.01%+15mA	
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+135mV	
	Current	≤0.05%+30mA	
Setup Resolution	Voltage	10mV	
	Current	10mA	
	Power	0.1W	
Read Back Resolution	Voltage	10mV	
	Current	10mA	
	Power	0.1W	

Setup Accuracy ³ (within 12 months, 25°C ±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+135mV
	Current	≤0.2%+30mA
	Power	1%+30W
Read Back Accuracy ⁴ (within 12 months, 25°C ±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+135mV
	Current	≤0.2%+30mA
	Power	1%+30W
Ripple (20Hz -20MHz)	Voltage	≤360mVp-p
	Current	≤0.05%+30mArms
Setup Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+135mV
	Current	≤0.02%+30mA
Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+135mV
	Current	≤0.02%+30mA
Rise time(no load) ⁵	Voltage	≤50ms
Rise time(full load) ⁵	Voltage	≤80ms
Fall time(no load) ⁵	Voltage	≤250ms
Fall time(full load) ⁵	Voltage	≤55ms
Current seamless switching ⁶	-90%-90%	≤50ms
	90%--90%	≤50ms
Transient Response Time	Voltage	≤3ms
AC Input ⁷	Voltage	220V±10%
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+30mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+30mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+30mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+30mA
efficiency	80%	
Remote Sense Compensation Voltage	3V	
Command Response Time	20mS	
Power Factor	0.99	
Maximum input current ⁸	19A	
Maximum input apparent power	3800VA	
Storage temperature	-10°C-70°C	
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)	500V	
Parallel Number	≤8	
Parallel Number of Power Dissipater	1/2/3	
Working temperature	0-40°C	
Dimension (mm)	483mmW×105.4mmH×640.8mmD	
Weight(net)	17Kg	

Output Rating (0 °C-40 °C)	Output Voltage	0-360V
	Output Current	0-60A
	Internal Sink Current ¹	0-25A
	External Sink Current ¹	0-60A
	Output Power	0-6KW
	Internal Sink Power ¹	0-300W
	External Sink Power ¹	0-18KW
Output Resistance	Range	0-21.6Ω
	Accuracy ²	0.25%+135mΩ*A
	Resolution	1mΩ
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+40mV
	Current	≤0.01%+30mA
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+135mV
	Current	≤0.05%+60mA
Setup Resolution	Voltage	10mV
	Current	10mA
	Power	0.1W
Read Back Resolution	Voltage	10mV
	Current	10mA
	Power	0.1W
Setup Accuracy ³ (within 12 months, 25°C ±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+135mV
	Current	≤0.2%+60mA
	Power	1%+60W
Read Back Accuracy ⁴ (within 12 months, 25°C ±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+135mV
	Current	≤0.2%+60mA
	Power	1%+60W
Ripple (20Hz -20MHz)	Voltage	≤360mVp-p
	Current	≤0.05%+60mArms
Setup Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+135mV
	Current	≤0.02%+60mA
Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+135mV
	Current	≤0.02%+60mA
Rise time(no load) ⁵	Voltage	≤50ms
Rise time(full load) ⁵	Voltage	≤80ms
Fall time(no load) ⁵	Voltage	≤250ms
Fall time(full load) ⁵	Voltage	≤55ms
Current seamless switching ⁶	-90%-90%	≤100ms
	90%--90%	≤100ms
Transient Response Time	Voltage	≤3ms
AC Input ⁷	Voltage	220V±10%
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+60mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+60mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+60mA

Readback stability-8h (%of Output +Offset)	Voltage	$\leq 0.05\% + 135\text{mV}$
	Current	$\leq 0.1\% + 60\text{mA}$
efficiency		80%
Remote Sense Compensation Voltage		3V
Command Response Time		20mS
Power Factor		0.99
Maximum input current ⁸		38A
Maximum input apparent power		7600VA
Storage temperature		-10℃-70℃
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP, Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)		500V
Parallel Number		≤ 8
Parallel Number of Power Dissipater		2/4/6
Working temperature		0-40℃
Dimension (mm)	483mmW×194mmH×640.8mmD	
Weight(net)	35Kg	

Parameter		IT6544C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-360V	
	Output Current	0-90A	
	Internal Sink Current ¹	0-37.5A	
	External Sink Current ¹	0-90A	
	Output Power	0-9KW	
	Internal Sink Power ¹	0-450W	
	External Sink Power ¹	0-27KW	
Output Resistance	Range	0-14.4Ω	
	Accuracy ²	0.25%+135mΩ*A	
	Resolution	1mΩ	
Line regulation ±(%of Output+Offset)	Voltage	$\leq 0.01\% + 40\text{mV}$	
	Current	$\leq 0.01\% + 45\text{mA}$	
Load regulation ±(%of Output+Offset)	Voltage	$\leq 0.01\% + 135\text{mV}$	
	Current	$\leq 0.05\% + 90\text{mA}$	
Setup Resolution	Voltage	10mV	
	Current	10mA	
	Power	0.1W	
Read Back Resolution	Voltage	10mV	
	Current	10mA	
	Power	0.1W	
Setup Accuracy ³ (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	$\leq 0.05\% + 135\text{mV}$	
	Current	$\leq 0.2\% + 90\text{mA}$	
	Power	1%+90W	
Read Back Accuracy ⁴ (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	$\leq 0.05\% + 135\text{mV}$	
	Current	$\leq 0.2\% + 90\text{mA}$	
	Power	1%+90W	

Ripple (20Hz -20MHz)	Voltage	≤360mVp-p
	Current	≤0.05%+90mA _{rms}
Setup Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+135mV
	Current	≤0.02%+90mA
Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+135mV
	Current	≤0.02%+90mA
Rise time(no load) ⁵	Voltage	≤50ms
Rise time(full load) ⁵	Voltage	≤80ms
Fall time(no load) ⁵	Voltage	≤250ms
Fall time(full load) ⁵	Voltage	≤55ms
Current seamless switching ⁶	-90%-90%	≤150ms
	90%--90%	≤150ms
Transient Response Time	Voltage	≤3ms
AC Input ⁷	Voltage	220V±10%
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+90mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+90mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+90mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+90mA
efficiency		80%
Remote Sense Compensation Voltage		3V
Command Response Time		20mS
Power Factor		0.99
Maximum input current ⁸		19A
Maximum input apparent power		11400VA
Storage temperature		-10℃-70℃
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)		500V
Parallel Number		≤8
Parallel Number of Power Dissipater		3/6/9
Working temperature		0-40℃
Dimension (mm)	483mmW×283.2mmH×640.8mmD	
Weight(net)	53Kg	

Parameter		IT6554C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-360V	
	Output Current	0-120A	
	Internal Sink Current ¹	0-50A	
	External Sink Current ¹	0-120A	

	Output Power	0-12KW
	Internal Sink Power ¹	0-600W
	External Sink Power ¹	0-36KW
Output Resistance	Range	0-10.8Ω
	Accuracy ²	0.25%+135mΩ*A
	Resolution	1mΩ
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+40mV
	Current	≤0.01%+60mA
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+135mV
	Current	≤0.05%+120mA
Setup Resolution	Voltage	10mV
	Current	10mA
	Power	0.1W
Read Back Resolution	Voltage	10mV
	Current	10mA
	Power	0.1W
Setup Accuracy ³ (within 12 months, 25°C ±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+135mV
	Current	≤0.2%+120mA
	Power	1%+120W
Read Back Accuracy ⁴ (within 12 months, 25°C ±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+135mV
	Current	≤0.2%+120mA
	Power	1%+120W
Ripple (20Hz -20MHz)	Voltage	≤360mVp-p
	Current	≤0.05%+120mArms
Setup Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+135mV
	Current	≤0.02%+120mA
Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+135mV
	Current	≤0.02%+120mA
Rise time(no load) ⁵	Voltage	≤50ms
Rise time(full load) ⁵	Voltage	≤80ms
Fall time(no load) ⁵	Voltage	≤250ms
Fall time(full load) ⁵	Voltage	≤55ms
Current seamless switching ⁶	-90%-90%	≤200ms
	90%--90%	≤200ms
Transient Response Time	Voltage	≤3ms
AC Input ⁷	Voltage	380Vac±10%(Three-phase five wire)
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+120mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+120mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+120mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+120mA
efficiency		80%
Remote Sense Compensation Voltage		3V

Command Response Time	20mS
Power Factor	0.99
Maximum input current ⁸	38A
Maximum input apparent power	15200VA
Storage temperature	-10℃-70℃
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect
standard Interface	USB/RS232/CAN/GPIB/LAN
Isolation (output to ground)	500V
Parallel Number	≤8
Parallel Number of Power Dissipater	4/8/12
Working temperature	0-40℃
Dimension (mm)	554mmW×902mmH×807.5mmD(ITECH 15U Cabinet)
Weight(net)	119Kg

Parameter		IT6564C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-360V	
	Output Current	0-150A	
	Internal Sink Current ¹	0-62.5A	
	External Sink Current ¹	0-150A	
	Output Power	0-15KW	
	Internal Sink Power ¹	0-750W	
	External Sink Power ¹	0-45KW	
Output Resistance	Range	0-8.64Ω	
	Accuracy ²	0.25%+135mΩ*A	
	Resolution	1mΩ	
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+40mV	
	Current	≤0.01%+75mA	
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+135mV	
	Current	≤0.05%+150mA	
Setup Resolution	Voltage	10mV	
	Current	10mA	
	Power	0.1W	
Read Back Resolution	Voltage	10mV	
	Current	10mA	
	Power	0.1W	
Setup Accuracy ³ (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+135mV	
	Current	≤0.2%+150mA	
	Power	1%+150W	
Read Back Accuracy ⁴ (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+135mV	
	Current	≤0.2%+150mA	
	Power	1%+150W	
Ripple (20Hz -20MHz)	Voltage	≤360mVp-p	
	Current	≤0.05%+150mArms	
Setup Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.01%+135mV	
	Current	≤0.02%+150mA	

Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+135mV
	Current	≤0.02%+150mA
Rise time(no load) ⁵	Voltage	≤50ms
Rise time(full load) ⁵	Voltage	≤80ms
Fall time(no load) ⁵	Voltage	≤250ms
Fall time(full load) ⁵	Voltage	≤55ms
Current seamless switching ⁶	-90%-90%	≤250ms
	90%--90%	≤250ms
Transient Response Time	Voltage	≤3ms
AC Input ⁷	Voltage	380Vac±10%(Three-phase five wire)
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+150mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+150mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+150mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+150mA
efficiency	80%	
Remote Sense Compensation Voltage	3V	
Command Response Time	20mS	
Power Factor	0.99	
Maximum input current ⁸	38A	
Maximum input apparent power	19000VA	
Storage temperature	-10℃-70℃	
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)	500V	
Parallel Number	≤8	
Parallel Number of Power Dissipater	5/10/15	
Working temperature	0-40℃	
Dimension (mm)	554mmW×902mmH×807.5mmD(ITECH 15U Cabinet)	
Weight(net)	137Kg	

Parameter		IT6574C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-360V	
	Output Current	0-210A	
	Internal Sink Current ¹	0-87.5A	
	External Sink Current ¹	0-210A	
	Output Power	0-21KW	
	Internal Sink Power ¹	0-1050W	
	External Sink Power ¹	0-63KW	
Output Resistance	Range	0-6.171Ω	

	Accuracy ²	0.25%+135mΩ*A
	Resolution	1mΩ
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+40mV
	Current	≤0.01%+105mA
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+135mV
	Current	≤0.05%+210mA
Setup Resolution	Voltage	10mV
	Current	100mA
	Power	0.1W
Read Back Resolution	Voltage	10mV
	Current	100mA
	Power	0.1W
Setup Accuracy ³ (within 12 months, 25°C ±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+135mV
	Current	≤0.2%+210mA
	Power	1%+210W
Read Back Accuracy ⁴ (within 12 months, 25°C ±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+135mV
	Current	≤0.2%+210mA
	Power	1%+210W
Ripple (20Hz -20MHz)	Voltage	≤360mVp-p
	Current	≤0.05%+210mArms
Setup Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+135mV
	Current	≤0.02%+210mA
Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+135mV
	Current	≤0.02%+210mA
Rise time(no load) ⁵	Voltage	≤50ms
Rise time(full load) ⁵	Voltage	≤80ms
Fall time(no load) ⁵	Voltage	≤250ms
Fall time(full load) ⁵	Voltage	≤55ms
Current seamless switching ⁶	-90%-90%	≤350ms
	90%--90%	≤350ms
Transient Response Time	Voltage	≤3ms
AC Input ⁷	Voltage	380V±10%(Three-phase five wire)
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+210mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+210mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+210mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+210mA
efficiency		80%
Remote Sense Compensation Voltage		3V
Command Response Time		20mS
Power Factor		0.99
Maximum input current ⁸		57A
Maximum input apparent power		26600VA

Storage temperature	-10℃-70℃
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect
standard Interface	USB/RS232/CAN/GPIB/LAN
Isolation (output to ground)	500V
Parallel Number	≤8
Parallel Number of Power Dissipater	7/14/21
Working temperature	0-40℃
Dimension (mm)	554mmW×902mmH×807.5mmD(ITECH 15U Cabinet)
Weight(net)	180Kg

Parameter		IT6584C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-360V	
	Output Current	0-240A	
	Internal Sink Current ¹	0-100A	
	External Sink Current ¹	0-240A	
	Output Power	0-24KW	
	Internal Sink Power ¹	0-1200W	
	External Sink Power ¹	0-72KW	
Output Resistance	Range	0-5.4Ω	
	Accuracy ²	0.25%+135mΩ*A	
	Resolution	1mΩ	
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+40mV	
	Current	≤0.01%+120mA	
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+135mV	
	Current	≤0.05%+240mA	
Setup Resolution	Voltage	10mV	
	Current	100mA	
	Power	0.1W	
Read Back Resolution	Voltage	10mV	
	Current	100mA	
	Power	0.1W	
Setup Accuracy ³ (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+135mV	
	Current	≤0.2%+240mA	
	Power	1%+240W	
Read Back Accuracy ⁴ (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+135mV	
	Current	≤0.2%+240mA	
	Power	1%+240W	
Ripple (20Hz -20MHz)	Voltage	≤360mVp-p	
	Current	≤0.05%+240mArms	
Setup Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.01%+135mV	
	Current	≤0.02%+240mA	
Read Back Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.01%+135mV	
	Current	≤0.02%+240mA	

Rise time(no load) ⁵	Voltage	≤50ms
Rise time(full load) ⁵	Voltage	≤80ms
Fall time(no load) ⁵	Voltage	≤250ms
Fall time(full load) ⁵	Voltage	≤55ms
Current seamless switching ⁶	-90%-90%	≤400ms
	90%--90%	≤400ms
Transient Response Time	Voltage	≤3ms
AC Input ⁷	Voltage	380V±10%(Three-phase five wire)
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+240mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+240mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+240mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+240mA
efficiency		80%
Remote Sense Compensation Voltage		3V
Command Response Time		20mS
Power Factor		0.99
Maximum input current ⁸		57A
Maximum input apparent power		30400VA
Storage temperature		-10℃-70℃
Protective function		Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect
standard Interface		USB/RS232/CAN/GPIB/LAN
Isolation (output to ground)		500V
Parallel Number		≤8
Parallel Number of Power Dissipater		8/16/24
Working temperature		0-40℃
Dimension (mm)		550mmW×1289.3mmH×834.8mmD
Weight(net)		248Kg

Parameter		IT6594C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-360V	
	Output Current	0-300A	
	Internal Sink Current ¹	0-125A	
	External Sink Current ¹	0-300A	
	Output Power	0-30KW	
	Internal Sink Power ¹	0-1500W	
	External Sink Power ¹	0-90KW	
Output Resistance	Range	0-4.32Ω	
	Accuracy ²	0.25%+135mΩ*A	
	Resolution	1mΩ	
Line regulation	Voltage	≤0.01%+40mV	

±(%of Output+Offset)	Current	≤0.01%+150mA
Load regulation	Voltage	≤0.01%+135mV
±(%of Output+Offset)	Current	≤0.05%+300mA
Setup Resolution	Voltage	10mV
	Current	100mA
	Power	0.1W
Read Back Resolution	Voltage	10mV
	Current	100mA
	Power	0.1W
Setup Accuracy ³ (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+135mV
	Current	≤0.2%+300mA
	Power	1%+300W
Read Back Accuracy ⁴ (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+135mV
	Current	≤0.2%+300mA
	Power	1%+300W
Ripple (20Hz -20MHz)	Voltage	≤360mVp-p
	Current	≤0.05%+300mArms
Setup Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.01%+135mV
	Current	≤0.02%+300mA
Read Back Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.01%+135mV
	Current	≤0.02%+300mA
Rise time(no load) ⁵	Voltage	≤50ms
Rise time(full load) ⁵	Voltage	≤80ms
Fall time(no load) ⁵	Voltage	≤250ms
Fall time(full load) ⁵	Voltage	≤55ms
Current seamless switching ⁶	-90%-90%	≤500ms
	90%--90%	≤500ms
Transient Response Time	Voltage	≤3ms
AC Input ⁷	Voltage	380V±10%(Three-phase five wire)
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+300mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+300mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+300mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+135mV
	Current	≤0.1%+300mA
efficiency		80%
Remote Sense Compensation Voltage		3V
Command Response Time		20mS
Power Factor		0.99
Maximum input current ⁸		76A
Maximum input apparent power		38000VA
Storage temperature		-10℃-70℃
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	

Isolation (output to ground)	500V
Parallel Number	≤8
Parallel Number of Power Dissipater	10/20/30
Working temperature	0-40℃
Dimension (mm)	550mmW×1289.3mmH×834.8mmD
Weight(net)	284Kg

Parameter		IT6515C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-500V	
	Output Current	0-20A	
	Internal Sink Current ¹	0-8A	
	External Sink Current ¹	0-20A	
	Output Power	0-1800W	
	Internal Sink Power ¹	0-150W	
	External Sink Power ¹	0-5400W	
Output Resistance	Range	0-138.88Ω	
	Accuracy ²	0.25%+200mΩ	
	Resolution	10mΩ	
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+50mV	
	Current	≤0.01%+10mA	
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+100mV	
	Current	≤0.05%+20mA	
Setup Resolution	Voltage	100mV	
	Current	10mA	
	Power	0.1W	
Read Back Resolution	Voltage	100mV	
	Current	10mA	
	Power	0.1W	
Setup Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+200mV	
	Current	≤0.2%+20mA	
	Power	≤1%+30W	
Read Back Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+200mV	
	Current	≤0.2%+20mA	
	Power	≤1%+30W	
Ripple (20Hz -20MHz)	Voltage	≤500mVp-p	
	Current	≤40mArms	
Setup Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.03 %+100mV	
	Current	≤0.1%+30mA	
Read Back Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.03%+100mV	
	Current	≤0.1%+30mA	
Rise time(no load) ⁵	Voltage	≤40ms	
Rise time(full load) ⁵	Voltage	≤70ms	

Fall time(no load) ⁵	Voltage	≤100ms
Fall time(full load) ⁵	Voltage	≤50ms
Current seamless switching ⁶	-90%-90%	≤20ms
	90%--90%	≤20ms
Transient Response Time	Voltage	≤2ms
AC Input ⁷	Voltage	220V±10%
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+30mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+30mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+30mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+30mA
efficiency	90%(150V/20A)-93%(500V/6A)	
Remote Sense Compensation Voltage	5V	
Command Response Time	20mS	
Power Factor	0.99	
Ma Maximum input current ⁸	10A	
Maximum input apparent power	2100VA	
Storage temperature	-10℃-70℃	
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)	500V	
Parallel Number	≤8	
Parallel Number of Power Dissipater	1/2/3	
Working temperature	0-40℃	
Dimension (mm)	483mmW×105.4mmH×640.8mmD	
Weight(net)	17Kg	

Parameter		IT6525C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-500V	
	Output Current	0-20A	
	Internal Sink Current ¹	0-8A	
	External Sink Current ¹	0-20A	
	Output Power	0-3000W	
	Internal Sink Power ¹	0-150W	
	External Sink Power ¹	0-9KW	
Output Resistance	Range	0-83.33Ω	
	Accuracy ²	0.25%+200mΩ	
	Resolution	10mΩ	

Line regulation $\pm$ (%of Output+Offset)	Voltage	$\leq 0.01\% + 50\text{mV}$
	Current	$\leq 0.01\% + 10\text{mA}$
Load regulation $\pm$ (%of Output+Offset)	Voltage	$\leq 0.01\% + 100\text{mV}$
	Current	$\leq 0.05\% + 20\text{mA}$
Setup Resolution	Voltage	100mV
	Current	10mA
	Power	0.1W
Read Back Resolution	Voltage	100mV
	Current	10mA
	Power	0.1W
Setup Accuracy (within 12 months, 25°C ±5°C) $\pm$ (%of Output+Offset)	Voltage	$\leq 0.05\% + 200\text{mV}$
	Current	$\leq 0.2\% + 20\text{mA}$
	Power	$\leq 1\% + 30\text{W}$
Read Back Accuracy (within 12 months, 25°C ±5°C) $\pm$ (%of Output+Offset)	Voltage	$\leq 0.05\% + 200\text{mV}$
	Current	$\leq 0.2\% + 20\text{mA}$
	Power	$\leq 1\% + 30\text{W}$
Ripple (20Hz -20MHz)	Voltage	$\leq 500\text{mVp-p}$
	Current	$\leq 40\text{mA}_{\text{rms}}$
Setup Temperature Coefficient (%of Output/°C+Offset)	Voltage	$\leq 0.03\% + 100\text{mV}$
	Current	$\leq 0.1\% + 30\text{mA}$
Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	$\leq 0.03\% + 100\text{mV}$
	Current	$\leq 0.1\% + 30\text{mA}$
Rise time(no load) ⁵	Voltage	$\leq 40\text{ms}$
Rise time(full load) ⁵	Voltage	$\leq 70\text{ms}$
Fall time(no load) ⁵	Voltage	$\leq 100\text{ms}$
Fall time(full load) ⁵	Voltage	$\leq 25\text{ms}$
Current seamless switching ⁶	-90%-90%	$\leq 20\text{ms}$
	90%--90%	$\leq 20\text{ms}$
Transient Response Time	Voltage	$\leq 2\text{ms}$
AC Input ⁷	Voltage	220V±10%
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	$\leq 0.03\% + 100\text{mV}$
	Current	$\leq 0.1\% + 30\text{mA}$
Setup stability-8h (%of Output +Offset)	Voltage	$\leq 0.03\% + 100\text{mV}$
	Current	$\leq 0.1\% + 30\text{mA}$
Readback stability-30min (%of Output +Offset)	Voltage	$\leq 0.03\% + 100\text{mV}$
	Current	$\leq 0.1\% + 30\text{mA}$
Readback stability-8h (%of Output +Offset)	Voltage	$\leq 0.03\% + 100\text{mV}$
	Current	$\leq 0.1\% + 30\text{mA}$
efficiency	90%(150V/20A)-93%(500V/6A)	
Remote Sense Compensation Voltage	5V	
Command Response Time	20mS	
Power Factor	0.99	
Maximum input current ⁸	19A	
Maximum input apparent power	3800VA	

Storage temperature	-10℃-70℃
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP, Vsense reversed protect
standard Interface	USB/RS232/CAN/GPIB/LAN
Isolation (output to ground)	500V
Parallel Number	≤8
Parallel Number of Power Dissipater	1/2/3
Working temperature	0-40℃
Dimension (mm)	483mmW×105.4mmH×640.8mmD
Weight(net)	17Kg

Parameter		IT6535C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-500V	
	Output Current	0-40A	
	Internal Sink Current ¹	0-16A	
	External Sink Current ¹	0-40A	
	Output Power	0-6KW	
	Internal Sink Power ¹	0-300W	
	External Sink Power ¹	0-18KW	
Output Resistance	Range	0-41.66Ω	
	Accuracy ²	0.25%+200mΩ	
	Resolution	10mΩ	
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+50mV	
	Current	≤0.01%+20mA	
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+100mV	
	Current	≤0.05%+40mA	
Setup Resolution	Voltage	100mV	
	Current	10mA	
	Power	0.1W	
Read Back Resolution	Voltage	100mV	
	Current	10mA	
	Power	0.1W	
Setup Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+200mV	
	Current	≤0.2%+40mA	
	Power	≤1%+60W	
Read Back Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+200mV	
	Current	≤0.2%+40mA	
	Power	≤1%+60W	
Ripple (20Hz -20MHz)	Voltage	≤500mVp-p	
	Current	≤80mArms	
Setup Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.03 %+100mV	
	Current	≤0.1%+60mA	
Read Back Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.03%+100mV	
	Current	≤0.1%+60mA	

Rise time(no load) ⁵	Voltage	≤40ms
Rise time(full load) ⁵	Voltage	≤70ms
Fall time(no load) ⁵	Voltage	≤100ms
Fall time(full load) ⁵	Voltage	≤25ms
Current seamless switching ⁶	-90%-90%	≤40ms
	90%--90%	≤40ms
Transient Response Time	Voltage	≤2ms
AC Input ⁷	Voltage	220V±10%
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+60mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+60mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+60mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+60mA
efficiency	90%(150V/40A)-93%(500V/12A)	
Remote Sense Compensation Voltage	5V	
Command Response Time	20mS	
Power Factor	0.99	
Maximum input current ⁸	38A	
Maximum input apparent power	7600VA	
Storage temperature	-10℃-70℃	
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP, Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)	500V	
Parallel Number	≤8	
Parallel Number of Power Dissipater	2/4/6	
Working temperature	0-40℃	
Dimension (mm)	483mmW×194mmH×640.8mmD	
Weight(net)	35Kg	

Parameter		IT6545C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-500V	
	Output Current	0-60A	
	Internal Sink Current ¹	0-24A	
	External Sink Current ¹	0-60A	
	Output Power	0-9KW	
	Internal Sink Power ¹	0-450W	
	External Sink Power ¹	0-27KW	
Output Resistance	Range	0-27.77Ω	
	Accuracy ²	0.25%+200mΩ	

	Resolution	10mΩ
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+50mV
	Current	≤0.01%+30mA
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+100mV
	Current	≤0.05%+60mA
Setup Resolution	Voltage	100mV
	Current	10mA
	Power	0.1W
Read Back Resolution	Voltage	100mV
	Current	10mA
	Power	0.1W
Setup Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+200mV
	Current	≤0.2%+60mA
	Power	≤1%+90W
Read Back Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+200mV
	Current	≤0.2%+60mA
	Power	≤1%+90W
Ripple (20Hz -20MHz)	Voltage	≤500mVp-p
	Current	≤120mA _{rms}
Setup Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.03 %+100mV
	Current	≤0.1%+90mA
Read Back Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+90mA
Rise time(no load) ⁵	Voltage	≤40ms
Rise time(full load) ⁵	Voltage	≤70ms
Fall time(no load) ⁵	Voltage	≤100ms
Fall time(full load) ⁵	Voltage	≤25ms
Current seamless switching ⁶	-90%-90%	≤60ms
	90%--90%	≤60ms
Transient Response Time	Voltage	≤2ms
AC Input ⁷	Voltage	220V±10%
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+90mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+90mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+90mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+90mA
efficiency	90%(150V/60A)-93%(500V/18A)	
Remote Sense Compensation Voltage	5V	
Command Response Time	20mS	
Power Factor	0.99	
Maximum input current ⁸	19A	
Maximum input	11400VA	

apparent power	
Storage temperature	-10℃-70℃
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP, Vsense reversed protect
standard Interface	USB/RS232/CAN/GPIB/LAN
Isolation (output to ground)	500V
Parallel Number	≤8
Parallel Number of Power Dissipater	3/6/9
Working temperature	0-40℃
Dimension (mm)	483mmW×283.2mmH×640.8mmD
Weight(net)	53Kg

Parameter		IT6555C	Version: V1.4
Output Rating (0℃-40℃)	Output Voltage	0-500V	
	Output Current	0-80A	
	Internal Sink Current ¹	0-32A	
	External Sink Current ¹	0-80A	
	Output Power	0-12KW	
	Internal Sink Power ¹	0-600W	
	External Sink Power ¹	0-36KW	
Output Resistance	Range	0-20.83Ω	
	Accuracy ²	0.25%+200mΩ	
	Resolution	10mΩ	
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+50mV	
	Current	≤0.01%+40mA	
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+100mV	
	Current	≤0.05%+80mA	
Setup Resolution	Voltage	100mV	
	Current	10mA	
	Power	0.1W	
Read Back Resolution	Voltage	100mV	
	Current	10mA	
	Power	0.1W	
Setup Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+200mV	
	Current	≤0.2%+80mA	
	Power	≤1%+120W	
Read Back Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+200mV	
	Current	≤0.2%+80mA	
	Power	≤1%+120W	
Ripple (20Hz -20MHz)	Voltage	≤500mVp-p	
	Current	≤160mArms	
Setup Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.03 %+100mV	
	Current	≤0.1%+120mA	
Read Back Temperature	Voltage	≤0.03%+100mV	

Coefficient (%of Output/°C+Offset)	Current	≤0.1%+120mA
Rise time(no load) ⁵	Voltage	≤40ms
Rise time(full load) ⁵	Voltage	≤70ms
Fall time(no load) ⁵	Voltage	≤100ms
Fall time(full load) ⁵	Voltage	≤25ms
Current seamless switching ⁶	-90%-90%	≤80ms
	90%--90%	≤80ms
Transient Response Time	Voltage	≤2ms
AC Input ⁷	Voltage	380Vac±10%(Three-phase five wire)
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+120mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+120mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+120mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+120mA
efficiency	90%(150V/80A)-93%(500V/24A)	
Remote Sense Compensation Voltage	5V	
Command Response Time	20mS	
Power Factor	0.99	
Maximum input current ⁸	38A	
Maximum input apparent power	15200VA	
Storage temperature	-10℃-70℃	
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP, Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)	500V	
Parallel Number	≤8	
Parallel Number of Power Dissipater	4/8/12	
Working temperature	0-40℃	
Dimension (mm)	554mmW×902mmH×807.5mmD(ITECH 15U Cabinet)	
Weight(net)	119Kg	

Parameter		IT6565C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-500V	
	Output Current	0-100A	
	Internal Sink Current ¹	0-40A	
	External Sink Current ¹	0-100A	
	Output Power	0-15KW	
	Internal Sink Power ¹	0-750W	
	External Sink Power ¹	0-45KW	

Output Resistance	Range	0-16.667Ω
	Accuracy ²	0.25%+200mΩ
	Resolution	10mΩ
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+50mV
	Current	≤0.01%+50mA
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+100mV
	Current	≤0.05%+100mA
Setup Resolution	Voltage	100mV
	Current	10mA
	Power	0.1W
Read Back Resolution	Voltage	100mV
	Current	10mA
	Power	0.1W
Setup Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+200mV
	Current	≤0.2%+100mA
	Power	≤1%+150W
Read Back Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.03%+200mV
	Current	≤0.2%+100mA
	Power	≤1%+150W
Ripple (20Hz -20MHz)	Voltage	≤500mVp-p
	Current	≤200mA _{rms}
Setup Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.03 %+100mV
	Current	≤0.1%+150mA
Read Back Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+150mA
Rise time(no load) ⁵	Voltage	≤40ms
Rise time(full load) ⁵	Voltage	≤70ms
Fall time(no load) ⁵	Voltage	≤100ms
Fall time(full load) ⁵	Voltage	≤25ms
Current seamless switching ⁶	-90%-90%	≤100ms
	90%--90%	≤100ms
Transient Response Time	Voltage	≤2ms
AC Input ⁷	Voltage	380Vac±10%(Three-phase five wire)
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+150mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+150mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+150mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+150mA
efficiency	90%(150V/20A)-93%(500V/6A)	
Remote Sense Compensation Voltage	5V	
Command Response	20mS	

Time	
Power Factor	0.99
Maximum input current ⁸	38A
Maximum input apparent power	19000VA
Storage temperature	-10℃-70℃
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP, Vsense reversed protect
standard Interface	USB/RS232/CAN/GPIB/LAN
Isolation (output to ground)	500V
Parallel Number	≤8
Parallel Number of Power Dissipater	5/10/15
Working temperature	0-40℃
Dimension (mm)	554mmW×902mmH×807.5mmD(ITECH 15U Cabinet)
Weight(net)	137Kg

Parameter		IT6575C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-500V	
	Output Current	0-140A	
	Internal Sink Current ¹	0-56A	
	External Sink Current ¹	0-140A	
	Output Power	0-21KW	
	Internal Sink Power ¹	0-1050W	
	External Sink Power ¹	0-63KW	
Output Resistance	Range	0-11.90Ω	
	Accuracy ²	0.25%+200mΩ	
	Resolution	10mΩ	
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+50mV	
	Current	≤0.01%+70mA	
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+100mV	
	Current	≤0.05%+140mA	
Setup Resolution	Voltage	100mV	
	Current	10mA	
	Power	0.1W	
Read Back Resolution	Voltage	100mV	
	Current	10mA	
	Power	0.1W	
Setup Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+200mV	
	Current	≤0.2%+140mA	
	Power	≤1%+210W	
Read Back Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+200mV	
	Current	≤0.2%+140mA	
	Power	≤1%+210W	
Ripple (20Hz -20MHz)	Voltage	≤500mVp-p	
	Current	≤280mArms	

Setup Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.03 %+100mV
	Current	≤0.1%+210mA
Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+210mA
Rise time(no load) ⁵	Voltage	≤40ms
Rise time(full load) ⁵	Voltage	≤70ms
Fall time(no load) ⁵	Voltage	≤100ms
Fall time(full load) ⁵	Voltage	≤25ms
Current seamless switching ⁶	-90%-90%	≤140ms
	90%--90%	≤140ms
Transient Response Time	Voltage	≤2ms
AC Input ⁷	Voltage	380V±10%(Three-phase five wire)
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+210mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+210mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+210mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+210mA
efficiency	90%(150V/140A)-93%(500V/42A)	
Remote Sense Compensation Voltage	5V	
Command Response Time	20mS	
Power Factor	0.99	
Maximum input current ⁸	57A	
Maximum input apparent power	26600VA	
Storage temperature	-10℃-70℃	
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)	500V	
Parallel Number	≤8	
Parallel Number of Power Dissipater	7/14/21	
Working temperature	0-40℃	
Dimension (mm)	554mmW×902mmH×807.5mmD(ITECH 15U Cabinet)	
Weight(net)	180Kg	

Parameter		IT6585C	Version: V1.4
Output Rating (0 °C-40 °C)	Output Voltage	0-500V	
	Output Current	0-160A	
	Internal Sink Current ¹	0-64A	
	External Sink Current ¹	0-160A	
	Output Power	0-24KW	
	Internal Sink	0-1200W	

	Power ¹	
	External Sink Power ¹	0-72KW
Output Resistance	Range	0-10.417Ω
	Accuracy ²	0.25%+200mΩ
	Resolution	10mΩ
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+50mV
	Current	≤0.01%+80mA
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+100mV
	Current	≤0.05%+160mA
Setup Resolution	Voltage	100mV
	Current	10mA
	Power	0.1W
Read Back Resolution	Voltage	100mV
	Current	10mA
	Power	0.1W
Setup Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+200mV
	Current	≤0.2%+160mA
	Power	≤1%+240W
Read Back Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+200mV
	Current	≤0.2%+160mA
	Power	≤1%+240W
Ripple (20Hz -20MHz)	Voltage	≤500mVp-p
	Current	≤320mArms
Setup Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.03 %+100mV
	Current	≤0.1%+240mA
Read Back Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+240mA
Rise time(no load) ⁵	Voltage	≤40ms
Rise time(full load) ⁵	Voltage	≤70ms
Fall time(no load) ⁵	Voltage	≤100ms
Fall time(full load) ⁵	Voltage	≤25ms
Current seamless switching ⁶	-90%-90%	≤160ms
	90%--90%	≤160ms
Transient Response Time	Voltage	≤2ms
AC Input ⁷	Voltage	380V±10%(Three-phase five wire)
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+240mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+240mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+240mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+240mA
efficiency	90%(150V/160A)-93%(500V/48A)	
Remote Sense	5V	

Compensation Voltage	
Command Response Time	20mS
Power Factor	0.99
Maximum input current ⁸	57A
Maximum input apparent power	30400VA
Storage temperature	-10℃-70℃
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP, Vsense reversed protect
standard Interface	USB/RS232/CAN/GPIB/LAN
Isolation (output to ground)	500V
Parallel Number	≤8
Parallel Number of Power Dissipater	8/16/24
Working temperature	0-40℃
Dimension (mm)	550mmW×1289.3mmH×834.8mmD
Weight(net)	248Kg

Parameter		IT6595C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-500V	
	Output Current	0-200A	
	Internal Sink Current ¹	0-80A	
	External Sink Current ¹	0-200A	
	Output Power	0-30KW	
	Internal Sink Power ¹	0-1500W	
	External Sink Power ¹	0-90KW	
Output Resistance	Range	0-8.33Ω	
	Accuracy ²	0.25%+200mΩ	
	Resolution	10mΩ	
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+50mV	
	Current	≤0.01%+100mA	
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+100mV	
	Current	≤0.05%+200mA	
Setup Resolution	Voltage	100mV	
	Current	10mA	
	Power	0.1W	
Read Back Resolution	Voltage	100mV	
	Current	10mA	
	Power	0.1W	
Setup Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+200mV	
	Current	≤0.2%+200mA	
	Power	≤1%+300W	
Read Back Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+200mV	
	Current	≤0.2%+200mA	
	Power	≤1%+300W	
Ripple	Voltage	≤500mVp-p	

(20Hz -20MHz)	Current	≤400mArms
Setup Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.03 %+100mV
	Current	≤0.1%+300mA
Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+300mA
Rise time(no load) ⁵	Voltage	≤40ms
Rise time(full load) ⁵	Voltage	≤70ms
Fall time(no load) ⁵	Voltage	≤100ms
Fall time(full load) ⁵	Voltage	≤25ms
Current seamless switching ⁶	-90%-90%	≤200ms
	90%--90%	≤200ms
Transient Response Time	Voltage	≤2ms
AC Input ⁷	Voltage	380V±10%(Three-phase five wire)
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+300mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+300mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+300mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+300mA
efficiency	90%(150V/200A)-93%(500V/60A)	
Remote Sense Compensation Voltage	5V	
Command Response Time	20mS	
Power Factor	0.99	
Maximum input current ⁸	76A	
Maximum input apparent power	38000VA	
Storage temperature	-10℃-70℃	
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)	500V	
Parallel Number	≤8	
Parallel Number of Power Dissipater	10/20/30	
Working temperature	0-40℃	
Dimension (mm)	550mmW×1289.3mmH×834.8mmD	
Weight(net)	284Kg	

Parameter		IT6516C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-750V	
	Output Current	0-15A	
	Internal Sink Current ¹	0-5A	
	External Sink Current ¹	0-15A	
	Output Power	0-1800W	

	Internal Sink Power ¹	0-150W
	External Sink Power ¹	0-5.4KW
Output Resistance	Range	0-312.5Ω
	Accuracy ²	0.25%+300mΩ
	Resolution	10mΩ
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+75mV
	Current	≤0.1%+7.5mA
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+200mV
	Current	≤0.05%+15mA
Setup Resolution	Voltage	100mV
	Current	1mA
	Power	0.1W
Read Back Resolution	Voltage	100mV
	Current	1mA
	Power	0.1W
Setup Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+300mV
	Current	≤0.2%+15mA
	Power	≤1%+30W
Read Back Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+300mV
	Current	≤0.2%+15mA
	Power	≤1%+30W
Ripple (20Hz -20MHz)	Voltage	≤750mVp-p
	Current	≤30mA _{rms}
Setup Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.03 %+100mV
	Current	≤0.1%+30mA
Read Back Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+30mA
Rise time(no load) ⁵	Voltage	≤50ms
Rise time(full load) ⁵	Voltage	≤80ms
Fall time(no load) ⁵	Voltage	≤120ms
Fall time(full load) ⁵	Voltage	≤40ms
Current seamless switching ⁶	-90%-90%	≤35ms
	90%--90%	≤35ms
Transient Response Time	Voltage	≤3.5ms
AC Input ⁷	Voltage	220V±10%
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+30mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+30mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+30mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+30mA
efficiency	91.5%(200V/15A)-93.5%(750V/4A)	
Remote Sense Compensation Voltage	5V	

Command Response Time	20mS
Power Factor	0.99
Maximum input current ⁸	10A
Maximum input apparent power	2000VA
Storage temperature	-10℃-70℃
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect
standard Interface	USB/RS232/CAN/GPIB/LAN
Isolation (output to ground)	750V
Parallel Number	≤8
Parallel Number of Power Dissipater	1/2/3
Working temperature	0-40℃
Dimension (mm)	483mmW×105.4mmH×640.8mmD
Weight(net)	17Kg

Parameter		IT6526C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-750V	
	Output Current	0-15A	
	Internal Sink Current ¹	0-5A	
	External Sink Current ¹	0-15A	
	Output Power	0-3000W	
	Internal Sink Power ¹	0-150W	
	External Sink Power ¹	0-9KW	
Output Resistance	Range	0-188Ω	
	Accuracy ²	0.25%+300mΩ	
	Resolution	10mΩ	
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+75mV	
	Current	≤0.1%+7.5mA	
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+200mV	
	Current	≤0.05%+15mA	
Setup Resolution	Voltage	100mV	
	Current	1mA	
	Power	0.1W	
Read Back Resolution	Voltage	100mV	
	Current	1mA	
	Power	0.1W	
Setup Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+300mV	
	Current	≤0.2%+15mA	
	Power	≤1%+30W	
Read Back Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+300mV	
	Current	≤0.2%+15mA	
	Power	≤1%+30W	
Ripple (20Hz -20MHz)	Voltage	≤750mVp-p	
	Current	≤30mA _{rms}	
Setup Temperature	Voltage	≤0.03 %+100mV	

Coefficient (%of Output/°C+Offset)	Current	≤0.1%+30mA
Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+30mA
Rise time(no load) ⁵	Voltage	≤50ms
Rise time(full load) ⁵	Voltage	≤80ms
Fall time(no load) ⁵	Voltage	≤120ms
Fall time(full load) ⁵	Voltage	≤20ms
Current seamless switching ⁶	-90%-90%	≤35ms
	90%--90%	≤35ms
Transient Response Time	Voltage	≤3.5ms
AC Input ⁷	Voltage	220V±10%
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+30mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+30mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+30mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+30mA
efficiency	91.5%(200V/15A)-93.5%(750V/4A)	
Remote Sense Compensation Voltage	5V	
Command Response Time	20mS	
Power Factor	0.99	
Maximum input current ⁸	19A	
Maximum input apparent power	3800VA	
Storage temperature	-10℃-70℃	
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)	750V	
Parallel Number	≤8	
Parallel Number of Power Dissipater	1/2/3	
Working temperature	0-40℃	
Dimension (mm)	483mmW×105.4mmH×640.8mmD	
Weight(net)	17Kg	

Parameter		IT6536C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-750V	
	Output Current	0-30A	
	Internal Sink Current ¹	0-10A	
	External Sink Current ¹	0-30A	
	Output Power	0-6KW	
	Internal Sink Power ¹	0-300W	

	External Sink Power ¹	0-18KW
Output Resistance	Range	0-93.75Ω
	Accuracy ²	0.25%+300mΩ
	Resolution	10mΩ
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+75mV
	Current	≤0.1%+15mA
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+200mV
	Current	≤0.05%+30mA
Setup Resolution	Voltage	100mV
	Current	10mA
	Power	0.1W
Read Back Resolution	Voltage	100mV
	Current	10mA
	Power	0.1W
Setup Accuracy (within 12 months, 25°C ±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+300mV
	Current	≤0.2%+30mA
	Power	≤1%+60W
Read Back Accuracy (within 12 months, 25°C ±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+300mV
	Current	≤0.2%+30mA
	Power	≤1%+60W
Ripple (20Hz -20MHz)	Voltage	≤750mVp-p
	Current	≤60mArms
Setup Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.03 %+100mV
	Current	≤0.1%+60mA
Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+60mA
Rise time(no load) ⁵	Voltage	≤50ms
Rise time(full load) ⁵	Voltage	≤80ms
Fall time(no load) ⁵	Voltage	≤120ms
Fall time(full load) ⁵	Voltage	≤20ms
Current seamless switching ⁶	-90%-90%	≤70ms
	90%--90%	≤70ms
Transient Response Time	Voltage	≤3.5ms
AC Input ⁷	Voltage	220V±10%
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+60mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+60mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+60mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+60mA
efficiency	91.5%(200V/30A)-93.5%(750V/8A)	
Remote Sense Compensation Voltage	5V	
Command Response Time	20mS	

Power Factor	0.99
Maximum input current ⁸	38A
Maximum input apparent power	7600VA
Storage temperature	-10℃-70℃
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP, Vsense reversed protect
standard Interface	USB/RS232/CAN/GPIB/LAN
Isolation (output to ground)	750V
Parallel Number	≤8
Parallel Number of Power Dissipater	2/4/6
Working temperature	0-40℃
Dimension (mm)	483mmW×194mmH×640.8mmD
Weight(net)	35Kg

Parameter		IT6546C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-750V	
	Output Current	0-45A	
	Internal Sink Current ¹	0-15A	
	External Sink Current ¹	0-45A	
	Output Power	0-9KW	
	Internal Sink Power ¹	0-450W	
	External Sink Power ¹	0-27KW	
Output Resistance	Range	0-62.5Ω	
	Accuracy ²	0.25%+300mΩ	
	Resolution	10mΩ	
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+75mV	
	Current	≤0.1%+22.5mA	
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+200mV	
	Current	≤0.05%+45mA	
Setup Resolution	Voltage	100mV	
	Current	10mA	
	Power	0.1W	
Read Back Resolution	Voltage	100mV	
	Current	10mA	
	Power	0.1W	
Setup Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+300mV	
	Current	≤0.2%+45mA	
	Power	≤1%+90W	
Read Back Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+300mV	
	Current	≤0.2%+45mA	
	Power	≤1%+90W	
Ripple (20Hz -20MHz)	Voltage	≤750mVp-p	
	Current	≤90mArms	
Setup Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.03 %+100mV	
	Current	≤0.1%+90mA	

Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+90mA
Rise time(no load) ⁵	Voltage	≤50ms
Rise time(full load) ⁵	Voltage	≤80ms
Fall time(no load) ⁵	Voltage	≤120ms
Fall time(full load) ⁵	Voltage	≤20ms
Current seamless switching ⁶	-90%-90%	≤105ms
	90%--90%	≤105ms
Transient Response Time	Voltage	≤3.5ms
AC Input ⁷	Voltage	220V±10%
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+90mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+90mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+90mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+90mA
efficiency	91.5%(200V/45A)-93.5%(750V/12A)	
Remote Sense Compensation Voltage	5V	
Command Response Time	20mS	
Power Factor	0.99	
Maximum input current ⁸	19A	
Maximum input apparent power	11400VA	
Storage temperature	-10℃-70℃	
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP, Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)	750V	
Parallel Number	≤8	
Parallel Number of Power Dissipater	3/6/9	
Working temperature	0-40℃	
Dimension (mm)	483mmW×283.2mmH×640.8mmD	
Weight(net)	53Kg	

Parameter		IT6556C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-750V	
	Output Current	0-60A	
	Internal Sink Current ¹	0-20A	
	External Sink Current ¹	0-60A	
	Output Power	0-12KW	
	Internal Sink Power ¹	0-600W	
	External Sink Power ¹	0-36KW	

Output Resistance	Range	0-46.87Ω
	Accuracy ²	0.25%+300mΩ
	Resolution	10mΩ
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+75mV
	Current	≤0.1%+30mA
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+200mV
	Current	≤0.05%+60mA
Setup Resolution	Voltage	100mV
	Current	10mA
	Power	0.1W
Read Back Resolution	Voltage	100mV
	Current	10mA
	Power	0.1W
Setup Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+300mV
	Current	≤0.2%+60mA
	Power	≤1%+120W
Read Back Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+300mV
	Current	≤0.2%+60mA
	Power	≤1%+120W
Ripple (20Hz -20MHz)	Voltage	≤750mVp-p
	Current	≤120mArms
Setup Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.03 %+100mV
	Current	≤0.1%+120mA
Read Back Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+120mA
Rise time(no load) ⁵	Voltage	≤50ms
Rise time(full load) ⁵	Voltage	≤80ms
Fall time(no load) ⁵	Voltage	≤120ms
Fall time(full load) ⁵	Voltage	≤20ms
Current seamless switching ⁶	-90%-90%	≤140ms
	90%--90%	≤140ms
Transient Response Time	Voltage	≤3.5ms
AC Input ⁷	Voltage	380Vac±10%(Three-phase five wire)
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+120mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+120mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+120mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+120mA
efficiency	91.5%(200V/60A)-93.5%(750V/16A)	
Remote Sense Compensation Voltage	5V	
Command Response Time	20mS	
Power Factor	0.99	

Maximum input current ⁸	38A
Maximum input apparent power	15200VA
Storage temperature	-10℃-70℃
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP, Vsense reversed protect
standard Interface	USB/RS232/CAN/GPIB/LAN
Isolation (output to ground)	750V
Parallel Number	≤8
Parallel Number of Power Dissipater	4/8/12
Working temperature	0-40℃
Dimension (mm)	554mmW×902mmH×807.5mmD(ITECH 15U Cabinet)
Weight(net)	119Kg

Parameter		IT6566C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-750V	
	Output Current	0-75A	
	Internal Sink Current ¹	0-25A	
	External Sink Current ¹	0-75A	
	Output Power	0-15KW	
	Internal Sink Power ¹	0-750W	
	External Sink Power ¹	0-45KW	
Output Resistance	Range	0-37.5Ω	
	Accuracy ²	0.25%+300mΩ	
	Resolution	10mΩ	
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+75mV	
	Current	≤0.1%+37.5mA	
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+200mV	
	Current	≤0.05%+75mA	
Setup Resolution	Voltage	100mV	
	Current	10mA	
	Power	0.1W	
Read Back Resolution	Voltage	100mV	
	Current	10mA	
	Power	0.1W	
Setup Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+300mV	
	Current	≤0.2%+75mA	
	Power	≤1%+150W	
Read Back Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+300mV	
	Current	≤0.2%+75mA	
	Power	≤1%+150W	
Ripple (20Hz -20MHz)	Voltage	≤750mVp-p	
	Current	≤150mA _{rms}	
Setup Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.03 %+100mV	
	Current	≤0.1%+150mA	
Read Back Temperature	Voltage	≤0.03%+100mV	

Coefficient (%of Output/°C+Offset)	Current	≤0.1%+150mA
Rise time(no load) ⁵	Voltage	≤50ms
Rise time(full load) ⁵	Voltage	≤80ms
Fall time(no load) ⁵	Voltage	≤120ms
Fall time(full load) ⁵	Voltage	≤20ms
Current seamless switching ⁶	-90%-90%	≤175ms
	90%--90%	≤175ms
Transient Response Time	Voltage	≤3.5ms
AC Input ⁷	Voltage	380Vac±10%(Three-phase five wire)
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+150mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+150mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+150mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+150mA
efficiency	91.5%(200V/75A)-93.5%(750V/20A)	
Remote Sense Compensation Voltage	5V	
Command Response Time	20mS	
Power Factor	0.99	
Maximum input current ⁸	38A	
Maximum input apparent power	19000VA	
Storage temperature	-10℃-70℃	
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)	750V	
Parallel Number	≤8	
Parallel Number of Power Dissipater	5/10/15	
Working temperature	0-40℃	
Dimension (mm)	554mmW×902mmH×807.5mmD(ITECH 15U Cabinet)	
Weight(net)	137Kg	

Parameter		IT6576C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-750V	
	Output Current	0-105A	
	Internal Sink Current ¹	0-35A	
	External Sink Current ¹	0-105A	
	Output Power	0-21KW	
	Internal Sink Power ¹	0-1050W	
	External Sink Power ¹	0-63KW	

Output Resistance	Range	0-26.8Ω
	Accuracy ²	0.25%+300mΩ
	Resolution	10mΩ
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+75mV
	Current	≤0.1%+52.5mA
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+200mV
	Current	≤0.05%+105mA
Setup Resolution	Voltage	100mV
	Current	10mA
	Power	0.1W
Read Back Resolution	Voltage	100mV
	Current	10mA
	Power	0.1W
Setup Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+300mV
	Current	≤0.2%+105mA
	Power	≤1%+210W
Read Back Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+300mV
	Current	≤0.2%+105mA
	Power	≤1%+210W
Ripple (20Hz -20MHz)	Voltage	≤750mVp-p
	Current	≤210mArms
Setup Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.03 %+100mV
	Current	≤0.1%+210mA
Read Back Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+210mA
Rise time(no load) ⁵	Voltage	≤50ms
Rise time(full load) ⁵	Voltage	≤80ms
Fall time(no load) ⁵	Voltage	≤120ms
Fall time(full load) ⁵	Voltage	≤20ms
Current seamless switching ⁶	-90%-90%	≤245ms
	90%--90%	≤245ms
Transient Response Time	Voltage	≤3.5ms
AC Input ⁷	Voltage	380V±10%(Three-phase five wire)
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+210mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+210mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+210mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+210mA
efficiency	91.5%(200V/105A)-93.5%(750V/28A)	
Remote Sense Compensation Voltage	5V	
Command Response Time	20mS	
Power Factor	0.99	

Maximum input current ⁸	57A
Maximum input apparent power	26600VA
Storage temperature	-10℃-70℃
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP, Vsense reversed protect
standard Interface	USB/RS232/CAN/GPIB/LAN
Isolation (output to ground)	750V
Parallel Number	≤8
Parallel Number of Power Dissipater	7/14/21
Working temperature	0-40℃
Dimension (mm)	554mmW×902mmH×807.5mmD(ITECH 15U Cabinet)
Weight(net)	180Kg

Parameter		IT6586C	Version: V1.3
Output Rating (0 ℃-40 ℃)	Output Voltage	0-750V	
	Output Current	0-120A	
	Internal Sink Current ¹	0-40A	
	External Sink Current ¹	0-120A	
	Output Power	0-24KW	
	Internal Sink Power ¹	0-1200W	
	External Sink Power ¹	0-72KW	
Output Resistance	Range	0-23.4Ω	
	Accuracy ²	0.25%+300mΩ	
	Resolution	10mΩ	
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+75mV	
	Current	≤0.1%+60mA	
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+200mV	
	Current	≤0.05%+120mA	
Setup Resolution	Voltage	100mV	
	Current	10mA	
	Power	0.1W	
Read Back Resolution	Voltage	100mV	
	Current	10mA	
	Power	0.1W	
Setup Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+300mV	
	Current	≤0.2%+120mA	
	Power	≤1%+240W	
Read Back Accuracy (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+300mV	
	Current	≤0.2%+120mA	
	Power	≤1%+240W	
Ripple (20Hz -20MHz)	Voltage	≤750mVp-p	
	Current	≤240mArms	
Setup Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.03 %+100mV	
	Current	≤0.1%+240mA	

Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+240mA
Rise time(no load) ⁵	Voltage	≤50ms
Rise time(full load) ⁵	Voltage	≤80ms
Fall time(no load) ⁵	Voltage	≤120ms
Fall time(full load) ⁵	Voltage	≤20ms
Current seamless switching ⁶	-90%-90%	≤280ms
	90%--90%	≤280ms
Transient Response Time	Voltage	≤3.5ms
AC Input ⁷	Voltage	380V±10%(Three-phase five wire)
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+240mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+240mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+240mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+240mA
efficiency	91.5%(200V/120A)-93.5%(750V/32A)	
Remote Sense Compensation Voltage	5V	
Command Response Time	20mS	
Power Factor	0.99	
Maximum input current ⁸	57A	
Maximum input apparent power	30400VA	
Storage temperature	-10℃-70℃	
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)	750V	
Parallel Number	≤8	
Parallel Number of Power Dissipater	8/16/24	
Working temperature	0-40℃	
Dimension (mm)	550mmW×1289.3mmH×834.8mmD	
Weight(net)	248Kg	

Parameter		IT6596C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-750V	
	Output Current	0-150A	
	Internal Sink Current ¹	0-50A	
	External Sink Current ¹	0-150A	
	Output Power	0-30KW	
	Internal Sink Power ¹	0-1500W	
	External Sink	0-90KW	

	Power ¹	
Output Resistance	Range	0-18.75Ω
	Accuracy ²	0.25%+300mΩ
	Resolution	10mΩ
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+75mV
	Current	≤0.1%+75mA
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+200mV
	Current	≤0.05%+150mA
Setup Resolution	Voltage	100mV
	Current	10mA
	Power	0.1W
Read Back Resolution	Voltage	100mV
	Current	10mA
	Power	0.1W
Setup Accuracy (within 12 months, 25°C ±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+300mV
	Current	≤0.2%+150mA
	Power	≤1%+300W
Read Back Accuracy (within 12 months, 25°C ±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+300mV
	Current	≤0.2%+150mA
	Power	≤1%+300W
Ripple (20Hz -20MHz)	Voltage	≤750mVp-p
	Current	≤300mArms
Setup Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.03 %+100mV
	Current	≤0.1%+300mA
Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+300mA
Rise time(no load) ⁵	Voltage	≤50ms
Rise time(full load) ⁵	Voltage	≤80ms
Fall time(no load) ⁵	Voltage	≤120ms
Fall time(full load) ⁵	Voltage	≤20ms
Current seamless switching ⁶	-90%-90%	≤350ms
	90%--90%	≤350ms
Transient Response Time	Voltage	≤3.5ms
AC Input ⁷	Voltage	380V±10%(Three-phase five wire)
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+300mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+300mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+300mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.03%+100mV
	Current	≤0.1%+300mA
efficiency	91.5%(200V/150A)-93.5%(750V/40A)	
Remote Sense Compensation Voltage	5V	
Command Response Time	20mS	

Power Factor	0.99
Maximum input current ⁸	76A
Maximum input apparent power	38000VA
Storage temperature	-10℃-70℃
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP, Vsense reversed protect
standard Interface	USB/RS232/CAN/GPIB/LAN
Isolation (output to ground)	750V
Parallel Number	≤8
Parallel Number of Power Dissipater	10/20/30
Working temperature	0-40℃
Dimension (mm)	550mmW×1289.3mmH×834.8mmD
Weight(net)	284Kg

Parameter		IT6517C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-1000V	
	Output Current	0-10A	
	Internal Sink Current ¹	0-4.2A	
	External Sink Current ¹	0-10A	
	Output Power	0-1800W	
	Internal Sink Power ¹	0-150W	
	External Sink Power ¹	0-5.4KW	
Output Resistance	Range	0-555.555Ω	
	Accuracy ²	0.25% + 375mΩ*A	
	Resolution	10mΩ	
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+100mV	
	Current	≤0.01%+5mA	
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+375mV	
	Current	≤0.05%+10mA	
Setup Resolution	Voltage	100mV	
	Current	1mA	
	Power	0.1W	
Read Back Resolution	Voltage	100mV	
	Current	1mA	
	Power	0.1W	
Setup Accuracy ³ (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+375mV	
	Current	≤0.2%+10mA	
	Power	1%+30W	
Read Back Accuracy ⁴ (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+375mV	
	Current	≤0.2%+10mA	
	Power	1%+30W	
Ripple (20Hz -20MHz)	Voltage	≤1.5Vp-p	
	Current	≤0.05%+10mA _{rms}	
Setup Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.01%+375mV	
	Current	≤0.02%+10mA	
Read Back Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.01%+375mV	
	Current	≤0.02%+10mA	

Rise time(no load) ⁵	Voltage	≤70ms
Rise time(full load) ⁵	Voltage	≤100ms
Fall time(no load) ⁵	Voltage	≤170ms
Fall time(full load) ⁵	Voltage	≤60ms
Current seamless switching ⁶	-90%-90%	≤25ms
	90%--90%	≤25ms
Transient Response Time	Voltage	≤3ms
AC Input ⁷	Voltage	220V±10%
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+10mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+10mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+10mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+10mA
efficiency	80%	
Remote Sense Compensation Voltage	3V	
Command Response Time	20mS	
Power Factor	0.99	
Maximum input current ⁸	12A	
Maximum input apparent power	2300VA	
Storage temperature	-10℃-70℃	
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)	1000V	
Parallel Number	≤8	
Parallel Number of Power Dissipater	1/2/3	
Working temperature	0-40℃	
Dimension (mm)	483mmW×105.4mmH×640.8mmD	
Weight(net)	17Kg	

Parameter		IT6527C	Version: V1.3
Output Rating (0 ℃-40 ℃)	Output Voltage	0-1000V	
	Output Current	0-10A	
	Internal Sink Current ¹	0-4.2A	
	External Sink Current ¹	0-10A	
	Output Power	0-3000W	
	Internal Sink Power ¹	0-150W	
	External Sink Power ¹	0-9000W	
Output Resistance	Range	0-333.333Ω	
	Accuracy ²	0.25%+375mΩ*A	
	Resolution	10mΩ	
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+100mV	
	Current	≤0.01%+5mA	

Load regulation $\pm(\% \text{ of Output} + \text{Offset})$	Voltage	$\leq 0.01\% + 375\text{mV}$
	Current	$\leq 0.05\% + 10\text{mA}$
Setup Resolution	Voltage	100mV
	Current	1mA
	Power	0.1W
Read Back Resolution	Voltage	100mV
	Current	1mA
	Power	0.1W
Setup Accuracy ³ (within 12 months, 25°C ±5°C) $\pm(\% \text{ of Output} + \text{Offset})$	Voltage	$\leq 0.05\% + 375\text{mV}$
	Current	$\leq 0.2\% + 10\text{mA}$
	Power	1% + 30W
Read Back Accuracy ⁴ (within 12 months, 25°C ±5°C) $\pm(\% \text{ of Output} + \text{Offset})$	Voltage	$\leq 0.05\% + 375\text{mV}$
	Current	$\leq 0.2\% + 10\text{mA}$
	Power	1% + 30W
Ripple (20Hz -20MHz)	Voltage	$\leq 1.5\text{Vp-p}$
	Current	$\leq 0.05\% + 10\text{mA}_{\text{rms}}$
Setup Temperature Coefficient (% of Output/°C + Offset)	Voltage	$\leq 0.01\% + 375\text{mV}$
	Current	$\leq 0.02\% + 10\text{mA}$
Read Back Temperature Coefficient (% of Output/°C + Offset)	Voltage	$\leq 0.01\% + 375\text{mV}$
	Current	$\leq 0.02\% + 10\text{mA}$
Rise time(no load) ⁵	Voltage	$\leq 70\text{ms}$
Rise time(full load) ⁵	Voltage	$\leq 100\text{ms}$
Fall time(no load) ⁵	Voltage	$\leq 170\text{ms}$
Fall time(full load) ⁵	Voltage	$\leq 30\text{ms}$
Current seamless switching ⁶	-90%-90%	$\leq 25\text{ms}$
	90%--90%	$\leq 25\text{ms}$
Transient Response Time	Voltage	$\leq 3\text{ms}$
AC Input ⁷	Voltage	220V±10%
	Frequency	47Hz-63Hz
Setup stability-30min (% of Output + Offset)	Voltage	$\leq 0.05\% + 375\text{mV}$
	Current	$\leq 0.1\% + 10\text{mA}$
Setup stability-8h (% of Output + Offset)	Voltage	$\leq 0.05\% + 375\text{mV}$
	Current	$\leq 0.1\% + 10\text{mA}$
Readback stability-30min (% of Output + Offset)	Voltage	$\leq 0.05\% + 375\text{mV}$
	Current	$\leq 0.1\% + 10\text{mA}$
Readback stability-8h (% of Output + Offset)	Voltage	$\leq 0.05\% + 375\text{mV}$
	Current	$\leq 0.1\% + 10\text{mA}$
efficiency		80%
Remote Sense Compensation Voltage		3V
Command Response Time		20mS
Power Factor		0.99
Maximum input current ⁸		19A
Maximum input apparent power		3800VA
Storage temperature		-10°C -70°C
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP, Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)	1000V	

Parallel Number	≤8
Parallel Number of Power Dissipater	1/2/3
Working temperature	0-40℃
Dimension (mm)	483mmW×105.4mmH×640.8mmD
Weight(net)	17Kg

Parameter		IT6537C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-1000V	
	Output Current	0-20A	
	Internal Sink Current ¹	0-8.4A	
	External Sink Current ¹	0-20A	
	Output Power	0-6KW	
	Internal Sink Power ¹	0-300W	
	External Sink Power ¹	0-18KW	
Output Resistance	Range	0-166.666Ω	
	Accuracy ²	0.25%+375mΩ*A	
	Resolution	10mΩ	
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+100mV	
	Current	≤0.01%+10mA	
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+375mV	
	Current	≤0.05%+20mA	
Setup Resolution	Voltage	100mV	
	Current	1mA	
	Power	0.1W	
Read Back Resolution	Voltage	100mV	
	Current	1mA	
	Power	0.1W	
Setup Accuracy ³ (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+375mV	
	Current	≤0.2%+20mA	
	Power	1%+60W	
Read Back Accuracy ⁴ (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+375mV	
	Current	≤0.2%+20mA	
	Power	1%+60W	
Ripple (20Hz -20MHz)	Voltage	≤1.5Vp-p	
	Current	≤0.05%+20mA _{rms}	
Setup Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.01%+375mV	
	Current	≤0.02%+20mA	
Read Back Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.01%+375mV	
	Current	≤0.02%+20mA	
Rise time(no load) ⁵	Voltage	≤70ms	
Rise time(full load) ⁵	Voltage	≤100ms	
Fall time(no load) ⁵	Voltage	≤170ms	
Fall time(full load) ⁵	Voltage	≤30ms	
Current seamless switching ⁶	-90%-90%	≤50ms	
	90%--90%	≤50ms	
Transient Response Time	Voltage	≤3ms	

AC Input ⁷	Voltage	220V±10%
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+20mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+20mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+20mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+20mA
efficiency		80%
Remote Sense Compensation Voltage		3V
Command Response Time		20mS
Power Factor		0.99
Maximum input current ⁸		38A
Maximum input apparent power		7600VA
Storage temperature		-10℃-70℃
Protective function		Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect
standard Interface		USB/RS232/CAN/GPIB/LAN
Isolation (output to ground)		1000V
Parallel Number		≤8
Parallel Number of Power Dissipater		2/4/6
Working temperature		0-40℃
Dimension (mm)		483mmW×194mmH×640.8mmD
Weight(net)		35Kg

Parameter		IT6547C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-1000V	
	Output Current	0-30A	
	Internal Sink Current ¹	0-12.6A	
	External Sink Current ¹	0-30A	
	Output Power	0-9KW	
	Internal Sink Power ¹	0-450W	
	External Sink Power ¹	0-27KW	
Output Resistance	Range	0-111.111Ω	
	Accuracy ²	0.25% + 375mΩ*A	
	Resolution	10mΩ	
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+100mV	
	Current	≤0.01%+15mA	
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+375mV	
	Current	≤0.05%+30mA	
Setup Resolution	Voltage	100mV	
	Current	10mA	
	Power	0.1W	
Read Back Resolution	Voltage	100mV	
	Current	10mA	
	Power	0.1W	

Setup Accuracy ³ (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+375mV
	Current	≤0.2%+30mA
	Power	1%+90W
Read Back Accuracy ⁴ (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+375mV
	Current	≤0.2%+30mA
	Power	1%+90W
Ripple (20Hz -20MHz)	Voltage	≤1.5Vp-p
	Current	≤0.05%+30mA _{rms}
Setup Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.01%+375mV
	Current	≤0.02%+30mA
Read Back Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.01%+375mV
	Current	≤0.02%+30mA
Rise time(no load) ⁵	Voltage	≤70ms
Rise time(full load) ⁵	Voltage	≤100ms
Fall time(no load) ⁵	Voltage	≤170ms
Fall time(full load) ⁵	Voltage	≤30ms
Current seamless switching ⁶	-90%-90%	≤75ms
	90%--90%	≤75ms
Transient Response Time	Voltage	≤3ms
AC Input ⁷	Voltage	220V±10%
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+30mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+30mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+30mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+30mA
efficiency	80%	
Remote Sense Compensation Voltage	3V	
Command Response Time	20mS	
Power Factor	0.99	
Maximum input current ⁸	19A	
Maximum input apparent power	11400VA	
Storage temperature	-10℃-70℃	
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)	1000V	
Parallel Number	≤8	
Parallel Number of Power Dissipater	3/6/9	
Working temperature	0-40℃	
Dimension (mm)	483mmW×283.2mmH×640.8mmD	
Weight(net)	53Kg	

Output Rating (0 °C-40 °C)	Output Voltage	0-1000V
	Output Current	0-40A
	Internal Sink Current ¹	0-16.8A
	External Sink Current ¹	0-40A
	Output Power	0-12KW
	Internal Sink Power ¹	0-600W
	External Sink Power ¹	0-36KW
Output Resistance	Range	0-83.333Ω
	Accuracy ²	0.25%+375mΩ*A
	Resolution	10mΩ
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+100mV
	Current	≤0.01%+20mA
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+375mV
	Current	≤0.05%+40mA
Setup Resolution	Voltage	100mV
	Current	10mA
	Power	0.1W
Read Back Resolution	Voltage	100mV
	Current	10mA
	Power	0.1W
Setup Accuracy ³ (within 12 months, 25°C ±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+375mV
	Current	≤0.2%+40mA
	Power	1%+120W
Read Back Accuracy ⁴ (within 12 months, 25°C ±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+375mV
	Current	≤0.2%+40mA
	Power	1%+120W
Ripple (20Hz -20MHz)	Voltage	≤1.5Vp-p
	Current	≤0.05%+40mArms
Setup Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+375mV
	Current	≤0.02%+40mA
Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+375mV
	Current	≤0.02%+40mA
Rise time(no load) ⁵	Voltage	≤70ms
Rise time(full load) ⁵	Voltage	≤100ms
Fall time(no load) ⁵	Voltage	≤170ms
Fall time(full load) ⁵	Voltage	≤30ms
Current seamless switching ⁶	-90%-90%	≤100ms
	90%--90%	≤100ms
Transient Response Time	Voltage	≤3ms
AC Input ⁷	Voltage	380Vac±10%(Three-phase five wire)
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+40mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+40mA
Readback stability-30min	Voltage	≤0.05%+375mV
	Current	≤0.1%+40mA

(%of Output +Offset)		
Readback stability-8h (%of Output +Offset)	Voltage	$\leq 0.05\% + 375\text{mV}$
	Current	$\leq 0.1\% + 40\text{mA}$
efficiency		80%
Remote Sense Compensation Voltage		3V
Command Response Time		20mS
Power Factor		0.99
Maximum input current ⁸		38A
Maximum input apparent power		15200VA
Storage temperature		-10℃-70℃
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP, Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)		1000V
Parallel Number		≤ 8
Parallel Number of Power Dissipater		4/8/12
Working temperature		0-40℃
Dimension (mm)	554mmW×902mmH×807.5mmD(ITECH 15U Cabinet)	
Weight(net)		119Kg

Parameter		IT6567C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-1000V	
	Output Current	0-50A	
	Internal Sink Current ¹	0-21A	
	External Sink Current ¹	0-50A	
	Output Power	0-15KW	
	Internal Sink Power ¹	0-750W	
	External Sink Power ¹	0-45KW	
Output Resistance	Range	0-66.666Ω	
	Accuracy ²	0.25%+375mΩ*A	
	Resolution	10mΩ	
Line regulation ±(%of Output+Offset)	Voltage	$\leq 0.01\% + 100\text{mV}$	
	Current	$\leq 0.01\% + 25\text{mA}$	
Load regulation ±(%of Output+Offset)	Voltage	$\leq 0.01\% + 375\text{mV}$	
	Current	$\leq 0.05\% + 50\text{mA}$	
Setup Resolution	Voltage	100mV	
	Current	10mA	
	Power	0.1W	
Read Back Resolution	Voltage	100mV	
	Current	10mA	
	Power	0.1W	
Setup Accuracy ³ (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	$\leq 0.05\% + 375\text{mV}$	
	Current	$\leq 0.2\% + 50\text{mA}$	
	Power	1%+150W	
Read Back Accuracy ⁴ (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	$\leq 0.05\% + 375\text{mV}$	
	Current	$\leq 0.2\% + 50\text{mA}$	
	Power	1%+150W	

Ripple (20Hz -20MHz)	Voltage	≤1.5Vp-p
	Current	≤0.05%+50mArms
Setup Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+375mV
	Current	≤0.02%+50mA
Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+375mV
	Current	≤0.02%+50mA
Rise time(no load) ⁵	Voltage	≤70ms
Rise time(full load) ⁵	Voltage	≤100ms
Fall time(no load) ⁵	Voltage	≤170ms
Fall time(full load) ⁵	Voltage	≤30ms
Current seamless switching ⁶	-90%-90%	≤125ms
	90%--90%	≤125ms
Transient Response Time	Voltage	≤3ms
AC Input ⁷	Voltage	380Vac±10%(Three-phase five wire)
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+50mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+50mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+50mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+50mA
efficiency		80%
Remote Sense Compensation Voltage		3V
Command Response Time		20mS
Power Factor		0.99
Maximum input current ⁸		38A
Maximum input apparent power		19000VA
Storage temperature		-10℃-70℃
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)		1000V
Parallel Number		≤8
Parallel Number of Power Dissipater		5/10/15
Working temperature		0-40℃
Dimension (mm)	554mmW×902mmH×807.5mmD(ITECH 15U Cabinet)	
Weight(net)	137Kg	

Parameter		IT6577C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-1000V	
	Output Current	0-70A	
	Internal Sink Current ¹	0-29.4A	
	External Sink Current ¹	0-70A	

	Output Power	0-21KW
	Internal Sink Power ¹	0-1050W
	External Sink Power ¹	0-63KW
Output Resistance	Range	0-47.622Ω
	Accuracy ²	0.25% + 375mΩ*A
	Resolution	10mΩ
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+100mV
	Current	≤0.01%+35mA
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+375mV
	Current	≤0.05%+70mA
Setup Resolution	Voltage	100mV
	Current	10mA
	Power	0.1W
Read Back Resolution	Voltage	100mV
	Current	10mA
	Power	0.1W
Setup Accuracy ³ (within 12 months, 25°C ±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+375mV
	Current	≤0.2%+70mA
	Power	1%+210W
Read Back Accuracy ⁴ (within 12 months, 25°C ±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+375mV
	Current	≤0.2%+70mA
	Power	1%+210W
Ripple (20Hz -20MHz)	Voltage	≤1.5Vp-p
	Current	≤0.05%+70mArms
Setup Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+375mV
	Current	≤0.02%+70mA
Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+375mV
	Current	≤0.02%+70mA
Rise time(no load) ⁵	Voltage	≤70ms
Rise time(full load) ⁵	Voltage	≤100ms
Fall time(no load) ⁵	Voltage	≤170ms
Fall time(full load) ⁵	Voltage	≤30ms
Current seamless switching ⁶	-90%-90%	≤175ms
	90%--90%	≤175ms
Transient Response Time	Voltage	≤3ms
AC Input ⁷	Voltage	380Vac±10%(Three-phase five wire)
	Frequency	
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+70mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+70mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+70mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+70mA
efficiency		80%
Remote Sense Compensation Voltage		3V

Command Response Time	20mS
Power Factor	0.99
Maximum input current ⁸	57A
Maximum input apparent power	26600VA
Storage temperature	-10℃-70℃
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect
standard Interface	USB/RS232/CAN/GPIB/LAN
Isolation (output to ground)	1000V
Parallel Number	≤8
Parallel Number of Power Dissipater	7/14/21
Working temperature	0-40℃
Dimension (mm)	554mmW×902mmH×807.5mmD(ITECH 15UCabinet)
Weight(net)	180Kg

Parameter		IT6587C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-1000V	
	Output Current	0-80A	
	Internal Sink Current ¹	0-33.6A	
	External Sink Current ¹	0-80A	
	Output Power	0-24KW	
	Internal Sink Power ¹	0-1200W	
	External Sink Power ¹	0-72KW	
Output Resistance	Range	0-41.666Ω	
	Accuracy ²	0.25%+375mΩ*A	
	Resolution	10mΩ	
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+100mV	
	Current	≤0.01%+40mA	
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+375mV	
	Current	≤0.05%+80mA	
Setup Resolution	Voltage	100mV	
	Current	10mA	
	Power	0.1W	
Read Back Resolution	Voltage	100mV	
	Current	10mA	
	Power	0.1W	
Setup Accuracy ³ (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+375mV	
	Current	≤0.2%+80mA	
	Power	1%+240W	
Read Back Accuracy ⁴ (within 12 months, 25℃ ±5℃) ±(%of Output+Offset)	Voltage	≤0.05%+375mV	
	Current	≤0.2%+80mA	
	Power	1%+240W	
Ripple (20Hz -20MHz)	Voltage	≤1.5Vp-p	
	Current	≤0.05%+80mArms	
Setup Temperature Coefficient (%of Output/℃+Offset)	Voltage	≤0.01%+375mV	
	Current	≤0.02%+80mA	

Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+375mV
	Current	≤0.02%+80mA
Rise time(no load) ⁵	Voltage	≤70ms
Rise time(full load) ⁵	Voltage	≤100ms
Fall time(no load) ⁵	Voltage	≤170ms
Fall time(full load) ⁵	Voltage	≤30ms
Current seamless switching ⁶	-90%-90%	≤200ms
	90%--90%	≤200ms
Transient Response Time	Voltage	≤3ms
AC Input ⁷	Voltage	380Vac±10%(Three-phase five wire)
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+80mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+80mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+80mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+80mA
efficiency	80%	
Remote Sense Compensation Voltage	3V	
Command Response Time	20mS	
Power Factor	0.99	
Maximum input current ⁸	57A	
Maximum input apparent power	30400VA	
Storage temperature	-10℃-70℃	
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect	
standard Interface	USB/RS232/CAN/GPIB/LAN	
Isolation (output to ground)	1000V	
Parallel Number	≤8	
Parallel Number of Power Dissipater	8/16/24	
Working temperature	0-40℃	
Dimension (mm)	550mmW×1289.3mmH×834.8mmD	
Weight(net)	248Kg	

Parameter		IT6597C	Version: V1.4
Output Rating (0 ℃-40 ℃)	Output Voltage	0-1000V	
	Output Current	0-100A	
	Internal Sink Current ¹	0-42A	
	External Sink Current ¹	0-100A	
	Output Power	0-30KW	
	Internal Sink Power ¹	0-1500W	
	External Sink Power ¹	0-90KW	
Output Resistance	Range	0-33.333Ω	

	Accuracy ²	0.25%+375mΩ*A
	Resolution	10mΩ
Line regulation ±(%of Output+Offset)	Voltage	≤0.01%+100mV
	Current	≤0.01%+50mA
Load regulation ±(%of Output+Offset)	Voltage	≤0.01%+375mV
	Current	≤0.05%+100mA
Setup Resolution	Voltage	100mV
	Current	10mA
	Power	0.1W
Read Back Resolution	Voltage	100mV
	Current	10mA
	Power	0.1W
Setup Accuracy ³ (within 12 months, 25°C ±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+375mV
	Current	≤0.2%+100mA
	Power	1%+300W
Read Back Accuracy ⁴ (within 12 months, 25°C ±5°C) ±(%of Output+Offset)	Voltage	≤0.05%+375mV
	Current	≤0.2%+100mA
	Power	1%+300W
Ripple (20Hz -20MHz)	Voltage	≤1.5Vp-p
	Current	≤0.05%+100mArms
Setup Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+375mV
	Current	≤0.02%+100mA
Read Back Temperature Coefficient (%of Output/°C+Offset)	Voltage	≤0.01%+375mV
	Current	≤0.02%+100mA
Rise time(no load) ⁵	Voltage	≤70ms
Rise time(full load) ⁵	Voltage	≤100ms
Fall time(no load) ⁵	Voltage	≤170ms
Fall time(full load) ⁵	Voltage	≤30ms
Current seamless switching ⁶	-90%-90%	≤250ms
	90%--90%	≤250ms
Transient Response Time	Voltage	≤3ms
AC Input ⁷	Voltage	380Vac±10%(Three-phase five wire)
	Frequency	47Hz-63Hz
Setup stability-30min (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+100mA
Setup stability-8h (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+100mA
Readback stability-30min (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+100mA
Readback stability-8h (%of Output +Offset)	Voltage	≤0.05%+375mV
	Current	≤0.1%+100mA
efficiency		80%
Remote Sense Compensation Voltage		3V
Command Response Time		20mS
Power Factor		0.99
Maximum input current ⁸		76A
Maximum input apparent power		38000VA

Storage temperature	-10℃-70℃
Protective function	Source OVP, OCP, OPP and Load OCP, OPP, OTP,Vsense reversed protect
standard Interface	USB/RS232/CAN/GPIB/LAN
Isolation (output to ground)	1000V
Parallel Number	≤8
Parallel Number of Power Dissipater	10/20/30
Working temperature	0-40℃
Dimension (mm)	550mmW×1289.3mmH×834.8mmD
Weight(net)	284Kg

The above specifications may be subject to change without prior notice.

1. Internal absorption current and internal absorption power mean the absorption current and power of the standard power dissipater inside the power supply; and external absorption current and external absorption power mean the absorption current and power of the optional power dissipater outside the power supply.
2. Resistance programming accuracy differs based on different output current. For example, 10A Transient 1.0Ω, accuracy: $(1.0\Omega * 0.25\%) + (375m\Omega * A / 10A) = 40m\Omega$.
3. Set value accuracy means the set accuracy realized through the panel button or communication instructions. When external analog is used for programming, the programming accuracy is 1%.
4. Read-back value accuracy means the read-back accuracy realized through panel display or communication instructions; when external analog is used for monitoring, the monitoring accuracy is 1%.
5. Up time and down time mean the time of establishment from one value to another value under ON status when the internal standard power dissipater is enabled.
6. Use 12V/120AH battery for test.
7. When used in parallel, to balance power of each phase, distribute the instrument to three phases. But must ensure that single machine input voltage meets Specification requirements.
8. It means the maximum phase current value under minimum work input voltage.

5.2 Supplemental characteristics

- State storage capacity
100 sets
- Recommended calibration frequency
once a year
- Cooling style
fans

Appendix

Specifications of Red and Black Test Lines

ITECH provides you with optional red and black test lines, which individual sales and you can select for test. For specifications of ITECH test lines and maximum current values, refer to the table below.

Model	Specification	Cross section	Length
IT-E301/10A	10A	-	1m
IT-E301/30A	30A	6mm ²	1.2m
IT-E301/30A	30A	6mm ²	2m
IT-E301/60A	60A	20mm ²	1.5m
IT-E301/120A	120A	50mm ²	2m
IT-E301/240A	240A	70mm ²	1m
IT-E301/240A	240A	70mm ²	2m
IT-E301/360A	360A	95mm ²	2m

For maximum current of AWG copper wire, refer to table below.


AWG	10	12	14	16	18	20	22	24	26	28
The Maximum current value(A)	40	25	20	13	10	7	5	3.5	2.5	1.7

Note: AWG (American Wire Gage), it means X wire (marked on the wire). The table above lists current capacity of single wire at working temperature of 30°C. For reference only.

How to avoid it couldn't start when test battery

When test battery, the main reason of no start is that battery (residual voltage) discharges capacitors of positive and negative terminals of the power supply.

Method to avoid no start: connect a switch which is parallel with a current limiting discharging resistor. Close the switch after all the all leads connected well. The wiring diagram as follows:



Contact US

Thank you for purchasing ITECH products. If you have any doubt about this product, please contact us as follow.

1. Please refer to the CD-ROM of related user's manual in package.
2. Visit ITECH website www.itechate.com .
3. Select the most convenient contact for further consultation.